





M26L - PUNK 39 93045 DIM5

REFERENCE

23245 9315 B

AVAILABLE IN

BLACK 23245 9315 B



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.2
ADJUSTABILITY	0° to 85° swiveling, 350° rotatable
INFORMATION	REFLECTOR WFL-45° EXCL.LED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	DALI
ENERGY CLASS	D
CERTIFICATES	CB, EAC, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8W / CRI>90 (R9: 52) / 3000K / 787lm
TM-30 VALUES	Rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	45°
LED TECHNICS (LIGHT SOURCE)	787lm // 5,8W // 135lm/W
LED TECHNICS (LUMINAIRE)	530lm // 6,7W // 79lm/W

Remarks

[Take a look at our MAGNETIC PROFILES movie](#)

Requirements

LED POWER SUPPLY 48V-DC

For detailed installation instructions, please consult the manual : [23245_XXXX_HAND.pdf](#)

FINISH YOUR SPECIFICATION


LED power supplies

of Fixtures



of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




300 89 48 90 LED POWER SUPPLY 48V-DC / 90W

10

Dimtype: non-dimmable


Cutout dimension (mm): 75



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN

12


Dimtype: non-dimmable



300 89 48 150 LED POWER SUPPLY 48V-DC / 150W

17


Dimtype: non-dimmable



300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN

29

Dimtype: non-dimmable




21012 0230 LED POWER SUPPLY 48V-DC / 100W

12

Dimtype: non-dimmable

Cutout dimension (mm): 40



21012 0240 LED POWER SUPPLY 48V-DC / 200W

24

Dimtype: non-dimmable

Cutout dimension (mm): 40

Power box

of Fixtures





of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current





DELTALIGHT


M26L - PUNK 39 93045 DIM5

23245 9315 B

	23377 0010 B SLM26L - POWERBOX 48V-DC / 96W B	12 ☐
Dimtype: non-dimmable		
	23377 0010 W SLM26L - POWERBOX 48V-DC / 96W W	12 ☐
	23377 0020 B SLM26L - MID POWERBOX 48V-DC / 96W B	12 ☐
Dimtype: non-dimmable		
	23377 0020 W SLM26L - MID POWERBOX 48V-DC / 96W W	12 ☐

COMPATIBLE COMPOSABLES


SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)	Available Colours
	23358 0000 SLM26L - PROFILE 
	23358 0010 SLM26L - PROFILE 1m 
	23358 0020 SLM26L - PROFILE 2m 
	23358 0030 SLM26L - PROFILE 3m 

SHIFTLINE M35R profile	Available Colours
	23375 0000 SLM35R - PROFILE 


DELTALIGHT

M26L - PUNK 39 93045 DIM5


23245 9315 B



23375 0010 SLM35R - PROFILE 1m



23375 0020 SLM35R - PROFILE 2m



23375 0030 SLM35R - PROFILE 3m



Notes: