





M26L - HALOSCAN HP 92714 MDL

23129 9210 W

AVAILABLE IN
BLACK 23129 9210 B
WHITE 23129 9210 W



[View on website](#)



General info	
LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.3
ADJUSTABILITY	0° to 45° swiveling, 355° rotatable
INFORMATION	LENS SP-14° EXCL.LED POWER SUPPLY 48V-DC
Electrical info	
ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	D
CERTIFICATES	CB, ENEC
Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 11,6W / CRI>90 (R9: 60) / 2700K / 1458lm
TM-30 VALUES	rf: 89 / Rg: 100
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	14°
LED TECHNICS (LIGHT SOURCE)	1458lm // 11,6W // 125lm/W
LED TECHNICS (LUMINAIRE)	1185lm // 13,3W // 89lm/W

Remarks

Take a look at our [MAGNETIC PROFILES](#) movie

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

Accessories

HALOSCAN HONEYCOMB
 HALOSCAN LINEAR SPREAD LENS

M26L - HALOSCAN HP 92714 MDL

23129 9210 W

For detailed installation instructions, please consult the manual : [23129_XXX0_HAND.pdf](#)


FINISH YOUR SPECIFICATION

Current supply

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



21032 0030 SMART 48 MODULATOR PLUG-IN WD

14


Dimtype: WDL = wireless dimmable

SMART 48

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


Min current | Max current



300 90 011 SMART 48 MODULATOR DIM9

14

Dimtype: 1-10V or DALI or push button



300 90 012 SMART 48 MODULATOR WD

14


Dimtype: WDL = wireless dimmable

LED power supplies

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN




7

Dimtype: non-dimmable



DELTALIGHT

M26L - HALOSCAN HP 92714 MDL




23129 9210 W

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	17	☐
Dimtype: non-dimmable			
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	7	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	14	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			

Light altering devices

	23110 0040 HALOSCAN LINEAR SPREAD LENS	☐
	23110 0050 B HALOSCAN HONEYCOMB B	☐


COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)	Available Colours
	 
	 
	         

DELTALIGHT

M26L - HALOSCAN HP 92714 MDL

23129 9210 W




23358 0030 SLM26L - PROFILE 3m




SHIFTLINE M35R profile


Available Colours




23375 0000 SLM35R - PROFILE



23375 0010 SLM35R - PROFILE 1m



23375 0020 SLM35R - PROFILE 2m



23375 0030 SLM35R - PROFILE 3m



Notes: