



## M26L - SPY 391 SOFT 93020 MDL

23437 9020 BROB

AVAILABLE IN

**NEGRO** 23437 9020 B

**ALU CEPILLADO** 23437 9020 BRA

**ANTRACITA CEPILLADO** 23437 9020 BRAT

**COBRE CEPILLADO** 23437 9020 BRCU

**ORO CEPILLADO** 23437 9020 BRG

**BRONCE VIEJO CEPILLADO** 23437 9020 BROB



**FLEMISH BRONZE** 23437 9020 FBR

**FLEMISH GOLD** 23437 9020 FG

**ORO COLOREADO** 23437 9020 GC

**NEGRO PIANO** 23437 9020 PB

**BLANCO** 23437 9020 W



[View on website](#)



### General info

|                           |                                                              |
|---------------------------|--------------------------------------------------------------|
| <b>LOCATION</b>           | interior                                                     |
| <b>INSTALLATION</b>       | Sistemas de baja tensión Montado en sistemas de baja tensión |
| <b>INGRESS PROTECTION</b> | IP20                                                         |
| <b>WEIGHT (KG)</b>        | 0.3                                                          |
| <b>ADJUSTABILITY</b>      | 0° to 85° giratorio, 360° orientable                         |
| <b>INFORMATION</b>        | REFLECTOR FL-20°<br>EXCL.LED POWER SUPPLY 48V-DC             |

### Electrical info

|                      |                                           |
|----------------------|-------------------------------------------|
| <b>ELECTRICAL</b>    | 48V-DC                                    |
| <b>CLASS</b>         | III                                       |
| <b>DIM TYPE</b>      | MDL = 1 a 10 v o DALI o SWITCH DE PRESION |
| <b>ENERGY CLASS</b>  | F                                         |
| <b>CERTIFICATION</b> | EPD                                       |

### Lightsource info

|                                    |                                                      |
|------------------------------------|------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                  |
| <b>LIGHTSOURCE</b>                 | LED array 6W / CRI>90 (R9: 50) / 3000K-1800K / 623lm |
| <b>RVALUES</b>                     | rf: 90 / Rg: 99                                      |
| <b>SDMC</b>                        | SDCM2                                                |
| <b>RISKGROUP</b>                   | RG1                                                  |
| <b>LM80</b>                        | L90B10 > 50000                                       |
| <b>BEAMANGLE</b>                   | 20°                                                  |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 623lm // 6W // 105lm/W                               |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 508lm // 6,9W // 74lm/W                              |

### Requirements






SPY 39 TUBE  
LED POWER SUPPLY 48V-DC

### Options

DIMMABLE MODULATOR



For detailed installation instructions, please consult the manual : [23437\\_XXX0\\_HAND.pdf](#)

FINISH YOUR SPECIFICATION


| Cable de alimentación                                                                                                                                                                    |                         | # of Fixtures             |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------|---------------------------|
| <div><div></div><div>web2print_power_supply_info_box</div></div>                                        |                         | Min current   Max current |
| <div><div></div><div><div>21032 0030</div><div>SMART 48 MODULATOR PLUG-IN WD</div></div></div>           | 16 <input type="text"/> |                           |
| Dimtype: WDL = Regulable inalámbrico                                                                                                                                                     |                         |                           |
| SMART 48                                                                                                                                                                                 |                         | # of Fixtures             |
| <div><div></div><div>web2print_power_supply_info_box</div></div>                                      |                         | Min current   Max current |
| <div><div></div><div><div>300 90 011</div><div>SMART 48 MODULATOR DIM9</div></div></div>               | 16 <input type="text"/> |                           |
| Dimtype: 1 a 10 V o DALI o switch de presion                                                                                                                                             |                         |                           |
| <div><div></div><div><div>300 90 012</div><div>SMART 48 MODULATOR WD</div></div></div>                 | 16 <input type="text"/> |                           |
| Dimtype: WDL = Regulable inalámbrico                                                                                                                                                     |                         |                           |
| Fuente de Alimentación LED                                                                                                                                                               |                         | # of Fixtures             |
| <div><div></div><div>web2print_power_supply_info_box</div></div>                                      |                         | Min current   Max current |
| <div><div></div><div><div>300 89 48 100</div><div>LED POWER SUPPLY 48V-DC / 100W DIN</div></div></div> | 8 <input type="text"/>  |                           |
| Dimtype: no dimerizable                                                                                                                                                                  |                         |                           |
| <div><div></div><div><div>300 89 48 240</div><div>LED POWER SUPPLY 48V-DC / 240W DIN</div></div></div> | 20 <input type="text"/> |                           |
| Dimtype: no dimerizable                                                                                                                                                                  |                         |                           |

M26L - SPY 391 SOFT 93020 MDL



23437 9020 BROB

|                                                                                  |                           |                                |    |                          |
|----------------------------------------------------------------------------------|---------------------------|--------------------------------|----|--------------------------|
|  | <b>21012 0230</b>         | LED POWER SUPPLY 48V-DC / 100W | 8  | <input type="checkbox"/> |
|                                                                                  | Dimtype: no dimerizable   |                                |    |                          |
|                                                                                  | Cutout dimension (mm): 40 |                                |    |                          |
|  | <b>21012 0240</b>         | LED POWER SUPPLY 48V-DC / 200W | 17 | <input type="checkbox"/> |
|                                                                                  | Dimtype: no dimerizable   |                                |    |                          |
|                                                                                  | Cutout dimension (mm): 40 |                                |    |                          |

Termina tu producto

|                                                                                  |                                                                                     |                                   |                          |
|----------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-----------------------------------|--------------------------|
|  | <b>24144 0010 B</b>                                                                 | SPY 39 TUBE B                     | <input type="checkbox"/> |
|                                                                                  | <b>24144 0010 FBR</b>                                                               | SPY 39 TUBE FBR                   | <input type="checkbox"/> |
|                                                                                  | <b>24144 0010 FG</b>                                                                | SPY 39 TUBE FG                    | <input type="checkbox"/> |
|                                                                                  | <b>24144 0010 GC</b>                                                                | SPY 39 TUBE GC                    | <input type="checkbox"/> |
|                                                                                  | <b>24144 0010 W</b>                                                                 | SPY 39 TUBE W                     | <input type="checkbox"/> |
|                                                                                  |  | <b>24144 0070</b> SPY 39 TUBE SBL | <input type="checkbox"/> |


COMPATIBLE COMPOSABLES

| SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)                                    |                                       | Available Colours                                                                                                                                                           |
|-------------------------------------------------------------------------------------|---------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|  | <b>23358 0000</b> SLM26L - PROFILE    |   |
|                                                                                     |                                       |                                                                                                                                                                             |
|  | <b>23358 0010</b> SLM26L - PROFILE 1m |   |
|                                                                                     |                                       |                                                                                                                                                                             |


# DELTALIGHT

## M26L - SPY 391 SOFT 93020 MDL

23437 9020 BROB



**23358 0020** SLM26L - PROFILE 2m



**23358 0030** SLM26L - PROFILE 3m



Notes: