

DELTALIGHT



MILES C2 AMBER 92750

REFERENCE 23933 9230





View on website

General info	
LOCATION	indoor
INSTALLATION	Ceiling Suspended
INGRESS PROTECTION	IP20
WEIGHT (KG)	1.3
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR WFL-50° INCL.1 x CABLE 2 x 0.75mm² 1,6m INCL.1 x CABLE CLAMP BLACK EXCL.LED POWER SUPPLY 350mA-DC

Electrical info	
CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	D
CERTIFICATES	CB, EAC, ENEC

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8W / CRI>90 (R9: 60) / 2700K / 753lm
TM-30 VALUES	Rf: 89 / Rg: 100
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	50°
LED TECHNICS (LIGHT SOURCE)	753lm // 5,8W // 129lm/W
LED TECHNICS (LUMINAIRE)	569lm // 6,7W // 85lm/W

Requirements

LED POWER SUPPLY 350mA-DC DIM
MILES POWERBOX 350mA DIM8

Options

CONNECTION TRIMLESS
CEILING BASE R
MILES CEILING BASE 3L / 3R

Accessories

MILES TUBE








DELTALIGHT

MILES C2 AMBER 92750

23933 9230

For detailed installation instructions, please consult the manual : **23933_9230_HAND.pdf**


FINISH YOUR SPECIFICATION

LED power supplies		# of Fixtures Min current | Max current
ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		
	**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 **Dimtype: 1-10V** **Cutout dimension (mm): 30**	1 ☐
	**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 **Dimtype: DALI** **Cutout dimension (mm): 45**	1 ☐
	**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL **Dimtype: non-dimmable** **Cutout dimension (mm): 30**	1 ☐
	**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL **Dimtype: WDL = wireless dimmable** **Cutout dimension (mm): 45**	1 ☐
	**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6 **Dimtype: mains (phase cut-off) or push button** **Cutout dimension (mm): 56**	2 ☐
	**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9 **Dimtype: 1-10V or DALI or push button** **Cutout dimension (mm): 82**	4(4) ☐
	**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7 **Dimtype: 1-10V or push button** **Cutout dimension (mm): 72**	2(1) ☐

DELTALIGHT


MILES C2 AMBER 92750

23933 9230



300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 — 2


Dimtype: 1-10V or DALI or push button



300 90 68 LED POWER SUPPLY MULTI-POWER DIM5 — 2(2)

Dimtype: DALI


Cutout dimension (mm): 72



300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9 — 2->6(6)

Dimtype: 1-10V or DALI or push button


Cutout dimension (mm): 84



300 90 124 LED POWER SUPPLY MULTI-POWER DIM7 — 3(2)

Dimtype: 1-10V or push button


Cutout dimension (mm): 55



300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5 — 2(2)

Dimtype: DALI


Cutout dimension (mm): 55



300 90 135 LED POWER SUPPLY MULTI-POWER HV — 3->3

Dimtype: non-dimmable


Cutout dimension (mm): 90



21012 0010 LED POWER SUPPLY MULTI POWER — 2

Dimtype: non-dimmable


Cutout dimension (mm): 50



21012 0021 LED POWER SUPPLY MULTI POWER DIM1 — 3

Dimtype: 1-10V


Cutout dimension (mm): 54



21012 0035 LED POWER SUPPLY MULTI POWER DIM5 — 3

Dimtype: DALI

Cutout dimension (mm): 54



21012 004W LED POWER SUPPLY MULTI-POWER WDL — 3(3)


Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 84

DELTALIGHT

MILES C2 AMBER 92750


23933 9230



21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL — 3

Dimtype: WDL = wireless dimmable


Cutout dimension (mm): 54



21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8 — 1

Dimtype: mains (phase cut-off)


Cutout dimension (mm): 50



21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 — 2

Dimtype: mains (phase cut-off)


Cutout dimension (mm): 48



21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68 — 2(2)

Dimtype: non-dimmable

Cutout dimension (mm): 60



21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 2

Dimtype: DALI


Cutout dimension (mm): 30

Power box

of Fixtures

Min current | Max current


ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



23942 0018 B MILES POWERBOX 350 mA DIM8 B — 1

Dimtype: mains (phase cut-off)

Electric connection parts



328 10 03 CONNECTION TRIMLESS O.F.A.


Cutout dimension (mm): 62 (CONCRETE: 102)

DELTALIGHT

MILES C2 AMBER 92750

23933 9230


Decorative ornaments




23944 0010 B MILES TUBE B ☐

23944 0010 M MILES TUBE M ☐


Ceiling bases



23943 0010 B CEILING BASE R B ☐



23945 0010 B CEILING BASE 3L B ☐



23945 0020 B CEILING BASE 3R B ☐

Notes: