



## SPY 39 PLUG WALLWASH 930

24177 9300 FG

AVAILABLE IN

**NOIR** 24177 9300 B

**ALU BROSSÉ** 24177 9300 BRA

**ANTHRACITE BROSSÉ** 24177 9300 BRAT

**CUIVRE BROSSÉ** 24177 9300 BRCU

**OR BROSSÉ** 24177 9300 BRG

**BRONZE VIEUX BROSSÉ** 24177 9300 BROB


**FLEMISH BRONZE** 24177 9300 FBR

**FLEMISH GOLD** 24177 9300 FG

**ENTIÈREMENT BLANC** 24177 9300 FW

**COULEUR OR** 24177 9300 GC

**BLANC** 24177 9300 W



[View on website](#)



### General info

|                               |                                                |
|-------------------------------|------------------------------------------------|
| <b>LOCATION</b>               | interieur                                      |
| <b>INSTALLATION</b>           | Plafond Semi-encastré                          |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | circulaire - Ø KIT                             |
| <b>RECESSED DEPTH (MM)</b>    | 80                                             |
| <b>INGRESS PROTECTION</b>     | IP20                                           |
| <b>WEIGHT (KG)</b>            | 0.4                                            |
| <b>ADJUSTABILITY</b>          | 0° à 85° inclinable, 355° rotatif              |
| <b>INFORMATION</b>            | WALLWASH LENS<br>EXCLLED POWER SUPPLY 350mA-DC |

### Electrical info

|                      |                                      |
|----------------------|--------------------------------------|
| <b>CLASS</b>         | III                                  |
| <b>DIM TYPE</b>      | selon le type d'alimentation externe |
| <b>ENERGY CLASS</b>  | E                                    |
| <b>CERTIFICATION</b> | CB, ENEC                             |

### Lightsource info

|                                    |                                                  |
|------------------------------------|--------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                              |
| <b>LIGHTSOURCE</b>                 | LED array 5,8W / CRI>90 (R9: 52) / 3000K / 787lm |
| <b>RVALUES</b>                     | rf: 90 / Rg: 99                                  |
| <b>SDMC</b>                        | SDCM1                                            |
| <b>RISKGROUP</b>                   | RG1                                              |
| <b>LM80</b>                        | L90B10 > 50000                                   |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 787lm // 5,8W // 135lm/W                         |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 431lm // 6,7W // 65lm/W                          |

### Requirements

MOUNTING KIT PLUG O.F.A.

LED POWER SUPPLY 350mA-DC DIM

For detailed installation instructions, please consult the manual : [24177\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## SPY 39 PLUG WALLWASH 930

24177 9300 FG






### CEILING COMPATIBILITY

| Ceiling Type                                                                                                | Mounting Kit                                                                                                            |          |
|-------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|----------|
|  Plasterboard               |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  Concrete + plaster         |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  Lintel + plaster           |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  Hollow-core slab + plaster |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |

### FINISH YOUR SPECIFICATION


#### les alimentations led

#### # of Fixtures

| web2print_power_supply_info_box                                                    |                                                                                                                                                           |   | Min current   Max current |
|------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|---|---------------------------|
|  | <b>300 48 350 ED1</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1<br><b>Dimtype: 1 à 10 V</b><br><b>Cutout dimension (mm): 30</b>               | 2 | <input type="text"/>      |
|  | <b>300 48 350 ED5</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 45</b>                   | 2 | <input type="text"/>      |
|  | <b>300 48 350 MDL</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL<br><b>Dimtype: non dimmable</b><br><b>Cutout dimension (mm): 30</b>            | 2 | <input type="text"/>      |
|  | <b>300 48 350 WDL</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br><b>Dimtype: WDL = dimmable sans fil</b><br><b>Cutout dimension (mm): 45</b> | 2 | <input type="text"/>      |
|  | <b>300 48 500 ED1</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1<br><b>Dimtype: 1 à 10 V</b><br><b>Cutout dimension (mm): 30</b>               | 2 | <input type="text"/>      |








SPY 39 PLUG WALLWASH 930

24177 9300 FG

|                                                                                    |                                                                                                                                                     |             |                          |
|------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 48 500 ED5</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 45                   | 2           | <input type="checkbox"/> |
|    | <b>300 48 500 MDL</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL<br><br>Dimtype: non dimmable<br><br>Cutout dimension (mm): 30            | 2           | <input type="checkbox"/> |
|    | <b>300 48 500 WDL</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL<br><br>Dimtype: WDL = dimmable sans fil<br><br>Cutout dimension (mm): 45 | 2           | <input type="checkbox"/> |
|    | <b>300 90 61</b><br>LED POWER SUPPLY MULTI-POWER DIM6<br><br>Dimtype: fin de phase ou bouton poussoir<br><br>Cutout dimension (mm): 56              | 2   2       | <input type="checkbox"/> |
|  | <b>300 90 63</b><br>LED POWER SUPPLY MULTI-POWER DIM9<br><br>Dimtype: 1 à 10 V ou DALI ou bouton poussoir<br><br>Cutout dimension (mm): 82          | 4(4)        | <input type="checkbox"/> |
|  | <b>300 90 64</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br><br>Dimtype: 1 à 10 V ou bouton poussoir<br><br>Cutout dimension (mm): 72                  | 2(2)   2(1) | <input type="checkbox"/> |
|  | <b>300 90 67</b><br>LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9<br><br>Dimtype: 1 à 10 V ou DALI ou bouton poussoir                        | 2   -       | <input type="checkbox"/> |
|  | <b>300 90 68</b><br>LED POWER SUPPLY MULTI-POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 72                                         | 2(2)        | <input type="checkbox"/> |
|  | <b>300 90 69</b><br>LED POWER SUPPLY MULTI-POWER HV DIM9<br><br>Dimtype: 1 à 10 V ou DALI ou bouton poussoir<br><br>Cutout dimension (mm): 84       | 2->6(6)     | <input type="checkbox"/> |
|  | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br><br>Dimtype: 1 à 10 V ou bouton poussoir<br><br>Cutout dimension (mm): 55                 | 3(2)        | <input type="checkbox"/> |

## SPY 39 PLUG WALLWASH 930






24177 9300 FG

|                                                                                    |                                  |                                                 |             |                          |
|------------------------------------------------------------------------------------|----------------------------------|-------------------------------------------------|-------------|--------------------------|
|    | <b><u>300 90 125</u></b>         | LED POWER SUPPLY MULTI-POWER MINI DIM5          | 2(2)        | <input type="checkbox"/> |
| <b>Dimtype: DALI</b>                                                               | <b>Cutout dimension (mm): 55</b> |                                                 |             |                          |
|    | <b><u>300 90 135</u></b>         | LED POWER SUPPLY MULTI-POWER HV                 | 3->4   2->4 | <input type="checkbox"/> |
| <b>Dimtype: non dimmable</b>                                                       | <b>Cutout dimension (mm): 90</b> |                                                 |             |                          |
|    | <b><u>21012 0010</u></b>         | LED POWER SUPPLY MULTI POWER                    | 2   2       | <input type="checkbox"/> |
| <b>Dimtype: non dimmable</b>                                                       | <b>Cutout dimension (mm): 50</b> |                                                 |             |                          |
|    | <b><u>21012 0021</u></b>         | LED POWER SUPPLY MULTI POWER DIM1               | 3   3       | <input type="checkbox"/> |
| <b>Dimtype: 1 à 10 V</b>                                                           | <b>Cutout dimension (mm): 54</b> |                                                 |             |                          |
|  | <b><u>21012 0035</u></b>         | LED POWER SUPPLY MULTI POWER DIM5               | 3           | <input type="checkbox"/> |
| <b>Dimtype: DALI</b>                                                               | <b>Cutout dimension (mm): 54</b> |                                                 |             |                          |
|  | <b><u>21012 004W</u></b>         | LED POWER SUPPLY MULTI-POWER WDL                | 4(4)   3(3) | <input type="checkbox"/> |
| <b>Dimtype: WDL = dimmable sans fil</b>                                            | <b>Cutout dimension (mm): 84</b> |                                                 |             |                          |
|  | <b><u>21012 005W</u></b>         | LED POWER SUPPLY MULTI-POWER COMPACT WDL        | 3   2       | <input type="checkbox"/> |
| <b>Dimtype: WDL = dimmable sans fil</b>                                            | <b>Cutout dimension (mm): 54</b> |                                                 |             |                          |
|  | <b><u>21012 0268</u></b>         | LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 | 2->2        | <input type="checkbox"/> |
| <b>Dimtype: fin de phase</b>                                                       | <b>Cutout dimension (mm): 50</b> |                                                 |             |                          |
|  | <b><u>21012 0278</u></b>         | LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 | 1           | <input type="checkbox"/> |
| <b>Dimtype: fin de phase</b>                                                       | <b>Cutout dimension (mm): 55</b> |                                                 |             |                          |
|  | <b><u>21012 0288</u></b>         | LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 | 2->2        | <input type="checkbox"/> |
| <b>Dimtype: fin de phase</b>                                                       | <b>Cutout dimension (mm): 55</b> |                                                 |             |                          |


# DELTALIGHT

## SPY 39 PLUG WALLWASH 930

24177 9300 FG

|                                                                                    |                                                                                                                                |      |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|------|--------------------------|
|    | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: fin de phase<br>Cutout dimension (mm): 48 | 2    | <input type="checkbox"/> |
|    | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: fin de phase<br>Cutout dimension (mm): 40             | 1    | <input type="checkbox"/> |
|    | <b>21012 0318</b><br>LED POWER SUPPLY 500mA / 10W DIM8<br><br>Dimtype: fin de phase<br>Cutout dimension (mm): 40               | 1    | <input type="checkbox"/> |
|   | <b>21012 0480</b><br>LED POWER SUPPLY 350mA-DC / 17W IP68<br><br>Dimtype: non dimmable<br>Cutout dimension (mm): 60            | 2(2) | <input type="checkbox"/> |
|  | <b>21032 0295</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30      | 2    | <input type="checkbox"/> |
|  | <b>21032 0305</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30      | 2    | <input type="checkbox"/> |

### kit de montage

|                                                                                    |                                                                                             |  |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|--|--------------------------|
|  | <b>24144 0060</b> MOUNTING KIT PLUG O.F.A.<br><br>Cutout dimension (mm): 62 (CONCRETE: 102) |  | <input type="checkbox"/> |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|--|--------------------------|

Notes: