





SPY 39 ON FOCUS 927

24174 9200 BROB

AVAILABLE IN

- BLACK** 24174 9200 B
- BRUSHED ALU** 24174 9200 BRA
- BRUSHED ANTHRACITE** 24174 9200 BRAT
- BRUSHED COPPER** 24174 9200 BRCU
- BRUSHED GOLD** 24174 9200 BRG
- BRUSHED OLD BRONZE** 24174 9200 BROB
- FLEMISH BRONZE** 24174 9200 FBR
- FLEMISH GOLD** 24174 9200 FG
- FULL WHITE** 24174 9200 FW
- GOLD COLOURED** 24174 9200 GC
- WHITE** 24174 9200 W



 [View on website](#)



General info

LOCATION	indoor
INSTALLATION	Ceiling Surface mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	0° to 85° swiveling, 355° rotatable
INFORMATION	ADJUSTABLE BEAM 15°-45°

Electrical info

CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	F
CERTIFICATES	LCA

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 702-974lm
TM-30 VALUES	rf: 89 / Rg: 100
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	15°-45°
LED TECHNICS (LIGHT SOURCE)	974lm // 8,6W // 113lm/W
LED TECHNICS (LUMINAIRE)	290lm // 9,9W // 29lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

Options

COVERSET R 90-100

DELTALIGHT

SPY 39 ON FOCUS 927


24174 9200 BROB

For detailed installation instructions, please consult the manual : [24174_XXX0_HAND.pdf](#)


FINISH YOUR SPECIFICATION

LED power supplies

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45




300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30




300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45




300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45



300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

2


Dimtype: non-dimmable

Cutout dimension (mm): 30

DELTALIGHT

SPY 39 ON FOCUS 927

24174 9200 BROB



300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

2 | 2

Dimtype: mains (phase cut-off) or push button

Cutout dimension (mm): 56




300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

4(4) | 4(4)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 82



300 90 64 LED POWER SUPPLY MULTI-POWER DIM7

2(2) | 2(1)

Dimtype: 1-10V or push button

Cutout dimension (mm): 72



300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

2 | -

Dimtype: 1-10V or DALI or push button



300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

2(2) | 2(1)

Dimtype: DALI

Cutout dimension (mm): 72



300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6) | 6(4)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 84



300 90 124 LED POWER SUPPLY MULTI-POWER DIM7

2(2) | 2(1)

Dimtype: 1-10V or push button

Cutout dimension (mm): 55



300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5

2(2) | 2(1)

Dimtype: DALI

Cutout dimension (mm): 55



300 90 135 LED POWER SUPPLY MULTI-POWER HV

3->4 | 2->4











Dimtype: non-dimmable

Cutout dimension (mm): 90

DELTALIGHT

SPY 39 ON FOCUS 927

24174 9200 BROB

	21012 0010 LED POWER SUPPLY MULTI POWER	2 2 <input type="checkbox"/>
	Dimtype: non-dimmable	
	Cutout dimension (mm): 50	
	21012 0021 LED POWER SUPPLY MULTI POWER DIM1	3 3 <input type="checkbox"/>
	Dimtype: 1-10V	
	Cutout dimension (mm): 54	
	21012 0035 LED POWER SUPPLY MULTI POWER DIM5	3 3 <input type="checkbox"/>
	Dimtype: DALI	
	Cutout dimension (mm): 54	
	21012 004W LED POWER SUPPLY MULTI-POWER WDL	4(4) 3(3) <input type="checkbox"/>
	Dimtype: WDL = wireless dimmable	
	Cutout dimension (mm): 84	
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL	3 3 <input type="checkbox"/>
	Dimtype: WDL = wireless dimmable	
	Cutout dimension (mm): 54	
	21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	2->2 2->2 <input type="checkbox"/>
	Dimtype: mains (phase cut-off)	
	Cutout dimension (mm): 50	
	21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	1 <input type="checkbox"/>
	Dimtype: mains (phase cut-off)	
	Cutout dimension (mm): 55	
	21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	2->3 <input type="checkbox"/>
	Dimtype: mains (phase cut-off)	
	Cutout dimension (mm): 55	
	21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	2 2 <input type="checkbox"/>
	Dimtype: mains (phase cut-off)	
	Cutout dimension (mm): 48	
	21012 0308 LED POWER SUPPLY 350mA / 7,35W DIM8	1 <input type="checkbox"/>
	Dimtype: mains (phase cut-off)	
	Cutout dimension (mm): 40	

DELTALIGHT

SPY 39 ON FOCUS 927

24174 9200 BROB



21012 0318 LED POWER SUPPLY 500mA / 10W DIM8

1

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 40



21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68

2(2)

Dimtype: non-dimmable

Cutout dimension (mm): 60



21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68

2(1)

Dimtype: non-dimmable

Cutout dimension (mm): 60



21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 30



21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 30

Coversets



204 00 100 ANO COVERSET R 100 ANO

204 00 100 B COVERSET R 100 B

204 00 100 W COVERSET R 100 W

Notes: