



M26L - BOXY L A 93033 MDL

10739 9320 W-W



AVAILABLE IN

BLACK-BLACK 10739 9320 B-B

BLACK-FLEMISH BRONZE 10739 9320 B-FBR

BLACK-FLEMISH GOLD 10739 9320 B-FG

WHITE-WHITE 10739 9320 W-W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1089lm
TM-30 VALUES	rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	33°
LED TECHNICS (LIGHT SOURCE)	1089lm // 8,6W // 127lm/W
LED TECHNICS (LUMINAIRE)	729lm // 9,9W // 74lm/W

Remarks

[Take a look at our MAGNETIC PROFILES movie](#)

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

Accessories

BOXY HONEYCOMB
BOXY SOFTENING LENS
BOXY GLASS SBL

For detailed installation instructions, please consult the manual : [10739_XXX0_HAND.pdf](#)


FINISH YOUR SPECIFICATION

Current supply

of Fixtures

Min current | Max current

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



21032 0030 SMART 48 MODULATOR PLUG-IN WD

Dimtype: WDL = wireless dimmable


19

SMART 48

of Fixtures

Min current | Max current


 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



300 90 011 SMART 48 MODULATOR DIM9

Dimtype: 1-10V or DALI or push button

19



300 90 012 SMART 48 MODULATOR WD

Dimtype: WDL = wireless dimmable


19

LED power supplies

of Fixtures

Min current | Max current

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN




Dimtype: non-dimmable

10

DELTALIGHT

M26L - BOXY L A 93033 MDL

10739 9320 W-W

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	24	☐
	Dimtype: non-dimmable		
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	10	☐
	Dimtype: non-dimmable		
	Cutout dimension (mm): 40		
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	20	☐
	Dimtype: non-dimmable		
	Cutout dimension (mm): 40		

Light altering devices





	251 70 03 01 B BOXY HONEYCOMB B	☐
	251 70 03 01 W BOXY HONEYCOMB W	☐
	251 70 03 04 B BOXY SOFTENING LENS B	☐
	251 70 03 04 W BOXY SOFTENING LENS W	☐
	251 70 03 05 B BOXY GLASS SBL B	☐
	251 70 03 05 W BOXY GLASS SBL W	☐

DELTALIGHT

M26L - BOXY L A 93033 MDL

10739 9320 W-W

COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)		Available Colours
	23358 0000 SLM26L - PROFILE	 
	23358 0010 SLM26L - PROFILE 1m	 
	23358 0020 SLM26L - PROFILE 2m	         
	23358 0030 SLM26L - PROFILE 3m	         

Notes: