



## SPY 39 TRIMLESS IN 93020

24123 9320 BRCU

AVAILABLE IN

**BLACK** 24123 9320 B

**BRUSHED ALU** 24123 9320 BRA

**BRUSHED ANTHRACITE** 24123 9320 BRAT

**BRUSHED COPPER** 24123 9320 BRCU

**BRUSHED GOLD** 24123 9320 BRG

**BRUSHED OLD BRONZE** 24123 9320 BROB

**FLEMISH BRONZE** 24123 9320 FBR


**FLEMISH GOLD** 24123 9320 FG

**FULL WHITE** 24123 9320 FW


**GOLD COLOURED** 24123 9320 GC

**PIANO BLACK** 24123 9320 PB

**WHITE** 24123 9320 W



0-85°/355°



[View on website](#)



### General info

|                               |                                                        |
|-------------------------------|--------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                 |
| <b>INSTALLATION</b>           | Ceiling Recessed                                       |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - Ø KIT                                          |
| <b>RECESSED DEPTH (MM)</b>    | 130                                                    |
| <b>INGRESS PROTECTION</b>     | IP20                                                   |
| <b>WEIGHT (KG)</b>            | 0.4                                                    |
| <b>ADJUSTABILITY</b>          | 0° to 85° swiveling, 355° rotatable                    |
| <b>INFORMATION</b>            | REFLECTOR FL-20°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | D                         |
| <b>CERTIFICATES</b> | CB, ENEC                  |

### Lightsource info

|                                    |                                                           |
|------------------------------------|-----------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                       |
| <b>LIGHTSOURCE</b>                 | LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm |
| <b>TM-30 VALUES</b>                | rf: 90 / Rg: 99                                           |
| <b>SDCM</b>                        | SDCM1                                                     |
| <b>RISKGROUP</b>                   | RG1                                                       |
| <b>LM80</b>                        | L90B10 > 50000                                            |
| <b>BEAMANGLE</b>                   | 20°                                                       |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1089lm // 8,6W // 127lm/W                                 |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 888lm // 9,9W // 90lm/W                                   |

### Requirements

SPY 39 TUBE or VISOR 39

MOUNTING KIT SPY 39 TRIMLESS IN

LED POWER SUPPLY 350 / 500mA-DC DIM (Remote)

# DELTALIGHT

## SPY 39 TRIMLESS IN 93020

24123 9320 BRCU

For detailed installation instructions, please consult the manual : [24123\\_XXX0\\_HAND.pdf](#)

### CEILING COMPATIBILITY

| Ceiling Type                                                                                                         | Mounting Kit                                                                                                                     |          |
|----------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------|----------|
|  <b>System ceiling</b>               |  24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN   | Required |
|  <b>Plasterboard</b>                 |  24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN   | Required |
|  <b>Stucanet</b>                     |  24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN   | Required |
|  <b>Concrete + plaster</b>           |  24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN   | Required |
|  <b>Lintel + plaster</b>            |  24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN | Required |
|  <b>Hollow-core slab + plaster</b> |  24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN | Required |

### FINISH YOUR SPECIFICATION


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45



**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL








2

Dimtype: non-dimmable

Cutout dimension (mm): 30











SPY 39 TRIMLESS IN 93020

24123 9320 BRCU

|                                                                                    |                                                                                                                                                  |             |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 45 | 2           | <input type="checkbox"/> |
|    | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1<br><br>Dimtype: 1-10V<br><br>Cutout dimension (mm): 30                  | 2           | <input type="checkbox"/> |
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 45                   | 2           | <input type="checkbox"/> |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL<br><br>Dimtype: non-dimmable<br><br>Cutout dimension (mm): 30            | 2           | <input type="checkbox"/> |
|  | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 45 | 2           | <input type="checkbox"/> |
|  | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6<br><br>Dimtype: mains (phase cut-off) or push button<br><br>Cutout dimension (mm): 56         | 2   2       | <input type="checkbox"/> |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9<br><br>Dimtype: 1-10V or DALI or push button<br><br>Cutout dimension (mm): 82                 | 4(4)   4(4) | <input type="checkbox"/> |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7<br><br>Dimtype: 1-10V or push button<br><br>Cutout dimension (mm): 72                         | 2(2)   2(1) | <input type="checkbox"/> |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9<br><br>Dimtype: 1-10V or DALI or push button                               | 2   -       | <input type="checkbox"/> |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 72                                         | 2(2)   2(1) | <input type="checkbox"/> |




SPY 39 TRIMLESS IN 93020

24123 9320 BRCU

|                                                                                    |                                                                                                                                     |                |                          |
|------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------|----------------|--------------------------|
|    | <b>300 90 69</b><br>LED POWER SUPPLY MULTI-POWER HV DIM9<br>Dimtype: 1-10V or DALI or push button<br>Cutout dimension (mm): 84      | 2->6(6)   6(4) | <input type="checkbox"/> |
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br>Dimtype: 1-10V or push button<br>Cutout dimension (mm): 55                | 3(2)   2(1)    | <input type="checkbox"/> |
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 55                           | 2(2)   2(1)    | <input type="checkbox"/> |
|    | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 90                          | 3->4   2->4    | <input type="checkbox"/> |
|  | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 50                             | 2   2          | <input type="checkbox"/> |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 54                               | 3   3          | <input type="checkbox"/> |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 54                                | 3   3          | <input type="checkbox"/> |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 84              | 4(4)   3(3)    | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 54      | 3   3          | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 50 | 2->2   0       | <input type="checkbox"/> |

SPY 39 TRIMLESS IN 93020

24123 9320 BRCU


|                                                                                    |                                                                                                                                         |       |                          |
|------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|-------|--------------------------|
|    | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 1     | <input type="checkbox"/> |
|    | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 2->3  | <input type="checkbox"/> |
|    | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 48 | 2   2 | <input type="checkbox"/> |
|    | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40             | 1     | <input type="checkbox"/> |
|  | <b>21012 0318</b><br>LED POWER SUPPLY 500mA / 10W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40               | 1     | <input type="checkbox"/> |
|  | <b>21012 0480</b><br>LED POWER SUPPLY 350mA-DC / 17W IP68<br><br>Dimtype: non-dimmable<br>Cutout dimension (mm): 60                     | 2(2)  | <input type="checkbox"/> |
|  | <b>21012 0500</b><br>LED POWER SUPPLY 500mA-DC / 24W IP68<br><br>Dimtype: non-dimmable<br>Cutout dimension (mm): 60                     | 2(1)  | <input type="checkbox"/> |
|  | <b>21032 0295</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30               | 2     | <input type="checkbox"/> |
|  | <b>21032 0305</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30               | 2     | <input type="checkbox"/> |

# DELTALIGHT

## SPY 39 TRIMLESS IN 93020

24123 9320 BRCU

### Mounting kits




**24144 0050** MOUNTING KIT SPY 39 TRIMLESS IN

Cutout dimension (mm): 82

☐


### Light altering devices



**24144 0030 B** VISOR 39 B

☐

### Finish your product



**24144 0010 B** SPY 39 TUBE B

☐

**24144 0010 FBR** SPY 39 TUBE FBR

☐

**24144 0010 FG** SPY 39 TUBE FG

☐

**24144 0010 GC** SPY 39 TUBE GC

☐

**24144 0010 W** SPY 39 TUBE W

☐



**24144 0070** SPY 39 TUBE SBL

☐

Notes: