



## SPY 39 ON 92720

24127 9220 BRCU

AVAILABLE IN

**BLACK** 24127 9220 B

**BRUSHED ALU** 24127 9220 BRA

**BRUSHED ANTHRACITE** 24127 9220 BRAT

**BRUSHED COPPER** 24127 9220 BRCU

**BRUSHED GOLD** 24127 9220 BRG

**BRUSHED OLD BRONZE** 24127 9220 BROB

**FLEMISH BRONZE** 24127 9220 FBR


**FLEMISH GOLD** 24127 9220 FG

**FULL WHITE** 24127 9220 FW

**GOLD COLOURED** 24127 9220 GC

**PIANO BLACK** 24127 9220 PB

**WHITE** 24127 9220 W



[View on website](#)



### General info

|                           |                                                        |
|---------------------------|--------------------------------------------------------|
| <b>LOCATION</b>           | indoor                                                 |
| <b>INSTALLATION</b>       | Ceiling Surface mounted                                |
| <b>INGRESS PROTECTION</b> | IP20                                                   |
| <b>WEIGHT (KG)</b>        | 0.4                                                    |
| <b>ADJUSTABILITY</b>      | 0° to 85° swiveling, 355° rotatable                    |
| <b>INFORMATION</b>        | REFLECTOR FL-20°<br>EXCL LED POWER SUPPLY 350-500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | E                         |
| <b>CERTIFICATES</b> | CB, ENEC, LCA             |

### Lightsource info

|                                    |                                                           |
|------------------------------------|-----------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                       |
| <b>LIGHTSOURCE</b>                 | LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm |
| <b>TM-30 VALUES</b>                | rf: 89 / Rg: 100                                          |
| <b>SDCM</b>                        | SDCM1                                                     |
| <b>RISKGROUP</b>                   | RG1                                                       |
| <b>LM80</b>                        | L90B10 > 50000                                            |
| <b>BEAMANGLE</b>                   | 20°                                                       |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1041lm // 8,6W // 121lm/W                                 |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 849lm // 9,9W // 86lm/W                                   |

### Requirements

SPY 39 TUBE or VISOR 39

LED POWER SUPPLY 350 / 500mA-DC DIM

### Options

COVERSET R 90-100

For detailed installation instructions, please consult the manual : [24127\\_XXX0\\_HAND.pdf](#)

### FINISH YOUR SPECIFICATION

#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30



**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45



**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30



**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45




**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45



**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL










2

Dimtype: non-dimmable

Cutout dimension (mm): 30

SPY 39 ON 92720

24127 9220 BRCU

|                                                                                    |                                                                                                                                                        |                |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|--------------------------|
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL<br><b>Dimtype:</b> WDL = wireless dimmable<br><b>Cutout dimension (mm):</b> 45 | 2              | <input type="checkbox"/> |
|    | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6<br><b>Dimtype:</b> mains (phase cut-off) or push button<br><b>Cutout dimension (mm):</b> 56         | 2   2          | <input type="checkbox"/> |
|    | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button<br><b>Cutout dimension (mm):</b> 82                 | 4(4)   4(4)    | <input type="checkbox"/> |
|    | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype:</b> 1-10V or push button<br><b>Cutout dimension (mm):</b> 72                         | 2(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button                                  | 2   -          | <input type="checkbox"/> |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 72                                         | 2(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button<br><b>Cutout dimension (mm):</b> 84              | 2->6(6)   6(4) | <input type="checkbox"/> |
|  | <b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype:</b> 1-10V or push button<br><b>Cutout dimension (mm):</b> 55                        | 3(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 125</b> LED POWER SUPPLY MULTI-POWER MINI DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 55                                   | 2(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 135</b> LED POWER SUPPLY MULTI-POWER HV<br><b>Dimtype:</b> non-dimmable<br><b>Cutout dimension (mm):</b> 90                                  | 3->4   2->4    | <input type="checkbox"/> |

# DELTALIGHT

## SPY 39 ON 92720

24127 9220 BRCU

|                                                                                    |                                                                                                                                         |             |                          |
|------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><br>Dimtype: non-dimmable<br>Cutout dimension (mm): 50                             | 2   2       | <input type="checkbox"/> |
|    | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><br>Dimtype: 1-10V<br>Cutout dimension (mm): 54                               | 3   3       | <input type="checkbox"/> |
|    | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 54                                | 3   3       | <input type="checkbox"/> |
|    | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 84              | 4(4)   3(3) | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 54      | 3   3       | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 50 | 2->2   0    | <input type="checkbox"/> |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 1           | <input type="checkbox"/> |
|  | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 2->3        | <input type="checkbox"/> |
|  | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 48 | 2   2       | <input type="checkbox"/> |
|  | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40             | 1           | <input type="checkbox"/> |



# DELTALIGHT

## SPY 39 ON 92720

24127 9220 BRCU

|                                                                                    |                                                                      |      |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|------|--------------------------|
|    | <b>21012 0318</b> LED POWER SUPPLY 500mA / 10W DIM8                  | 1    | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off)                                       |      |                          |
|                                                                                    | Cutout dimension (mm): 40                                            |      |                          |
|    | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 2(2) | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                |      |                          |
|                                                                                    | Cutout dimension (mm): 60                                            |      |                          |
|    | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 2(1) | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                |      |                          |
|                                                                                    | Cutout dimension (mm): 60                                            |      |                          |
|    | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 2    | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                        |      |                          |
|                                                                                    | Cutout dimension (mm): 30                                            |      |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2    | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                        |      |                          |
|                                                                                    | Cutout dimension (mm): 30                                            |      |                          |

### Coversets

|                                                                                    |                                          |                          |
|------------------------------------------------------------------------------------|------------------------------------------|--------------------------|
|  | <b>204 00 90 ANO</b> COVERSET R 90 ANO   | <input type="checkbox"/> |
|                                                                                    | <b>204 00 90 B</b> COVERSET R 90 B       | <input type="checkbox"/> |
|                                                                                    | <b>204 00 90 W</b> COVERSET R 90 W       | <input type="checkbox"/> |
|  | <b>204 00 100 ANO</b> COVERSET R 100 ANO | <input type="checkbox"/> |
|                                                                                    | <b>204 00 100 B</b> COVERSET R 100 B     | <input type="checkbox"/> |
|                                                                                    | <b>204 00 100 W</b> COVERSET R 100 W     | <input type="checkbox"/> |

## SPY 39 ON 92720

24127 9220 BRCU

### Light altering devices



**24144 0030 B** VISOR 39 B

☐

### Finish your product



**24144 0010 B** SPY 39 TUBE B

☐

**24144 0010 FBR** SPY 39 TUBE FBR

☐

**24144 0010 FG** SPY 39 TUBE FG

☐

**24144 0010 GC** SPY 39 TUBE GC

☐

**24144 0010 W** SPY 39 TUBE W

☐

**24144 0070** SPY 39 TUBE SBL

☐

Notes: