



SPY 39 ON 92740

24127 9230 BRCU

AVAILABLE IN

NOIR 24127 9230 B

ALU BROSSÉ 24127 9230 BRA

ANTHRACITE BROSSÉ 24127 9230 BRAT

CUIVRE BROSSÉ 24127 9230 BRCU

OR BROSSÉ 24127 9230 BRG

BRONZE VIEUX BROSSÉ 24127 9230 BROB

FLEMISH BRONZE 24127 9230 FBR

FLEMISH GOLD 24127 9230 FG

ENTIÈREMENT BLANC 24127 9230 FW

COULEUR OR 24127 9230 GC

NOIR PIANO 24127 9230 PB

BLANC 24127 9230 W



[View on website](#)



General info

LOCATION	interieur
INSTALLATION	Plafond Applique
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	0° à 85° inclinable, 355° rotatif
INFORMATION	REFLECTOR WFL-40° EXCL LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
DIM TYPE	selon le type d'alimentation externe
ENERGY CLASS	E
CERTIFICATION	CB, ENEC, LCA

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
RVALUES	rf: 89 / Rg: 100
SDMC	SDCM1
RISKGROUPE	RG1
LM80	L90B10 > 50000
BEAMANGLE	40°
LED TECHNICS (LIGHT SOURCE)	1041lm // 8,6W // 121lm/W
LED TECHNICS (LUMINAIRE)	844lm // 9,9W // 85lm/W

Requirements

SPY 39 TUBE or VISOR 39








LED POWER SUPPLY 350 / 500mA-DC DIM

Options

COVERSET R 90-100

For detailed installation instructions, please consult the manual : [24127_XXX0_HAND.pdf](#)

FINISH YOUR SPECIFICATION

les alimentations led			# of Fixtures
 web2print_power_supply_info_box			Min current Max current
	300 48 350 ED1	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1	2 ☐
	Dimtype: 1 à 10 V		
	Cutout dimension (mm): 30		
	300 48 350 ED5	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	2 ☐
	Dimtype: DALI		
	Cutout dimension (mm): 45		
	300 48 350 MDL	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL	2 ☐
	Dimtype: non dimmable		
	Cutout dimension (mm): 30		
	300 48 350 WDL	LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL	2 ☐
	Dimtype: WDL = dimmable sans fil		
	Cutout dimension (mm): 45		
	300 48 500 ED1	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1	2 ☐
	Dimtype: 1 à 10 V		
	Cutout dimension (mm): 30		
	300 48 500 ED5	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	2 ☐
	Dimtype: DALI		
	Cutout dimension (mm): 45		
	300 48 500 MDL	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL	2 ☐
	Dimtype: non dimmable		
	Cutout dimension (mm): 30		

DELTALIGHT

SPY 39 ON 92740











24127 9230 BRCU

	300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL	2	☐
Dimtype: WDL = dimmable sans fil			
Cutout dimension (mm): 45			
	300 90 61 LED POWER SUPPLY MULTI-POWER DIM6	2 2	☐
Dimtype: fin de phase ou bouton poussoir			
Cutout dimension (mm): 56			
	300 90 63 LED POWER SUPPLY MULTI-POWER DIM9	4(4) 4(4)	☐
Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
Cutout dimension (mm): 82			
	300 90 64 LED POWER SUPPLY MULTI-POWER DIM7	2(2) 2(1)	☐
Dimtype: 1 à 10 V ou bouton poussoir			
Cutout dimension (mm): 72			
	300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9	2 -	☐
Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
	300 90 68 LED POWER SUPPLY MULTI-POWER DIM5	2(2) 2(1)	☐
Dimtype: DALI			
Cutout dimension (mm): 72			
	300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9	2->6(6) 6(4)	☐
Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
Cutout dimension (mm): 84			
	300 90 124 LED POWER SUPPLY MULTI-POWER DIM7	3(2) 2(1)	☐
Dimtype: 1 à 10 V ou bouton poussoir			
Cutout dimension (mm): 55			
	300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5	2(2) 2(1)	☐
Dimtype: DALI			
Cutout dimension (mm): 55			
	300 90 135 LED POWER SUPPLY MULTI-POWER HV	3->4 2->4	☐
Dimtype: non dimmable			
Cutout dimension (mm): 90			

DELTALIGHT

SPY 39 ON 92740





24127 9230 BRCU

	21012 0010 LED POWER SUPPLY MULTI POWER Dimtype: non dimmable Cutout dimension (mm): 50	2 2	☐
	21012 0021 LED POWER SUPPLY MULTI POWER DIM1 Dimtype: 1 à 10 V Cutout dimension (mm): 54	3 3	☐
	21012 0035 LED POWER SUPPLY MULTI POWER DIM5 Dimtype: DALI Cutout dimension (mm): 54	3 3	☐
	21012 004W LED POWER SUPPLY MULTI-POWER WDL Dimtype: WDL = dimmable sans fil Cutout dimension (mm): 84	4(4) 3(3)	☐
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL Dimtype: WDL = dimmable sans fil Cutout dimension (mm): 54	3 3	☐
	21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 Dimtype: fin de phase Cutout dimension (mm): 50	2->2 0	☐
	21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 Dimtype: fin de phase Cutout dimension (mm): 55	1	☐
	21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 Dimtype: fin de phase Cutout dimension (mm): 55	2->3	☐
	21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 Dimtype: fin de phase Cutout dimension (mm): 48	2 2	☐
	21012 0308 LED POWER SUPPLY 350mA / 7,35W DIM8 Dimtype: fin de phase Cutout dimension (mm): 40	1	☐



DELTALIGHT

SPY 39 ON 92740

24127 9230 BRCU

	21012 0318 LED POWER SUPPLY 500mA / 10W DIM8	1	☐
	Dimtype: fin de phase		
	Cutout dimension (mm): 40		
	21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68	2(2)	☐
	Dimtype: non dimmable		
	Cutout dimension (mm): 60		
	21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68	2(1)	☐
	Dimtype: non dimmable		
	Cutout dimension (mm): 60		
	21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	2	☐
	Dimtype: DALI		
	Cutout dimension (mm): 30		
	21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	2	☐
	Dimtype: DALI		
	Cutout dimension (mm): 30		

les sets pour recouvrement plafond

	204 00 90 ANO COVERSET R 90 ANO	☐
	204 00 90 B COVERSET R 90 B	☐
	204 00 90 W COVERSET R 90 W	☐
	204 00 100 ANO COVERSET R 100 ANO	☐
	204 00 100 B COVERSET R 100 B	☐
	204 00 100 W COVERSET R 100 W	☐

modifier les dispositifs de lumière



24144 0030 B VISOR 39 B

☐

Terminez votre produit



24144 0010 B SPY 39 TUBE B

☐

24144 0010 FBR SPY 39 TUBE FBR

☐

24144 0010 FG SPY 39 TUBE FG

☐

24144 0010 GC SPY 39 TUBE GC

☐

24144 0010 W SPY 39 TUBE W

☐

24144 0070 SPY 39 TUBE SBL

☐

Notes: