





## SPY 39 CLIP 93020

24125 9320 BRCU-B

AVAILABLE IN

**BLACK-BLACK** 24125 9320 B-B  
**BRUSHED ALU-BLACK** 24125 9320 BRA-B  
**BRUSHED ANTHRACITE-BLACK** 24125 9320 BRAT-B  
**BRUSHED COPPER-BLACK** 24125 9320 BRCU-B  
**BRUSHED GOLD-BLACK** 24125 9320 BRG-B  
**BRUSHED OLD BRONZE-BLACK** 24125 9320 BROB-B  
**FLEMISH BRONZE-BLACK** 24125 9320 FBR-B  
**FLEMISH GOLD-BLACK** 24125 9320 FG-B  
**FULL WHITE** 24125 9320 FW  
**GOLD COLORED-BLACK** 24125 9320 GC-B  
**PIANO BLACK-BLACK** 24125 9320 PB-B  
**WHITE-WHITE** 24125 9320 W-W



[View on website](#)



### General info

|                               |                                                        |
|-------------------------------|--------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                 |
| <b>INSTALLATION</b>           | Ceiling Semi-recessed                                  |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - 43                                             |
| <b>RECESSED DEPTH (MM)</b>    | 40                                                     |
| <b>INGRESS PROTECTION</b>     | IP20                                                   |
| <b>WEIGHT (KG)</b>            | 0.3                                                    |
| <b>ADJUSTABILITY</b>          | 0° to 85° swiveling, 355° rotatable                    |
| <b>INFORMATION</b>            | REFLECTOR FL-20°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | D                         |
| <b>CERTIFICATES</b> | CB, ENEC, LCA             |

### Lightsource info








|                                    |                                                           |
|------------------------------------|-----------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                       |
| <b>LIGHTSOURCE</b>                 | LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm |
| <b>TM-30 VALUES</b>                | rf: 90 / Rg: 99                                           |
| <b>SDCM</b>                        | SDCM1                                                     |
| <b>RISKGROUP</b>                   | RG1                                                       |
| <b>LM80</b>                        | L90B10 > 50000                                            |
| <b>BEAMANGLE</b>                   | 20°                                                       |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1089lm // 8,6W // 127lm/W                                 |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 888lm // 9,9W // 90lm/W                                   |

### Requirements

SPY 39 TUBE or VISOR 39  
 LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : [24125\\_XXX0\\_HAND.pdf](#)

### FINISH YOUR SPECIFICATION

| LED power supplies                                                                                                                                                                                                                                                                                                                                |                                                                                                                                                        | # of Fixtures             |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------|
| <p> # of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</p> |                                                                                                                                                        | Min current   Max current |
|                                                                                                                                                                                                                                                                   | <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1<br><b>Dimtype: 1-10V</b><br><b>Cutout dimension (mm): 30</b>                  | 2 <input type="text"/>    |
|                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                        |                           |
|                                                                                                                                                                                                                                                                  | <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 45</b>                   | 2 <input type="text"/>    |
|                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                        |                           |
|                                                                                                                                                                                                                                                                 | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL<br><b>Dimtype: non-dimmable</b><br><b>Cutout dimension (mm): 30</b>            | 2 <input type="text"/>    |
|                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                        |                           |
|                                                                                                                                                                                                                                                                 | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br><b>Dimtype: WDL = wireless dimmable</b><br><b>Cutout dimension (mm): 45</b> | 2 <input type="text"/>    |
|                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                        |                           |
|                                                                                                                                                                                                                                                                 | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1<br><b>Dimtype: 1-10V</b><br><b>Cutout dimension (mm): 30</b>                  | 2 <input type="text"/>    |
|                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                        |                           |
|                                                                                                                                                                                                                                                                 | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 45</b>                   | 2 <input type="text"/>    |
|                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                        |                           |
|                                                                                                                                                                                                                                                                 | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL<br><b>Dimtype: non-dimmable</b><br><b>Cutout dimension (mm): 30</b>            | 2 <input type="text"/>    |
|                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                        |                           |

# DELTALIGHT

## SPY 39 CLIP 93020



24125 9320 BRCU-B

|                                                                                    |                                                                                                                                                        |                |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|--------------------------|
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL<br><b>Dimtype:</b> WDL = wireless dimmable<br><b>Cutout dimension (mm):</b> 45 | 2              | <input type="checkbox"/> |
|    | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6<br><b>Dimtype:</b> mains (phase cut-off) or push button<br><b>Cutout dimension (mm):</b> 56         | 2   2          | <input type="checkbox"/> |
|    | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button<br><b>Cutout dimension (mm):</b> 82                 | 4(4)   4(4)    | <input type="checkbox"/> |
|    | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype:</b> 1-10V or push button<br><b>Cutout dimension (mm):</b> 72                         | 2(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button                                  | 2   -          | <input type="checkbox"/> |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 72                                         | 2(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button<br><b>Cutout dimension (mm):</b> 84              | 2->6(6)   6(4) | <input type="checkbox"/> |
|  | <b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype:</b> 1-10V or push button<br><b>Cutout dimension (mm):</b> 55                        | 3(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 125</b> LED POWER SUPPLY MULTI-POWER MINI DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 55                                   | 2(2)   2(1)    | <input type="checkbox"/> |
|  | <b>300 90 135</b> LED POWER SUPPLY MULTI-POWER HV<br><b>Dimtype:</b> non-dimmable<br><b>Cutout dimension (mm):</b> 90                                  | 3->4   2->4    | <input type="checkbox"/> |

# DELTALIGHT

## SPY 39 CLIP 93020

24125 9320 BRCU-B

|                                                                                    |                                                                                                                                         |             |                          |
|------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><br>Dimtype: non-dimmable<br>Cutout dimension (mm): 50                             | 2   2       | <input type="checkbox"/> |
|    | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><br>Dimtype: 1-10V<br>Cutout dimension (mm): 54                               | 3   3       | <input type="checkbox"/> |
|    | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 54                                | 3   3       | <input type="checkbox"/> |
|    | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 84              | 4(4)   3(3) | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 54      | 3   3       | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 50 | 2->2   0    | <input type="checkbox"/> |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 1           | <input type="checkbox"/> |
|  | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 2->3        | <input type="checkbox"/> |
|  | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 48 | 2   2       | <input type="checkbox"/> |
|  | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40             | 1           | <input type="checkbox"/> |


# DELTALIGHT

## SPY 39 CLIP 93020


24125 9320 BRCU-B

|                                                                                    |                                                                      |      |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|------|--------------------------|
|    | <b>21012 0318</b> LED POWER SUPPLY 500mA / 10W DIM8                  | 1    | <input type="checkbox"/> |
| <b>Dimtype: mains (phase cut-off)</b>                                              |                                                                      |      |                          |
| <b>Cutout dimension (mm): 40</b>                                                   |                                                                      |      |                          |
|    | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 2(2) | <input type="checkbox"/> |
| <b>Dimtype: non-dimmable</b>                                                       |                                                                      |      |                          |
| <b>Cutout dimension (mm): 60</b>                                                   |                                                                      |      |                          |
|    | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 2(1) | <input type="checkbox"/> |
| <b>Dimtype: non-dimmable</b>                                                       |                                                                      |      |                          |
| <b>Cutout dimension (mm): 60</b>                                                   |                                                                      |      |                          |
|    | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 2    | <input type="checkbox"/> |
| <b>Dimtype: DALI</b>                                                               |                                                                      |      |                          |
| <b>Cutout dimension (mm): 30</b>                                                   |                                                                      |      |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2    | <input type="checkbox"/> |
| <b>Dimtype: DALI</b>                                                               |                                                                      |      |                          |
| <b>Cutout dimension (mm): 30</b>                                                   |                                                                      |      |                          |

### Light altering devices

|                                                                                    |                                |                          |
|------------------------------------------------------------------------------------|--------------------------------|--------------------------|
|  | <b>24144 0030 B</b> VISOR 39 B | <input type="checkbox"/> |
|------------------------------------------------------------------------------------|--------------------------------|--------------------------|

### Finish your product

|                                                                                    |                                   |                          |
|------------------------------------------------------------------------------------|-----------------------------------|--------------------------|
|  | <b>24144 0010 B</b> SPY 39 TUBE B | <input type="checkbox"/> |
| <b>24144 0010 FBR</b> SPY 39 TUBE FBR                                              |                                   | <input type="checkbox"/> |
| <b>24144 0010 FG</b> SPY 39 TUBE FG                                                |                                   | <input type="checkbox"/> |
| <b>24144 0010 GC</b> SPY 39 TUBE GC                                                |                                   | <input type="checkbox"/> |

# DELTALIGHT

## SPY 39 CLIP 93020

24125 9320 BRCU-B

**24144 0010 W** SPY 39 TUBE W



**24144 0070** SPY 39 TUBE SBL



### COMPATIBLE COMPOSABLES

#### ZOOVER 4CLIP

#### Available Colours



**28215 0005** ZOOVER 4CLIP 120 LIGHT GREY DIM5



**28216 0005** ZOOVER 4CLIP 120 DARK GREY DIM5



**28217 0005** ZOOVER 4CLIP 140 LIGHT GREY DIM5



**28218 0005** ZOOVER 4CLIP 140 DARK GREY DIM5

Notes: