



NIME II AIR 92752

26412 9230 PRIM

AVAILABLE IN  
PRIMER 26412 9230 PRIM



[View on website](#)



General info

|                        |                                                    |
|------------------------|----------------------------------------------------|
| LOCATION               | indoor                                             |
| INSTALLATION           | Ceiling Recessed                                   |
| CUTOUT SHAPE/SIZE (MM) | round - Ø KIT                                      |
| INGRESS PROTECTION     | IP20                                               |
| WEIGHT (KG)            | 0.2                                                |
| ADJUSTABILITY          | non adjustable                                     |
| INFORMATION            | LENS WFL-52°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

Electrical info

|              |                           |
|--------------|---------------------------|
| CLASS        | III                       |
| DIM TYPE     | depending on power supply |
| ENERGY CLASS | G                         |

Lightsource info

|                             |                                                          |
|-----------------------------|----------------------------------------------------------|
| LIGHTSOURCE NAME            | LED                                                      |
| LIGHTSOURCE                 | LED array 3,9-5,7W / CRI>90 (R9: 56) / 2700K / 385-519lm |
| TM-30 VALUES                | rf: 91 / Rg: 99                                          |
| SDCM                        | SDCM2                                                    |
| RISKGROUP                   | RG2 (threshold 0,6m)                                     |
| LM80                        | L90B10 > 41000                                           |
| BEAMANGLE                   | 52°                                                      |
| LED TECHNICS (LIGHT SOURCE) | 519lm // 5,7W // 90lm/W                                  |
| LED TECHNICS (LUMINAIRE)    | 335lm // 6,6W // 51lm/W                                  |

Requirements






MOUNTING KIT AIR 105  
LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : [26412\\_XXX0\\_HAND.pdf](#)

CEILING COMPATIBILITY











| Ceiling Type                                                                     | Mounting Kit                                                                                                                                      |
|----------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
|  |  29810 0110 - MOUNTING KIT SIDE AIR 105 <span>Required</span>    |
|                                                                                  |  29810 0120 - MOUNTING KIT NO AIR 105 <span>Required</span>      |
|                                                                                  |  29810 0100 - MOUNTING KIT SIDE AIR ONLY 1 <span>Required</span> |
|  |  29810 0130 - MOUNTING KIT TOP AIR 105 <span>Required</span>     |
|                                                                                  |  29810 0200 - MOUNTING KIT TOP AIR ONLY 1 <span>Required</span>  |
|                                                                                  |  29810 0120 - MOUNTING KIT NO AIR 105 <span>Required</span>      |

FINISH YOUR SPECIFICATION

| LED power supplies                                                                                                                                                                                                                                                                                                                        |                                                                                                                                          | # of Fixtures             |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------|---------------------------|
|  # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V. |                                                                                                                                          | Min current   Max current |
|                                                                                                                                                                                                                                                         | <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 30                  | 3 <input type="text"/>    |
|                                                                                                                                                                                                                                                         | <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 45                   | 3 <input type="text"/>    |
|                                                                                                                                                                                                                                                         | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 30            | 3 <input type="text"/>    |
|                                                                                                                                                                                                                                                         | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 45 | 3 <input type="text"/>    |
|                                                                                                                                                                                                                                                         | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 30                  | 3 <input type="text"/>    |











NIME II AIR 92752

26412 9230 PRIM

|                                                                                    |                                                                          |                 |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|-----------------|--------------------------|
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 3               | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                 |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                 |                          |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 3               | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                 |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                 |                          |
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 3               | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                 |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                 |                          |
|    | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 3   3           | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |                 |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |                 |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 6(6)   6(6)     | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                 |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |                 |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 2->4(3)   4(2)  | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                 |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                 |                          |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9    | 3               | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                 |                          |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5                       | 4(3)   4(2)     | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                 |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                 |                          |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9                    | 2->9(10)   9(6) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                 |                          |
|                                                                                    | Cutout dimension (mm): 84                                                |                 |                          |
|  | <b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7                      | 2->4(3)   3(2)  | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                 |                          |
|                                                                                    | Cutout dimension (mm): 55                                                |                 |                          |

NIME II AIR 92752


26412 9230 PRIM

|                                                                                    |                                                                                                                                             |                    |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------|--------------------|--------------------------|
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 55                           | 4(3)   3(2)        | <input type="checkbox"/> |
|    | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br><br>Dimtype: non-dimmable<br><br>Cutout dimension (mm): 90                          | 5->7   4->7   4->6 | <input type="checkbox"/> |
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><br>Dimtype: non-dimmable<br><br>Cutout dimension (mm): 50                             | 2->3   3           | <input type="checkbox"/> |
|    | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><br>Dimtype: 1-10V<br><br>Cutout dimension (mm): 54                               | 4   4              | <input type="checkbox"/> |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 54                                | 4   4              | <input type="checkbox"/> |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 84              | 6(6)   5(5)        | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 54      | 4   4              | <input type="checkbox"/> |
|  | <b>21012 0258</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 50 | 2->2               | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 50 | 3->3               | <input type="checkbox"/> |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 55 | 2->2               | <input type="checkbox"/> |

# DELTALIGHT

## NIME II AIR 92752

26412 9230 PRIM



**21012 0288**


LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

3->4



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**



**21012 0298**


LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

3 | 3



**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 48**



**21012 0480**


LED POWER SUPPLY 350mA-DC / 17W IP68

4(3)



**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**



**21012 0500**


LED POWER SUPPLY 500mA-DC / 24W IP68

4(2)



**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**



**21032 0295**


LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

3



**Dimtype: DALI**

**Cutout dimension (mm): 30**



**21032 0305**

LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5


3



**Dimtype: DALI**

**Cutout dimension (mm): 30**

### Mounting kits side air + light




**29810 0110** MOUNTING KIT SIDE AIR 105



**Cutout dimension (mm): 168**

### Mounting kits top air + light



**29810 0130** MOUNTING KIT TOP AIR 105




**Cutout dimension (mm): 135**

# DELTALIGHT

## NIME II AIR 92752

26412 9230 PRIM

### Mounting kits side air only




**29810 0100** MOUNTING KIT SIDE AIR ONLY 1

Cutout dimension (mm): 168

☐

### Mounting kits top air only



**29810 0200** MOUNTING KIT TOP AIR ONLY 1

Cutout dimension (mm): 135

☐

### Mounting kits no air



**29810 0120** MOUNTING KIT NO AIR 105

Cutout dimension (mm): 168

☐

Notes: