





## M26L - SPY 39 FRAMER 930 MDL

23431 9300 B

AVAILABLE IN  
**BLACK** 23431 9300 B



 [View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Low voltage systems Low voltage system mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3
<b>ADJUSTABILITY</b>	0° to 85° swiveling, 360° rotatable
<b>INFORMATION</b>	EXCL.LED POWER SUPPLY 48V-DC

### Electrical info

<b>ELECTRICAL</b>	48V-DC
<b>CLASS</b>	III
<b>DIM TYPE</b>	MDL = 1-10V or DALI or push button
<b>ENERGY CLASS</b>	E

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1018lm
<b>TM-30 VALUES</b>	rf: 90 / Rg: 99
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	1018lm // 8,6W // 118lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	347lm // 9,9W // 35lm/W

### Requirements

LED POWER SUPPLY 48V-DC

### Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : [23431\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## M26L - SPY 39 FRAMER 930 MDL

23431 9300 B

### FINISH YOUR SPECIFICATION


#### Current supply

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



**21032 0030** SMART 48 MODULATOR PLUG-IN WD

19

Dimtype: WDL = wireless dimmable


#### SMART 48

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


Min current | Max current



**300 90 011** SMART 48 MODULATOR DIM9

19

Dimtype: 1-10V or DALI or push button



**300 90 012** SMART 48 MODULATOR WD

19

Dimtype: WDL = wireless dimmable


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


Min current | Max current



**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN

10

Dimtype: non-dimmable



**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN


24

Dimtype: non-dimmable

# DELTALIGHT

## M26L - SPY 39 FRAMER 930 MDL

23431 9300 B




**21012 0230** LED POWER SUPPLY 48V-DC / 100W

10

**Dimtype: non-dimmable**

**Cutout dimension (mm): 40**



**21012 0240** LED POWER SUPPLY 48V-DC / 200W

20


**Dimtype: non-dimmable**

**Cutout dimension (mm): 40**


## COMPATIBLE COMPOSABLES

### SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)


### Available Colours




**23358 0000** SLM26L - PROFILE



**23358 0010** SLM26L - PROFILE 1m



**23358 0020** SLM26L - PROFILE 2m



**23358 0030** SLM26L - PROFILE 3m



Notes: