



## M26L - SPY 39 WALLWASH 927 MDL

23433 9200 BRA

AVAILABLE IN

- BLACK** 23433 9200 B
- BRUSHED ALU** 23433 9200 BRA
- BRUSHED ANTHRACITE** 23433 9200 BRAT
- BRUSHED COPPER** 23433 9200 BRCU
- BRUSHED GOLD** 23433 9200 BRG
- BRUSHED OLD BRONZE** 23433 9200 BROB
- FLEMISH BRONZE** 23433 9200 FBR
- FLEMISH GOLD** 23433 9200 FG
- GOLD COLOURED** 23433 9200 GC
- WHITE** 23433 9200 W



 [View on website](#)



General info	
<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Low voltage systems Low voltage system mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3
<b>ADJUSTABILITY</b>	0° to 85° swiveling, 360° rotatable
<b>INFORMATION</b>	WALLWASH LENS EXCL.LED POWER SUPPLY 48V-DC
Electrical info	
<b>ELECTRICAL</b>	48V-DC
<b>CLASS</b>	III
<b>DIM TYPE</b>	MDL = 1-10V or DALI or push button
<b>ENERGY CLASS</b>	E
Lightsource info	
<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8W / CRI>90 (R9: 60) / 2700K / 753lm
<b>TM-30 VALUES</b>	rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	753lm // 5,8W // 129lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	413lm // 6,7W // 62lm/W

### Requirements

LED POWER SUPPLY 48V-DC

### Options

DIMMABLE MODULATOR

# DELTALIGHT

## M26L - SPY 39 WALLWASH 927 MDL


23433 9200 BRA

For detailed installation instructions, please consult the manual : [23433\\_XXX0\\_HAND.pdf](#)

### FINISH YOUR SPECIFICATION

#### Current supply

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**21032 0030** SMART 48 MODULATOR PLUG-IN WD

19

Dimtype: WDL = wireless dimmable

#### SMART 48

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



**300 90 011** SMART 48 MODULATOR DIM9

19

Dimtype: 1-10V or DALI or push button




**300 90 012** SMART 48 MODULATOR WD

19

Dimtype: WDL = wireless dimmable

#### LED power supplies

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN


10

Dimtype: non-dimmable

# DELTALIGHT

## M26L - SPY 39 WALLWASH 927 MDL


23433 9200 BRA



**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN

24

Dimtype: non-dimmable




**21012 0230** LED POWER SUPPLY 48V-DC / 100W

10

Dimtype: non-dimmable

Cutout dimension (mm): 40



**21012 0240** LED POWER SUPPLY 48V-DC / 200W

20


Dimtype: non-dimmable

Cutout dimension (mm): 40


## COMPATIBLE COMPOSABLES

### SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)


### Available Colours




**23358 0000** SLM26L - PROFILE



**23358 0010** SLM26L - PROFILE 1m



**23358 0020** SLM26L - PROFILE 2m



**23358 0030** SLM26L - PROFILE 3m



Notes: