



M26L - OCTAV 39 93020 MDL

29021 9320 FG

AVAILABLE IN



BLACK 29021 9320 B

FLEMISH BRONZE 29021 9320 FBR

FLEMISH GOLD 29021 9320 FG

GOLD COLOURED 29021 9320 GC

WHITE 29021 9320 W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	0° to 85° swiveling, 360° rotatable
INFORMATION	REFLECTOR FL-20° EXCLLED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1089lm
TM-30 VALUES	rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	20°
LED TECHNICS (LIGHT SOURCE)	1089lm // 8,6W // 127lm/W
LED TECHNICS (LUMINAIRE)	683lm // 9,9W // 69lm/W

Remarks

Take a look at our **MAGNETIC PROFILES** movie

Requirements

SPY 39 L TUBE
LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : [29021_XXX0_HAND.pdf](#)

FINISH YOUR SPECIFICATION

Current supply

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



21032 0030 SMART 48 MODULATOR PLUG-IN WD

19

Dimtype: WDL = wireless dimmable

SMART 48

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



300 90 011 SMART 48 MODULATOR DIM9

19

Dimtype: 1-10V or DALI or push button



300 90 012 SMART 48 MODULATOR WD

19

Dimtype: WDL = wireless dimmable

LED power supplies

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN




10

Dimtype: non-dimmable


DELTALIGHT

M26L - OCTAV 39 93020 MDL



29021 9320 FG

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	24	☐
Dimtype: non-dimmable			
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	10	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	20	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			

Finish your product

	24144 0020 B SPY 39 L TUBE B	☐
	24144 0020 FBR SPY 39 L TUBE FBR	☐
	24144 0020 FG SPY 39 L TUBE FG	☐
	24144 0020 GC SPY 39 L TUBE GC	☐
	24144 0020 W SPY 39 L TUBE W	☐


COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)	Available Colours
	 
	 


DELTALIGHT

M26L - OCTAV 39 93020 MDL

29021 9320 FG



23358 0020 SLM26L - PROFILE 2m



23358 0030 SLM26L - PROFILE 3m



Notes: