
DELTALIGHT




M26L - BOXY R 93033 MDL

REFERENCE 10729 9320 B-B

AVAILABLE IN
BLACK-BLACK 10729 9320 B-B
BLACK-FLEMISH BRONZE 10729 9320 B-FBR
BLACK-FLEMISH GOLD 10729 9320 B-FG
WHITE-WHITE 10729 9320 W-W





View on website

General info	
LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.5
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 48V-DC

Electrical info	
ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1089lm
TM-30 VALUES	Rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	33°
LED TECHNICS (LIGHT SOURCE)	1089lm // 8,6W // 127lm/W
LED TECHNICS (LUMINAIRE)	852lm // 9,9W // 86lm/W

Remarks

Take a look at our MAGNETIC PROFILES movie

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

Accessories

BOXY HONEYCOMB
BOXY SOFTENING LENS
BOXY GLASS SBL

DELTALIGHT

M26L - BOXY R 93033 MDL

10729 9320 B-B

For detailed installation instructions, please consult the manual : **10729_XXX0_HAND.pdf**


FINISH YOUR SPECIFICATION

Current supply

# of Fixtures

Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



21032 0030 SMART 48 MODULATOR PLUG-IN WD — 19


Dimtype: WDL = wireless dimmable

SMART 48

# of Fixtures


Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



300 90 011 SMART 48 MODULATOR DIM9 — 19

Dimtype: 1-10V or DALI or push button



300 90 012 SMART 48 MODULATOR WD — 19


Dimtype: WDL = wireless dimmable

LED power supplies

# of Fixtures

Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.




300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN — 10

Dimtype: non-dimmable

DELTALIGHT


M26L - BOXY R 93033 MDL

10729 9320 B-B



300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN — 24


Dimtype: non-dimmable



21012 0230 LED POWER SUPPLY 48V-DC / 100W — 10

Dimtype: non-dimmable

Cutout dimension (mm): 40




21012 0240 LED POWER SUPPLY 48V-DC / 200W — 20

Dimtype: non-dimmable


Cutout dimension (mm): 40

Light altering devices




251 70 03 01 B BOXY HONEYCOMB B

251 70 03 01 W BOXY HONEYCOMB W



251 70 03 04 B BOXY SOFTENING LENS B

251 70 03 04 W BOXY SOFTENING LENS W



251 70 03 05 B BOXY GLASS SBL B





251 70 03 05 W BOXY GLASS SBL W

DELTALIGHT

M26L - BOXY R 93033 MDL

10729 9320 B-B

COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)	Available Colours
 **23358 0000** SLM26L - PROFILE	
 **23358 0010** SLM26L - PROFILE 1m	
 **23358 0020** SLM26L - PROFILE 2m	
 **23358 0030** SLM26L - PROFILE 3m	

Notes: