



TWEETER M TRIMLESS 92733

418 11 811 922 B-C

AVAILABLE IN
BLACK-CHROMED 418 11 811 922 B-C
WHITE-WHITE 418 11 811 922 W-W



 [View on website](#)



General info	
LOCATION	indoor
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - Ø KIT
RECESSED DEPTH (MM)	80
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.5
ADJUSTABILITY	0° to 45° swiveling, 355° rotatable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info	
CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
TM-30 VALUES	Rf: 89 / Rg: 100
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	33°
LED TECHNICS (LIGHT SOURCE)	1041lm // 8,6W // 121lm/W
LED TECHNICS (LUMINAIRE)	829lm // 10W // 84lm/W

Requirements	
MOUNTING KIT R102 TRIMLESS O.F.A.	
LED POWER SUPPLY 350 / 500mA-DC DIM (Remote)	

For detailed installation instructions, please consult the manual : [418_11_811_XXX_HAND.pdf](#)




TWEETER M TRIMLESS 92733

418 11 811 922 B-C

CEILING COMPATIBILITY










Ceiling Type	Mounting Kit	
 System ceiling	 15212 2010 - MOUNTING KIT R102 TRIMLESS O.F.A.	Required
 Plasterboard	 15212 2010 - MOUNTING KIT R102 TRIMLESS O.F.A.	Required
 Stucanet	 15212 2010 - MOUNTING KIT R102 TRIMLESS O.F.A.	Required
 Concrete + plaster	 15212 2010 - MOUNTING KIT R102 TRIMLESS O.F.A.	Required
 Lintel + plaster	 15212 2010 - MOUNTING KIT R102 TRIMLESS O.F.A.	Required
 Hollow-core slab + plaster	 15212 2010 - MOUNTING KIT R102 TRIMLESS O.F.A.	Required
 Stretched ceiling	 15212 0170 - MOUNTING KIT R102 TRIMLESS WSC	Required
	 15212 0090 - MOUNTING KIT R102 TRIMLESS CSC	Required

FINISH YOUR SPECIFICATION

LED power supplies		# of Fixtures
 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		Min current Max current
	300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 Dimtype: 1-10V Cutout dimension (mm): 30	1
	300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 Dimtype: DALI Cutout dimension (mm): 45	1
	300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL Dimtype: non-dimmable Cutout dimension (mm): 30	1









TWEETER M TRIMLESS 92733

418 11 811 922 B-C

	300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL Dimtype: WDL = wireless dimmable Cutout dimension (mm): 45	1	☐
	300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 Dimtype: 1-10V Cutout dimension (mm): 30	1	☐
	300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 Dimtype: DALI Cutout dimension (mm): 45	1	☐
	300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL Dimtype: non-dimmable Cutout dimension (mm): 30	1	☐
	300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL Dimtype: WDL = wireless dimmable Cutout dimension (mm): 45	1	☐
	300 90 61 LED POWER SUPPLY MULTI-POWER DIM6 Dimtype: mains (phase cut-off) or push button Cutout dimension (mm): 56	2 2	☐
	300 90 63 LED POWER SUPPLY MULTI-POWER DIM9 Dimtype: 1-10V or DALI or push button Cutout dimension (mm): 82	4(4) 4(4)	☐
	300 90 64 LED POWER SUPPLY MULTI-POWER DIM7 Dimtype: 1-10V or push button Cutout dimension (mm): 72	2(1) 2(1)	☐
	300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 Dimtype: 1-10V or DALI or push button	2	☐
	300 90 68 LED POWER SUPPLY MULTI-POWER DIM5 Dimtype: DALI Cutout dimension (mm): 72	2(2) 2(1)	☐

TWEETER M TRIMLESS 92733





418 11 811 922 B-C

	300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9 Dimtype: 1-10V or DALI or push button Cutout dimension (mm): 84	2->6(6) 6(4)	☐
	300 90 124 LED POWER SUPPLY MULTI-POWER DIM7 Dimtype: 1-10V or push button Cutout dimension (mm): 55	3(2) 2(1)	☐
	300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5 Dimtype: DALI Cutout dimension (mm): 55	2(1) 1(1)	☐
	300 90 135 LED POWER SUPPLY MULTI-POWER HV Dimtype: non-dimmable Cutout dimension (mm): 90	3->3 2->3	☐
	21012 004W LED POWER SUPPLY MULTI-POWER WDL Dimtype: WDL = wireless dimmable Cutout dimension (mm): 84	3(3) 3(3)	☐
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL Dimtype: WDL = wireless dimmable Cutout dimension (mm): 54	3 3	☐
	21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8 Dimtype: mains (phase cut-off) Cutout dimension (mm): 50	1	☐
	21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 Dimtype: mains (phase cut-off) Cutout dimension (mm): 55	1	☐
	21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 Dimtype: mains (phase cut-off) Cutout dimension (mm): 55	2->3	☐
	21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 Dimtype: mains (phase cut-off) Cutout dimension (mm): 48	2 2	☐


DELTALIGHT

TWEETER M TRIMLESS 92733



418 11 811 922 B-C

	21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68	2(2)	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 60			
	21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68	2(1)	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 60			
	21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	2	☐
Dimtype: DALI			
Cutout dimension (mm): 30			
	21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	2	☐
Dimtype: DALI			
Cutout dimension (mm): 30			

Mounting kits

	15212 2010 MOUNTING KIT R102 TRIMLESS O.F.A.	☐
Cutout dimension (mm): 127		

Mounting kits stretched ceiling

	15212 0090 MOUNTING KIT R102 TRIMLESS CSC	☐
	15212 0170 MOUNTING KIT R102 TRIMLESS WSC	☐

Notes:

DELTALIGHT

TWEETER M TRIMLESS 92733

418 11 811 922 B-C