



M26L - BOXY R 93033 MDL

10729 9320 W-W


AVAILABLE IN

BLACK-BLACK 10729 9320 B-B

BLACK-FLEMISH BRONZE 10729 9320 B-FBR

BLACK-FLEMISH GOLD 10729 9320 B-FG

WHITE-WHITE 10729 9320 W-W



[View on website](#)



General info	
LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.5
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 48V-DC

Electrical info	
ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1089lm
TM-30 VALUES	rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	33°
LED TECHNICS (LIGHT SOURCE)	1089lm // 8,6W // 127lm/W
LED TECHNICS (LUMINAIRE)	852lm // 9,9W // 86lm/W

Remarks
Take a look at our MAGNETIC PROFILES movie

Requirements
LED POWER SUPPLY 48V-DC

Options
DIMMABLE MODULATOR

Accessories
BOXY HONEYCOMB
BOXY SOFTENING LENS
BOXY GLASS SBL

For detailed installation instructions, please consult the manual : [10729_XXX0_HAND.pdf](#)

FINISH YOUR SPECIFICATION

Current supply		# of Fixtures		
		Min current Max current		
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.				
16 39 190 21032 0030 SMART 48 MODULATOR PLUG-IN WD Dimtype: WDL = wireless dimmable	19			
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.				
300 90 011 SMART 48 MODULATOR DIM9 Dimtype: 1-10V or DALI or push button			19	
300 90 012 SMART 48 MODULATOR WD Dimtype: WDL = wireless dimmable			19	
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.				
300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN Dimtype: non-dimmable			10	

DELTALIGHT

M26L - BOXY R 93033 MDL

10729 9320 W-W

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	24	☐
	Dimtype: non-dimmable		
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	10	☐
	Dimtype: non-dimmable		
	Cutout dimension (mm): 40		
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	20	☐
	Dimtype: non-dimmable		
	Cutout dimension (mm): 40		

Light altering devices

	251 70 03 01 B BOXY HONEYCOMB B	☐
	251 70 03 01 W BOXY HONEYCOMB W	☐
	251 70 03 04 B BOXY SOFTENING LENS B	☐
	251 70 03 04 W BOXY SOFTENING LENS W	☐
	251 70 03 05 B BOXY GLASS SBL B	☐
	251 70 03 05 W BOXY GLASS SBL W	☐

DELTA LIGHT


M26L - BOXY R 93033 MDL

10729 9320 W-W


COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)


Available Colours




32 **23358 0000** SLM26L - PROFILE



32 **23358 0010** SLM26L - PROFILE 1m



32 **23358 0020** SLM26L - PROFILE 2m



32 **23358 0030** SLM26L - PROFILE 3m



Notes: