
DELTALIGHT




SPY 39 ON FOCUS 930

REFERENCE 24174 9300 BRAT

AVAILABLE IN
BLACK 24174 9300 B
BRUSHED ALU 24174 9300 BRA
BRUSHED ANTHRACITE 24174 9300 BRAT
BRUSHED COPPER 24174 9300 BRCU
BRUSHED GOLD 24174 9300 BRG
BRUSHED OLD BRONZE 24174 9300 BROB
FLEMISH BRONZE 24174 9300 FBR
FLEMISH GOLD 24174 9300 FG
FULL WHITE 24174 9300 FW
GOLD COLOURED 24174 9300 GC
WHITE 24174 9300 W





View on website

General info	
LOCATION	indoor
INSTALLATION	Ceiling Surface mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	0° to 85° swiveling, 355° rotatable
INFORMATION	ADJUSTABLE BEAM 15°-45°

Electrical info	
CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	E
CERTIFICATES	LCA

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 734-1018lm
TM-30 VALUES	Rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	15°-45°
LED TECHNICS (LIGHT SOURCE)	1018lm // 8,6W // 118lm/W
LED TECHNICS (LUMINAIRE)	303lm // 9,9W // 31lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

Options

COVERSET R 90-100


SPY 39 ON FOCUS 930

24174 9300 BRAT

For detailed installation instructions, please consult the manual : **24174_XXX0_HAND.pdf**

FINISH YOUR SPECIFICATION


LED power supplies	# of Fixtures
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.	Min current | Max current



300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 — 2

Dimtype: 1-10V


Cutout dimension (mm): 30



300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 2

Dimtype: DALI


Cutout dimension (mm): 45



300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL — 2

Dimtype: non-dimmable


Cutout dimension (mm): 30



300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL — 2

Dimtype: WDL = wireless dimmable


Cutout dimension (mm): 45



300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 — 2

Dimtype: 1-10V


Cutout dimension (mm): 30



300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 2

Dimtype: DALI

Cutout dimension (mm): 45



300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL — 2


Dimtype: non-dimmable

Cutout dimension (mm): 30

DELTALIGHT

SPY 39 ON FOCUS 930


24174 9300 BRAT



300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL — 2

Dimtype: WDL = wireless dimmable


Cutout dimension (mm): 45



300 90 61 LED POWER SUPPLY MULTI-POWER DIM6 — 2 | 2

Dimtype: mains (phase cut-off) or push button


Cutout dimension (mm): 56



300 90 63 LED POWER SUPPLY MULTI-POWER DIM9 — 4(4) | 4(4)

Dimtype: 1-10V or DALI or push button


Cutout dimension (mm): 82



300 90 64 LED POWER SUPPLY MULTI-POWER DIM7 — 2(2) | 2(1)


Dimtype: 1-10V or push button

Cutout dimension (mm): 72



300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 — 2 | -


Dimtype: 1-10V or DALI or push button



300 90 68 LED POWER SUPPLY MULTI-POWER DIM5 — 2(2) | 2(1)

Dimtype: DALI


Cutout dimension (mm): 72



300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9 — 2->6(6) | 6(4)

Dimtype: 1-10V or DALI or push button


Cutout dimension (mm): 84



300 90 124 LED POWER SUPPLY MULTI-POWER DIM7 — 2(2) | 2(1)

Dimtype: 1-10V or push button


Cutout dimension (mm): 55



300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5 — 2(2) | 2(1)

Dimtype: DALI

Cutout dimension (mm): 55



300 90 135 LED POWER SUPPLY MULTI-POWER HV — 3->4 | 2->4


Dimtype: non-dimmable

Cutout dimension (mm): 90

DELTALIGHT

SPY 39 ON FOCUS 930


24174 9300 BRAT



21012 0010 LED POWER SUPPLY MULTI POWER 2 | 2

Dimtype: non-dimmable


Cutout dimension (mm): 50



21012 0021 LED POWER SUPPLY MULTI POWER DIM1 3 | 3

Dimtype: 1-10V


Cutout dimension (mm): 54



21012 0035 LED POWER SUPPLY MULTI POWER DIM5 3 | 3

Dimtype: DALI


Cutout dimension (mm): 54



21012 004W LED POWER SUPPLY MULTI-POWER WDL 4(4) | 3(3)

Dimtype: WDL = wireless dimmable


Cutout dimension (mm): 84



21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL 3 | 3

Dimtype: WDL = wireless dimmable


Cutout dimension (mm): 54



21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 2->2 | 2->2

Dimtype: mains (phase cut-off)


Cutout dimension (mm): 50



21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 1

Dimtype: mains (phase cut-off)


Cutout dimension (mm): 55



21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 2->3

Dimtype: mains (phase cut-off)


Cutout dimension (mm): 55



21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 2 | 2

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 48



21012 0308 LED POWER SUPPLY 350mA / 7,35W DIM8 1


Dimtype: mains (phase cut-off)

Cutout dimension (mm): 40

DELTALIGHT

SPY 39 ON FOCUS 930


24174 9300 BRAT



21012 0318 LED POWER SUPPLY 500mA / 10W DIM8 — 1

Dimtype: mains (phase cut-off)


Cutout dimension (mm): 40



21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68 — 2(2)

Dimtype: non-dimmable


Cutout dimension (mm): 60



21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68 — 2(1)

Dimtype: non-dimmable


Cutout dimension (mm): 60



21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 2

Dimtype: DALI

Cutout dimension (mm): 30




21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 2

Dimtype: DALI

Cutout dimension (mm): 30

Coversets



204 00 100 ANO COVERSET R 100 ANO

204 00 100 B COVERSET R 100 B

204 00 100 W COVERSET R 100 W

Notes: