
DELTALIGHT



# M26L - SPY 39 FOCUS 930 MDL


**REFERENCE** 23429 9300 BRA

AVAILABLE IN
**BLACK** 23429 9300 B
**BRUSHED ALU** 23429 9300 BRA
**BRUSHED ANTHRACITE** 23429 9300 BRAT
**BRUSHED COPPER** 23429 9300 BRCU
**BRUSHED GOLD** 23429 9300 BRG
**BRUSHED OLD BRONZE** 23429 9300 BROB
**FLEMISH BRONZE** 23429 9300 FBR
**FLEMISH GOLD** 23429 9300 FG
**GOLD COLOURED** 23429 9300 GC
**WHITE** 23429 9300 W










View on website

| General info | |
|---|---|
| **LOCATION** | indoor |
| **INSTALLATION** | Low voltage systems Low voltage system mounted |
| **INGRESS PROTECTION** | IP20 |
| **WEIGHT (KG)** | 0.3 |
| **ADJUSTABILITY** | 0° to 85° swiveling, 360° rotatable |
| **INFORMATION** | ADJUSTABLE BEAM 15°-45°<br>EXCL.LED POWER SUPPLY 48V-DC |

| Electrical info | |
|---|---|
| **ELECTRICAL** | 48V-DC |
| **CLASS** | III |
| **DIM TYPE** | MDL = 1-10V or DALI or push button |
| **ENERGY CLASS** | E |
| **CERTIFICATES** | EPD |

| Lightsource info | |
|---|---|
| **LIGHTSOURCE NAME** | LED |
| **LIGHTSOURCE** | LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1018lm |
| **TM-30 VALUES** | Rf: 90 / Rg: 99 |
| **SDCM** | SDCM1 |
| **RISKGROUP** | RG1 |
| **LM80** | L90B10 > 50000 |
| **BEAMANGLE** | 15°-45° |
| **LED TECHNICS (LIGHT SOURCE)** | 1018lm // 8,6W // 118lm/W |
| **LED TECHNICS (LUMINAIRE)** | 303lm // 9,9W // 31lm/W |

**Requirements**

LED POWER SUPPLY 48V-DC

**Options**

DIMMABLE MODULATOR

DELTALIGHT

# M26L - SPY 39 FOCUS 930 MDL

23429 9300 BRA

For detailed installation instructions, please consult the manual : **23429_XXX0_HAND.pdf**


## FINISH YOUR SPECIFICATION

### Current supply

**# of Fixtures**

**Min current | Max current**

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.




**21032 0030** SMART 48 MODULATOR PLUG-IN WD — 19


**Dimtype: WDL = wireless dimmable**

### SMART 48

**# of Fixtures**


**Min current | Max current**

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.




**300 90 011** SMART 48 MODULATOR DIM9 — 19

**Dimtype: 1-10V or DALI or push button**




**300 90 012** SMART 48 MODULATOR WD — 19


**Dimtype: WDL = wireless dimmable**

### LED power supplies

**# of Fixtures**

**Min current | Max current**

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.





**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN — 10

**Dimtype: non-dimmable**

DELTALIGHT


# M26L - SPY 39 FOCUS 930 MDL

23429 9300 BRA




**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN — 24


**Dimtype: non-dimmable**




**21012 0230** LED POWER SUPPLY 48V-DC / 100W — 10

**Dimtype: non-dimmable**

**Cutout dimension (mm): 40**








**21012 0240** LED POWER SUPPLY 48V-DC / 200W — 20

**Dimtype: non-dimmable**

**Cutout dimension (mm): 40**

## COMPATIBLE COMPOSABLES

| SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX) | Available Colours |
|---|---|
|  **23358 0000** SLM26L - PROFILE | |
|  **23358 0010** SLM26L - PROFILE 1m | |
|  **23358 0020** SLM26L - PROFILE 2m | |
|  **23358 0030** SLM26L - PROFILE 3m | |

Notes: