



M26L - BOXY R SOFT 93045 MDL

10730 9030 B-FBR



AVAILABLE IN

BLACK-BLACK 10730 9030 B-B

BLACK-FLEMISH BRONZE 10730 9030 B-FBR

BLACK-FLEMISH GOLD 10730 9030 B-FG

WHITE-WHITE 10730 9030 W-W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.5
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR WFL-45° EXCL.LED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	F
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 10,2W / CRI>90 (R9: 50) / 3000K-1800K / 1038lm
SDCM	SDCM2
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	45°
LED TECHNICS (LIGHT SOURCE)	1038lm // 10,2W // 109lm/W
LED TECHNICS (LUMINAIRE)	794lm // 11,7W // 68lm/W

Remarks

[Take a look at our MAGNETIC PROFILES movie](#)

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

Accessories

BOXY HONEYCOMB
BOXY SOFTENING LENS
BOXY GLASS SBL

For detailed installation instructions, please consult the manual : [10730_XXX0_HAND.pdf](#)




FINISH YOUR SPECIFICATION

Current supply		# of Fixtures		
		Min current Max current		
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.				
1639190	21032 0030 SMART 48 MODULATOR PLUG-IN WD Dimtype: WDL = wireless dimmable	27		
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.				
569378			300 90 011 SMART 48 MODULATOR DIM9 Dimtype: 1-10V or DALI or push button	27
569378			300 90 012 SMART 48 MODULATOR WD Dimtype: WDL = wireless dimmable	27
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.				
5510090			300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN Dimtype: non-dimmable	14

DELTALIGHT

M26L - BOXY R SOFT 93045 MDL

10730 9030 B-FBR

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	34	☐
Dimtype: non-dimmable			
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	14	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	29	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			

Light altering devices





	251 70 03 01 B BOXY HONEYCOMB B	☐
	251 70 03 01 W BOXY HONEYCOMB W	☐
	251 70 03 04 B BOXY SOFTENING LENS B	☐
	251 70 03 04 W BOXY SOFTENING LENS W	☐
	251 70 03 05 B BOXY GLASS SBL B	☐
	251 70 03 05 W BOXY GLASS SBL W	☐

DELTALIGHT

M26L - BOXY R SOFT 93045 MDL

10730 9030 B-FBR

COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)		Available Colours
	23358 0000 SLM26L - PROFILE	 
	23358 0010 SLM26L - PROFILE 1m	 
	23358 0020 SLM26L - PROFILE 2m	         
	23358 0030 SLM26L - PROFILE 3m	         

Notes: