



## OCTAV 39 CLIP 93040

29016 9330 FG-B

AVAILABLE IN



**BLACK-BLACK** 29016 9330 B-B

**FLEMISH BRONZE-BLACK** 29016 9330 FBR-B

**FLEMISH GOLD-BLACK** 29016 9330 FG-B

**GOLD COLORED-BLACK** 29016 9330 GC-B

**WHITE-WHITE** 29016 9330 W-W



[View on website](#)



### General info

|                               |                                                         |
|-------------------------------|---------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                  |
| <b>INSTALLATION</b>           | Ceiling Semi-recessed                                   |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - 43                                              |
| <b>RECESSED DEPTH (MM)</b>    | 40                                                      |
| <b>INGRESS PROTECTION</b>     | IP20                                                    |
| <b>WEIGHT (KG)</b>            | 0.3                                                     |
| <b>ADJUSTABILITY</b>          | 0° to 85° swiveling, 355° rotatable                     |
| <b>INFORMATION</b>            | REFLECTOR WFL-40°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | E                         |
| <b>CERTIFICATES</b> | CB, ENEC                  |

### Lightsource info

|                                    |                                                           |
|------------------------------------|-----------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                       |
| <b>LIGHTSOURCE</b>                 | LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm |
| <b>TM-30 VALUES</b>                | rf: 90 / Rg: 99                                           |
| <b>SDCM</b>                        | SDCM1                                                     |
| <b>RISKGROUP</b>                   | RG1                                                       |
| <b>LM80</b>                        | L90B10 > 50000                                            |
| <b>BEAMANGLE</b>                   | 40°                                                       |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1089lm // 8,6W // 127lm/W                                 |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 737lm // 9,9W // 75lm/W                                   |

### Requirements

SPY 39 L TUBE

LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : [29016\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## OCTAV 39 CLIP 93040

29016 9330 FG-B

### CEILING COMPATIBILITY

| Ceiling Type                                                                                       | Mounting Kit |
|----------------------------------------------------------------------------------------------------|--------------|
|  System ceiling    | -            |
|  Plasterboard      | -            |
|  Wood              | -            |
|  Concrete          | -            |
|  Hollow-core slab  | -            |
|  Stretched ceiling | -            |

### FINISH YOUR SPECIFICATION


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30



**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2











Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45

# DELTALIGHT

## OCTAV 39 CLIP 93040











29016 9330 FG-B

|                                                                                    |                                                                          |                |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|----------------|--------------------------|
|    | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V                                                           |                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                |                          |
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                |                          |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                |                          |
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                |                          |
|  | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 2   2          | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |                |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |                |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 4(4)   4(4)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |                |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                |                          |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9    | 2   -          | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5                       | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                |                          |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9                    | 2->6(6)   6(4) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 84                                                |                |                          |

# DELTALIGHT

## OCTAV 39 CLIP 93040









29016 9330 FG-B

|                                                                                    |                                                                                                                                                   |                                      |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------|
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype: 1-10V or push button</b><br><b>Cutout dimension (mm): 55</b>                | 3(2)   2(1) <input type="checkbox"/> |
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 55</b>                           | 2(2)   2(1) <input type="checkbox"/> |
|    | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br><b>Dimtype: non-dimmable</b><br><b>Cutout dimension (mm): 90</b>                          | 3->4   2->4 <input type="checkbox"/> |
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><b>Dimtype: non-dimmable</b><br><b>Cutout dimension (mm): 50</b>                             | 2   2 <input type="checkbox"/>       |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><b>Dimtype: 1-10V</b><br><b>Cutout dimension (mm): 54</b>                               | 3   3 <input type="checkbox"/>       |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 54</b>                                | 3   3 <input type="checkbox"/>       |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><b>Dimtype: WDL = wireless dimmable</b><br><b>Cutout dimension (mm): 84</b>              | 4(4)   3(3) <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><b>Dimtype: WDL = wireless dimmable</b><br><b>Cutout dimension (mm): 54</b>      | 3   3 <input type="checkbox"/>       |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><b>Dimtype: mains (phase cut-off)</b><br><b>Cutout dimension (mm): 50</b> | 2->2   0 <input type="checkbox"/>    |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><b>Dimtype: mains (phase cut-off)</b><br><b>Cutout dimension (mm): 55</b> | 1 <input type="checkbox"/>           |


# DELTALIGHT

## OCTAV 39 CLIP 93040

29016 9330 FG-B

|                                                                                    |                                                                                                                                                   |       |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------|-------|--------------------------|
|    | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><b>Dimtype: mains (phase cut-off)</b><br><b>Cutout dimension (mm): 55</b> | 2->3  | <input type="checkbox"/> |
|    | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><b>Dimtype: mains (phase cut-off)</b><br><b>Cutout dimension (mm): 48</b> | 2   2 | <input type="checkbox"/> |
|    | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><b>Dimtype: mains (phase cut-off)</b><br><b>Cutout dimension (mm): 40</b>             | 1     | <input type="checkbox"/> |
|    | <b>21012 0318</b><br>LED POWER SUPPLY 500mA / 10W DIM8<br><b>Dimtype: mains (phase cut-off)</b><br><b>Cutout dimension (mm): 40</b>               | 1     | <input type="checkbox"/> |
|  | <b>21012 0480</b><br>LED POWER SUPPLY 350mA-DC / 17W IP68<br><b>Dimtype: non-dimmable</b><br><b>Cutout dimension (mm): 60</b>                     | 2(2)  | <input type="checkbox"/> |
|  | <b>21012 0500</b><br>LED POWER SUPPLY 500mA-DC / 24W IP68<br><b>Dimtype: non-dimmable</b><br><b>Cutout dimension (mm): 60</b>                     | 2(1)  | <input type="checkbox"/> |
|  | <b>21032 0295</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 30</b>               | 2     | <input type="checkbox"/> |
|  | <b>21032 0305</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 30</b>               | 2     | <input type="checkbox"/> |

### Finish your product

|                                                                                    |                                        |  |                          |
|------------------------------------------------------------------------------------|----------------------------------------|--|--------------------------|
|  | <b>24144 0020 B</b><br>SPY 39 L TUBE B |  | <input type="checkbox"/> |
|------------------------------------------------------------------------------------|----------------------------------------|--|--------------------------|

# DELTALIGHT

## OCTAV 39 CLIP 93040

29016 9330 FG-B

|                              |                   |                          |
|------------------------------|-------------------|--------------------------|
| <b><u>24144 0020 FBR</u></b> | SPY 39 L TUBE FBR | <input type="checkbox"/> |
| <b><u>24144 0020 FG</u></b>  | SPY 39 L TUBE FG  | <input type="checkbox"/> |
| <b><u>24144 0020 GC</u></b>  | SPY 39 L TUBE GC  | <input type="checkbox"/> |
| <b><u>24144 0020 W</u></b>   | SPY 39 L TUBE W   | <input type="checkbox"/> |

Notes: