



## LUNELLE 52 TRIMLESS 92730

32811 9220 BRA

AVAILABLE IN

**BRUSHED ALU** 32811 9220 BRA



**BRUSHED ANTHRACITE** 32811 9220 BRAT

**BRUSHED BROWN BRONZE** 32811 9220 BRBB

**BRUSHED COPPER** 32811 9220 BRCU

**BRUSHED GOLD** 32811 9220 BRG

**BRUSHED OLD BRONZE** 32811 9220 BROB



 [View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Semi-recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	round - Ø kit
<b>RECESSED DEPTH (MM)</b>	80
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	G

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED 5,6W / CRI>90 (R9: 80) / 2700K / 485lm
<b>SDCM</b>	SDCM3
<b>RISKGROUP</b>	RG2
<b>BEAMANGLE</b>	30°
<b>LED TECHNICS (LIGHT SOURCE)</b>	485lm // 5,6W // 86lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	388lm // 6,4W // 60lm/W

### Requirements

MOUNTING KIT R53 TRIMLESS  
LED POWER SUPPLY 500mA-DC

### Accessories

VISOR 52









For detailed installation instructions, please consult the manual : [32811\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## LUNELLE 52 TRIMLESS 92730

32811 9220 BRA

### CEILING COMPATIBILITY

Ceiling Type	Mounting Kit	
 <b>Plasterboard</b>	 32210 0050 - MOUNTING KIT R53 TRIMLESS O.F.A.	<b>Required</b>
 <b>Concrete + plaster</b>	 32210 0050 - MOUNTING KIT R53 TRIMLESS O.F.A.	<b>Required</b>
 <b>Lintel + plaster</b>	 32210 0050 - MOUNTING KIT R53 TRIMLESS O.F.A.	<b>Required</b>
 <b>Hollow-core slab + plaster</b>	 32210 0050 - MOUNTING KIT R53 TRIMLESS O.F.A.	<b>Required</b>

### FINISH YOUR SPECIFICATION


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

1 -> 6 (6)

**Dimtype: 1-10V or DALI or push button**

**Cutout dimension (mm): 82**




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

1 -> 4 (2)

**Dimtype: DALI**

**Cutout dimension (mm): 72**




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9

1 -> 10 (7)

**Dimtype: 1-10V or DALI or push button**

**Cutout dimension (mm): 84**




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7

1 -> 3 (2)

**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 55**



**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

1 -> 3 (2)


**Dimtype: DALI**

**Cutout dimension (mm): 55**

# DELTALIGHT

## LUNELLE 52 TRIMLESS 92730

32811 9220 BRA




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

1 -> 4



Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 54



**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1 -> 3



Dimtype: mains (phase cut-off)

Cutout dimension (mm): 48



**21012 0595** LED POWER SUPPLY 500mA-DC 10W DIM5

1 -> 1



Dimtype: DALI

Cutout dimension (mm): 35

### Mounting kits



**32210 0050** MOUNTING KIT R53 TRIMLESS O.F.A.



Cutout dimension (mm): 82

### Light altering devices



**32810 0010 DC** VISOR 52 DC



Notes: