



## M26L - SPY 39 FOCUS 930 MDL

23429 9300 GC

AVAILABLE IN

**BLACK** 23429 9300 B

**BRUSHED ALU** 23429 9300 BRA

**BRUSHED ANTHRACITE** 23429 9300 BRAT

**BRUSHED COPPER** 23429 9300 BRCU

**BRUSHED GOLD** 23429 9300 BRG


**BRUSHED OLD BRONZE** 23429 9300 BROB

**FLEMISH BRONZE** 23429 9300 FBR

**FLEMISH GOLD** 23429 9300 FG

**GOLD COLOURED** 23429 9300 GC

**WHITE** 23429 9300 W



[View on website](#)



| General info                |                                                        |
|-----------------------------|--------------------------------------------------------|
| LOCATION                    | indoor                                                 |
| INSTALLATION                | Low voltage systems Low voltage system mounted         |
| INGRESS PROTECTION          | IP20                                                   |
| WEIGHT (KG)                 | 0.3                                                    |
| ADJUSTABILITY               | 0° to 85° swiveling, 360° rotatable                    |
| INFORMATION                 | ADJUSTABLE BEAM 15°-45°<br>EXCLLED POWER SUPPLY 48V-DC |
| Electrical info             |                                                        |
| ELECTRICAL                  | 48V-DC                                                 |
| CLASS                       | III                                                    |
| DIM TYPE                    | MDL = 1-10V or DALI or push button                     |
| ENERGY CLASS                | E                                                      |
| Lightsource info            |                                                        |
| LIGHTSOURCE NAME            | LED                                                    |
| LIGHTSOURCE                 | LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1018lm      |
| TM-30 VALUES                | rf: 90 / Rg: 99                                        |
| SDCM                        | SDCM1                                                  |
| RISKGROUP                   | RG1                                                    |
| LM80                        | L90B10 > 50000                                         |
| BEAMANGLE                   | 15°-45°                                                |
| LED TECHNICS (LIGHT SOURCE) | 1018lm // 8,6W // 118lm/W                              |
| LED TECHNICS (LUMINAIRE)    | 303lm // 9,9W // 31lm/W                                |

### Requirements

LED POWER SUPPLY 48V-DC

### Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : [23429\\_XXX0\\_HAND.pdf](#)

FINISH YOUR SPECIFICATION

| Current supply                                                                                                                                                                                                                                                                                                             |    | # of Fixtures             |    |             |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----|---------------------------|----|-------------|
|                                                                                                                                                                                                                                                                                                                            |    | Min current   Max current |    |             |
| <div><div><div><div></div><div></div></div><div># of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</div></div></div> |    |                           |    |             |
| <div><div><div><div><div></div><div></div></div><div></div></div><div></div></div><div>1639190</div></div> <div>21032 0030 SMART 48 MODULATOR PLUG-IN WD</div> <div>Dimtype: WDL = wireless dimmable</div>                                                                                                                 | 19 | <div></div>               |    |             |
| <div><div><div><div></div><div></div></div><div># of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</div></div></div> |    |                           |    |             |
| <div><div><div><div><div></div><div></div></div><div></div></div><div></div></div><div>569378</div></div> <div>300 90 011 SMART 48 MODULATOR DIM9</div> <div>Dimtype: 1-10V or DALI or push button</div>                                                                                                                   |    |                           | 19 | <div></div> |
| <div><div><div><div><div></div><div></div></div><div></div></div><div></div></div><div>569378</div></div> <div>300 90 012 SMART 48 MODULATOR WD</div> <div>Dimtype: WDL = wireless dimmable</div>                                                                                                                          |    |                           | 19 | <div></div> |
| <div><div><div><div></div><div></div></div><div># of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</div></div></div> |    |                           |    |             |
| <div><div><div><div><div></div><div></div></div><div></div></div><div></div></div><div>5510090</div></div> <div>300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN</div> <div>Dimtype: non-dimmable</div>                                                                                                                    |    |                           | 10 | <div></div> |

# DELTALIGHT

## M26L - SPY 39 FOCUS 930 MDL

23429 9300 GC

|                                                                                  |                                                         |    |                          |
|----------------------------------------------------------------------------------|---------------------------------------------------------|----|--------------------------|
|  | <b>300 89 48 240</b> LED POWER SUPPLY 48V-DC / 240W DIN | 24 | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                            |                                                         |    |                          |
|  | <b>21012 0230</b> LED POWER SUPPLY 48V-DC / 100W        | 10 | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                            |                                                         |    |                          |
| Cutout dimension (mm): 40                                                        |                                                         |    |                          |
|  | <b>21012 0240</b> LED POWER SUPPLY 48V-DC / 200W        | 20 | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                            |                                                         |    |                          |
| Cutout dimension (mm): 40                                                        |                                                         |    |                          |

### COMPATIBLE COMPOSABLES

| SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)                                                                          | Available Colours                                                                     |
|---------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|
|  <b>23358 0000</b> SLM26L - PROFILE    |  |
|  <b>23358 0010</b> SLM26L - PROFILE 1m |  |
|  <b>23358 0020</b> SLM26L - PROFILE 2m |  |
|  <b>23358 0030</b> SLM26L - PROFILE 3m |  |

Notes: