



DEEP RINGO LED 92733

202 272 811 922 FBR

AVAILABLE IN

NOIR 202 272 811 922 B

ALU BROSSÉ 202 272 811 922 BRA

ANTHRACITE BROSSÉ 202 272 811 922 BRAT

BRONZE BRUN BROSSÉ 202 272 811 922 BRBB

CUIVRE BROSSÉ 202 272 811 922 BRCU

OR BROSSÉ 202 272 811 922 BRG

BRONZE VIEUX BROSSÉ 202 272 811 922 BROB

CRÈME 202 272 811 922 CR



FLEMISH BRONZE 202 272 811 922 FBR

FLEMISH GOLD 202 272 811 922 FG

COULEUR OR 202 272 811 922 GC

NOIR PIANO 202 272 811 922 PB

BLANC 202 272 811 922 W



[View on website](#)



General info

LOCATION	interieur
INSTALLATION	Plafond Encastré
CUTOUT SHAPE/SIZE (MM)	circulaire - 76
RECESSED DEPTH (MM)	90
THICKNESS OF MOUNTING SURFACE (MM)	min.5
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.2
ADJUSTABILITY	non réglable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
DIM TYPE	selon le type d'alimentation externe
ENERGY CLASS	E
CERTIFICATION	CB, EAC, ENEC, EPD, LCA

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
RVALUES	rf: 89 / Rg: 100
SDMC	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	33°
LED TECHNICS (LIGHT SOURCE)	1041lm // 8,6W // 121lm/W
LED TECHNICS (LUMINAIRE)	768lm // 9,9W // 78lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM


For detailed installation instructions, please consult the manual : [202_272_811_XXX_HAND.pdf](#)

CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Concrete	-
 Concrete + plaster	-
 Lintel + plaster	-
 Hollow-core slab	-
 Hollow-core slab + plaster	-
 Stretched ceiling	-

FINISH YOUR SPECIFICATION

les batteries de secours

	21032 0270 B EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B	☐
	21032 0270 W EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W	☐

DELTALIGHT

DEEP RINGO LED 92733

202 272 811 922 FBR


les alimentations led

of Fixtures



web2print_power_supply_info_box

Min current | Max current



300 48 350 ED1


LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1

☐

Dimtype: 1 à 10 V

Cutout dimension (mm): 30



300 48 350 ED5


LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

☐

Dimtype: DALI

Cutout dimension (mm): 45



300 48 350 MDL


LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1

☐

Dimtype: non dimmable

Cutout dimension (mm): 30



300 48 350 WDL


LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1

☐

Dimtype: WDL = dimmable sans fil

Cutout dimension (mm): 45



300 48 500 ED1


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1

☐

Dimtype: 1 à 10 V

Cutout dimension (mm): 30



300 48 500 ED5


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1

☐

Dimtype: DALI

Cutout dimension (mm): 45



300 48 500 MDL


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1

☐

Dimtype: non dimmable

Cutout dimension (mm): 30



300 48 500 WDL


LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1

☐

Dimtype: WDL = dimmable sans fil

Cutout dimension (mm): 45



300 90 61

LED POWER SUPPLY MULTI-POWER DIM6

2 | 2











☐

Dimtype: fin de phase ou bouton poussoir

Cutout dimension (mm): 56









DEEP RINGO LED 92733

202 272 811 922 FBR

	<u>300 90 63</u> LED POWER SUPPLY MULTI-POWER DIM9	4(4) 4(4)	☐
Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
Cutout dimension (mm): 82			
	<u>300 90 64</u> LED POWER SUPPLY MULTI-POWER DIM7	2(1) 2(1)	☐
Dimtype: 1 à 10 V ou bouton poussoir			
Cutout dimension (mm): 72			
	<u>300 90 67</u> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9	2	☐
Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
	<u>300 90 68</u> LED POWER SUPPLY MULTI-POWER DIM5	2(2) 2(1)	☐
Dimtype: DALI			
Cutout dimension (mm): 72			
	<u>300 90 69</u> LED POWER SUPPLY MULTI-POWER HV DIM9	2->6(6) 6(4)	☐
Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
Cutout dimension (mm): 84			
	<u>300 90 124</u> LED POWER SUPPLY MULTI-POWER DIM7	3(2) 2(1)	☐
Dimtype: 1 à 10 V ou bouton poussoir			
Cutout dimension (mm): 55			
	<u>300 90 125</u> LED POWER SUPPLY MULTI-POWER MINI DIM5	2(2) 2(1)	☐
Dimtype: DALI			
Cutout dimension (mm): 55			
	<u>300 90 135</u> LED POWER SUPPLY MULTI-POWER HV	3->3 2->3	☐
Dimtype: non dimmable			
Cutout dimension (mm): 90			
	<u>21012 004W</u> LED POWER SUPPLY MULTI-POWER WDL	3(3) 3(3)	☐
Dimtype: WDL = dimmable sans fil			
Cutout dimension (mm): 84			
	<u>21012 005W</u> LED POWER SUPPLY MULTI-POWER COMPACT WDL	3 3	☐
Dimtype: WDL = dimmable sans fil			
Cutout dimension (mm): 54			

DEEP RINGO LED 92733

202 272 811 922 FBR

	21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8 Dimtype: fin de phase Cutout dimension (mm): 50	1	☐
	21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 Dimtype: fin de phase Cutout dimension (mm): 55	1	☐
	21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 Dimtype: fin de phase Cutout dimension (mm): 55	2->3	☐
	21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 Dimtype: fin de phase Cutout dimension (mm): 48	2 2	☐
	21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68 Dimtype: non dimmable Cutout dimension (mm): 60	2(2)	☐
	21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68 Dimtype: non dimmable Cutout dimension (mm): 60	2(1)	☐
	21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 Dimtype: DALI Cutout dimension (mm): 30	2	☐
	21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 Dimtype: DALI Cutout dimension (mm): 30	2	☐

Notes: