



## SPY 39 PLUG FOCUS 930

24176 9300 FG

AVAILABLE IN

**NOIR** 24176 9300 B

**ALU BROSSÉ** 24176 9300 BRA

**ANTHRACITE BROSSÉ** 24176 9300 BRAT

**CUIVRE BROSSÉ** 24176 9300 BRCU

**OR BROSSÉ** 24176 9300 BRG

**BRONZE VIEUX BROSSÉ** 24176 9300 BROB

**FLEMISH BRONZE** 24176 9300 FBR

**FLEMISH GOLD** 24176 9300 FG

**ENTIÈREMENT BLANC** 24176 9300 FW

**COULEUR OR** 24176 9300 GC

**BLANC** 24176 9300 W



[View on website](#)



### General info

|                               |                                   |
|-------------------------------|-----------------------------------|
| <b>LOCATION</b>               | interieur                         |
| <b>INSTALLATION</b>           | Plafond Semi-encastré             |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | circulaire - Ø KIT                |
| <b>RECESSED DEPTH (MM)</b>    | 80                                |
| <b>INGRESS PROTECTION</b>     | IP20                              |
| <b>WEIGHT (KG)</b>            | 0.4                               |
| <b>ADJUSTABILITY</b>          | 0° à 85° inclinable, 355° rotatif |
| <b>INFORMATION</b>            | ADJUSTABLE BEAM 15°-45°           |

### Electrical info

|                      |                                      |
|----------------------|--------------------------------------|
| <b>CLASS</b>         | III                                  |
| <b>DIM TYPE</b>      | selon le type d'alimentation externe |
| <b>ENERGY CLASS</b>  | E                                    |
| <b>CERTIFICATION</b> | CB, ENEC                             |

### Lightsource info

|                                    |                                                           |
|------------------------------------|-----------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                       |
| <b>LIGHTSOURCE</b>                 | LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 734-1018lm |
| <b>RVALUES</b>                     | rf: 90 / Rg: 99                                           |
| <b>SDMC</b>                        | SDCM1                                                     |
| <b>RISKGROUP</b>                   | RG1                                                       |
| <b>LM80</b>                        | L90B10 > 50000                                            |
| <b>BEAMANGLE</b>                   | 15°-45°                                                   |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1018lm // 8,6W // 118lm/W                                 |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 303lm // 9,9W // 31lm/W                                   |

### Requirements

MOUNTING KIT PLUG O.F.A.

LED POWER SUPPLY 350 / 500mA-DC DIM

# DELTALIGHT

## SPY 39 PLUG FOCUS 930





24176 9300 FG

For detailed installation instructions, please consult the manual : [24176\\_XXX0\\_HAND.pdf](#)

### CEILING COMPATIBILITY





| Ceiling Type                                                                                                       | Mounting Kit                                                                                                            |          |
|--------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|----------|
|  <b>Plasterboard</b>               |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Concrete + plaster</b>         |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Lintel + plaster</b>           |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Hollow-core slab + plaster</b> |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |

### FINISH YOUR SPECIFICATION

| les alimentations led                                                                                                               |                                                                                                                                                        | # of Fixtures              |
|-------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------|
|  <a href="#">web2print_power_supply_info_box</a> |                                                                                                                                                        | Min current   Max current  |
|                                                   | <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1<br><b>Dimtype: 1 à 10 V</b><br><b>Cutout dimension (mm): 30</b>               | 2 <input type="checkbox"/> |
|                                                   | <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><b>Dimtype: DALI</b><br><b>Cutout dimension (mm): 45</b>                   | 2 <input type="checkbox"/> |
|                                                   | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL<br><b>Dimtype: non dimmable</b><br><b>Cutout dimension (mm): 30</b>            | 2 <input type="checkbox"/> |
|                                                   | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br><b>Dimtype: WDL = dimmable sans fil</b><br><b>Cutout dimension (mm): 45</b> | 2 <input type="checkbox"/> |

SPY 39 PLUG FOCUS 930






24176 9300 FG

|                                                                                    |                                                     |                                                      |                |                          |
|------------------------------------------------------------------------------------|-----------------------------------------------------|------------------------------------------------------|----------------|--------------------------|
|    | <b>300 48 500 ED1</b>                               | LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1   | 2              | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> 1 à 10 V                            |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 30                    |                                                      |                |                          |
|    | <b>300 48 500 ED5</b>                               | LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5   | 2              | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> DALI                                |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 45                    |                                                      |                |                          |
|    | <b>300 48 500 MDL</b>                               | LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL    | 2              | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> non dimmable                        |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 30                    |                                                      |                |                          |
|    | <b>300 48 500 WDL</b>                               | LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL    | 2              | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> WDL = dimmable sans fil             |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 45                    |                                                      |                |                          |
|  | <b>300 90 61</b>                                    | LED POWER SUPPLY MULTI-POWER DIM6                    | 2   2          | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> fin de phase ou bouton poussoir     |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 56                    |                                                      |                |                          |
|  | <b>300 90 63</b>                                    | LED POWER SUPPLY MULTI-POWER DIM9                    | 4(4)   4(4)    | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> 1 à 10 V ou DALI ou bouton poussoir |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 82                    |                                                      |                |                          |
|  | <b>300 90 64</b>                                    | LED POWER SUPPLY MULTI-POWER DIM7                    | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> 1 à 10 V ou bouton poussoir         |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 72                    |                                                      |                |                          |
|  | <b>300 90 67</b>                                    | LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 | 2   -          | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> 1 à 10 V ou DALI ou bouton poussoir |                                                      |                |                          |
|  | <b>300 90 68</b>                                    | LED POWER SUPPLY MULTI-POWER DIM5                    | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> DALI                                |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 72                    |                                                      |                |                          |
|  | <b>300 90 69</b>                                    | LED POWER SUPPLY MULTI-POWER HV DIM9                 | 2->6(6)   6(4) | <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> 1 à 10 V ou DALI ou bouton poussoir |                                                      |                |                          |
|                                                                                    | <b>Cutout dimension (mm):</b> 84                    |                                                      |                |                          |

# DELTALIGHT

## SPY 39 PLUG FOCUS 930






24176 9300 FG

|                                                                                    |                                                                                                                                        |             |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br><br>Dimtype: 1 à 10 V ou bouton poussoir<br><br>Cutout dimension (mm): 55    | 2(2)   2(1) | <input type="checkbox"/> |
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 55                      | 2(2)   2(1) | <input type="checkbox"/> |
|    | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br><br>Dimtype: non dimmable<br><br>Cutout dimension (mm): 90                     | 3->4   2->4 | <input type="checkbox"/> |
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><br>Dimtype: non dimmable<br><br>Cutout dimension (mm): 50                        | 2   2       | <input type="checkbox"/> |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><br>Dimtype: 1 à 10 V<br><br>Cutout dimension (mm): 54                       | 3   3       | <input type="checkbox"/> |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 54                           | 3   3       | <input type="checkbox"/> |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = dimmable sans fil<br><br>Cutout dimension (mm): 84         | 4(4)   3(3) | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = dimmable sans fil<br><br>Cutout dimension (mm): 54 | 3   3       | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><br>Dimtype: fin de phase<br><br>Cutout dimension (mm): 50     | 2->2   2->2 | <input type="checkbox"/> |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: fin de phase<br><br>Cutout dimension (mm): 55     | 1           | <input type="checkbox"/> |


# DELTALIGHT

## SPY 39 PLUG FOCUS 930

24176 9300 FG

|                                                                                    |                                                                                                                                |       |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|-------|--------------------------|
|    | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><br>Dimtype: fin de phase<br>Cutout dimension (mm): 55 | 2->3  | <input type="checkbox"/> |
|    | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: fin de phase<br>Cutout dimension (mm): 48 | 2   2 | <input type="checkbox"/> |
|    | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: fin de phase<br>Cutout dimension (mm): 40             | 1     | <input type="checkbox"/> |
|    | <b>21012 0318</b><br>LED POWER SUPPLY 500mA / 10W DIM8<br><br>Dimtype: fin de phase<br>Cutout dimension (mm): 40               | 1     | <input type="checkbox"/> |
|  | <b>21012 0480</b><br>LED POWER SUPPLY 350mA-DC / 17W IP68<br><br>Dimtype: non dimmable<br>Cutout dimension (mm): 60            | 2(2)  | <input type="checkbox"/> |
|  | <b>21012 0500</b><br>LED POWER SUPPLY 500mA-DC / 24W IP68<br><br>Dimtype: non dimmable<br>Cutout dimension (mm): 60            | 2(1)  | <input type="checkbox"/> |
|  | <b>21032 0295</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30      | 2     | <input type="checkbox"/> |
|  | <b>21032 0305</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30      | 2     | <input type="checkbox"/> |

### kit de montage

|                                                                                    |                                                                                             |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|--------------------------|
|  | <b>24144 0060</b> MOUNTING KIT PLUG O.F.A.<br><br>Cutout dimension (mm): 62 (CONCRETE: 102) | <input type="checkbox"/> |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|--------------------------|

# DELTALIGHT

## SPY 39 PLUG FOCUS 930

24176 9300 FG

Notes: