
DELTALIGHT




M26L - MULTINOVA 30 930 MDL

REFERENCE 27938 9300 W

AVAILABLE IN
BLACK 27938 9300 B
GOLD COLOURED 27938 9300 GC
WHITE 27938 9300 W





View on website

General info	
LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	1.4
ADJUSTABILITY	non adjustable
INFORMATION	INCL.PC SBL EXCL.LED POWER SUPPLY 48V-DC

Electrical info	
ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	D
CERTIFICATES	CB, ENEC

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED cluster 14,9W / CRI>90 (R9: 68) / 3000K / 2174lm
TM-30 VALUES	Rf: 89 / Rg: 97
SDCM	SDCM3
LM80	L70 > 60000
LED TECHNICS (LIGHT SOURCE)	2174lm // 14,9W // 146lm/W
LED TECHNICS (LUMINAIRE)	1580lm // 17,1W // 92lm/W

Remarks

Take a look at our MAGNETIC PROFILES movie

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : **27938_XXX0_HAND.pdf**

DELTALIGHT

M26L - MULTINOVA 30 930 MDL

27938 9300 W


FINISH YOUR SPECIFICATION

Current supply

of Fixtures

Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



21032 0030 SMART 48 MODULATOR PLUG-IN WD — 11


Dimtype: WDL = wireless dimmable

SMART 48

of Fixtures


Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



300 90 011 SMART 48 MODULATOR DIM9 — 11

Dimtype: 1-10V or DALI or push button



300 90 012 SMART 48 MODULATOR WD — 11


Dimtype: WDL = wireless dimmable

LED power supplies

of Fixtures


Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN — 6

Dimtype: non-dimmable




300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN — 14

Dimtype: non-dimmable

M26L - MULTINOVA 30 930 MDL


27938 9300 W



21012 0230 LED POWER SUPPLY 48V-DC / 100W — 6

Dimtype: non-dimmable

Cutout dimension (mm): 40



21012 0240 LED POWER SUPPLY 48V-DC / 200W — 11


Dimtype: non-dimmable

Cutout dimension (mm): 40


COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)


Available Colours




23358 0000 SLM26L - PROFILE



23358 0010 SLM26L - PROFILE 1m




23358 0020 SLM26L - PROFILE 2m




23358 0030 SLM26L - PROFILE 3m

SHIFTLINE M35R profile

Available Colours



23375 0000 SLM35R - PROFILE




23375 0010 SLM35R - PROFILE 1m


DELTALIGHT

M26L - MULTINOVA 30 930 MDL

27938 9300 W



23375 0020 SLM35R - PROFILE 2m



23375 0030 SLM35R - PROFILE 3m

Notes: