



M26L - SPY 391 93040 MDL

23258 9330 BROB

AVAILABLE IN

BLACK 23258 9330 B

BRUSHED ALU 23258 9330 BRA

BRUSHED ANTHRACITE 23258 9330 BRAT

BRUSHED COPPER 23258 9330 BRCU

BRUSHED GOLD 23258 9330 BRG

BRUSHED OLD BRONZE 23258 9330 BROB


FLEMISH BRONZE 23258 9330 FBR

FLEMISH GOLD 23258 9330 FG

GOLD COLOURED 23258 9330 GC

PIANO BLACK 23258 9330 PB

WHITE 23258 9330 W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.3
ADJUSTABILITY	0° to 85° swiveling, 360° rotatable
INFORMATION	REFLECTOR WFL-40° EXCL.LED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	D
CERTIFICATES	CB, ENEC, EPD

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1089lm
TM-30 VALUES	Rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	40°
LED TECHNICS (LIGHT SOURCE)	1089lm // 8,6W // 127lm/W
LED TECHNICS (LUMINAIRE)	883lm // 9,9W // 89lm/W

Remarks

Take a look at our **MAGNETIC PROFILES** movie

Requirements

SPY 39 TUBE or VISOR 39

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : [23258_XXX0_HAND.pdf](#)

FINISH YOUR SPECIFICATION

Current supply		# of Fixtures
		Min current Max current
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		
16 39 190	21032 0030 SMART 48 MODULATOR PLUG-IN WD	19
Dimtype: WDL = wireless dimmable		
SMART 48		# of Fixtures
		Min current Max current
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		
93 56 78	300 90 011 SMART 48 MODULATOR DIM9	19
Dimtype: 1-10V or DALI or push button		
93 56 78	300 90 012 SMART 48 MODULATOR WD	19
Dimtype: WDL = wireless dimmable		
LED power supplies		# of Fixtures
		Min current Max current
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		
55 100 90	300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN	10
Dimtype: non-dimmable		


DELTALIGHT

M26L - SPY 391 93040 MDL


23258 9330 BROB

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	24	☐
Dimtype: non-dimmable			
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	10	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	20	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			

Light altering devices

	24144 0030 B VISOR 39 B	☐
---	--------------------------------	--------------------------

Finish your product










	24144 0010 B SPY 39 TUBE B	☐
	24144 0010 FBR SPY 39 TUBE FBR	☐
	24144 0010 FC SPY 39 TUBE FC	☐
	24144 0010 GC SPY 39 TUBE GC	☐
	24144 0010 W SPY 39 TUBE W	☐
	24144 0070 SPY 39 TUBE SBL	☐

DELTALIGHT

M26L - SPY 391 93040 MDL

23258 9330 BROB


COMPATIBLE COMPOSABLES

SHIFTLINE M26L FLOOR		Available Colours
	29321 0010 SLM26L F MDL	
	29322 002W SLM26L F MDL WD	
SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)		Available Colours
	23358 0000 SLM26L - PROFILE	 
	23358 0010 SLM26L - PROFILE 1m	 
	23358 0020 SLM26L - PROFILE 2m	         
	23358 0030 SLM26L - PROFILE 3m	         
SHIFTLINE M35R profile		Available Colours
	23375 0000 SLM35R - PROFILE	
	23375 0010 SLM35R - PROFILE 1m	
	23375 0020 SLM35R - PROFILE 2m	

DELTALIGHT

M26L - SPY 391 93040 MDL

23258 9330 BROB



23375 0030 SLM35R - PROFILE 3m



Notes: