





SPY 39 ON FOCUS 930

24174 9300 W

AVAILABLE IN

- BLACK** 24174 9300 B
- BRUSHED ALU** 24174 9300 BRA
- BRUSHED ANTHRACITE** 24174 9300 BRAT
- BRUSHED COPPER** 24174 9300 BRCU
- BRUSHED GOLD** 24174 9300 BRG
- BRUSHED OLD BRONZE** 24174 9300 BROB
- FLEMISH BRONZE** 24174 9300 FBR
- FLEMISH GOLD** 24174 9300 FG
- FULL WHITE** 24174 9300 FW
- GOLD COLOURED** 24174 9300 GC
- WHITE** 24174 9300 W



 [View on website](#)



General info

| | |
|---------------------------|-------------------------------------|
| LOCATION | indoor |
| INSTALLATION | Ceiling Surface mounted |
| INGRESS PROTECTION | IP20 |
| WEIGHT (KG) | 0.4 |
| ADJUSTABILITY | 0° to 85° swiveling, 355° rotatable |
| INFORMATION | ADJUSTABLE BEAM 15°-45° |

Electrical info

| | |
|---------------------|---------------------------|
| CLASS | III |
| DIM TYPE | depending on power supply |
| ENERGY CLASS | E |
| CERTIFICATES | LCA |

Lightsource info

| | |
|------------------------------------|---|
| LIGHTSOURCE NAME | LED |
| LIGHTSOURCE | LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 734-1018lm |
| TM-30 VALUES | rf: 90 / Rg: 99 |
| SDCM | SDCM1 |
| RISKGROUP | RG1 |
| LM80 | L90B10 > 50000 |
| BEAMANGLE | 15°-45° |
| LED TECHNICS (LIGHT SOURCE) | 1018lm // 8,6W // 118lm/W |
| LED TECHNICS (LUMINAIRE) | 303lm // 9,9W // 31lm/W |

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

Options

COVERSET R 90-100

DELTALIGHT

SPY 39 ON FOCUS 930

24174 9300 W

For detailed installation instructions, please consult the manual : [24174_XXXX_HAND.pdf](#)

FINISH YOUR SPECIFICATION


LED power supplies

of Fixtures



of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45




300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30




300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45




300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30




300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45



300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30

DELTALIGHT

SPY 39 ON FOCUS 930

24174 9300 W



300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

2 | 2

Dimtype: mains (phase cut-off) or push button

Cutout dimension (mm): 56



300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

4(4) | 4(4)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 82



300 90 64 LED POWER SUPPLY MULTI-POWER DIM7

2(2) | 2(1)

Dimtype: 1-10V or push button

Cutout dimension (mm): 72



300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

2 | -

Dimtype: 1-10V or DALI or push button



300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

2(2) | 2(1)

Dimtype: DALI

Cutout dimension (mm): 72



300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6) | 6(4)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 84



300 90 124 LED POWER SUPPLY MULTI-POWER DIM7

2(2) | 2(1)

Dimtype: 1-10V or push button

Cutout dimension (mm): 55



300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5

2(2) | 2(1)

Dimtype: DALI

Cutout dimension (mm): 55



300 90 135 LED POWER SUPPLY MULTI-POWER HV

3->4 | 2->4


Dimtype: non-dimmable

Cutout dimension (mm): 90

DELTALIGHT

SPY 39 ON FOCUS 930

24174 9300 W




21012 0010 LED POWER SUPPLY MULTI POWER

2 | 2

Dimtype: non-dimmable

Cutout dimension (mm): 50




21012 0021 LED POWER SUPPLY MULTI POWER DIM1

3 | 3

Dimtype: 1-10V

Cutout dimension (mm): 54




21012 0035 LED POWER SUPPLY MULTI POWER DIM5

3 | 3

Dimtype: DALI

Cutout dimension (mm): 54



21012 004W LED POWER SUPPLY MULTI-POWER WDL

4(4) | 3(3)

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 84




21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL

3 | 3

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 54




21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

2->2 | 2->2

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 50



21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 55




21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

2->3

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 55



21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2 | 2

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 48



21012 0308 LED POWER SUPPLY 350mA / 7,35W DIM8

1


Dimtype: mains (phase cut-off)

Cutout dimension (mm): 40

DELTALIGHT

SPY 39 ON FOCUS 930

24174 9300 W



21012 0318 LED POWER SUPPLY 500mA / 10W DIM8

1

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 40



21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68

2(2)

Dimtype: non-dimmable

Cutout dimension (mm): 60



21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68

2(1)

Dimtype: non-dimmable

Cutout dimension (mm): 60



21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 30



21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 30

Coversets



204 00 100 ANO COVERSET R 100 ANO

204 00 100 B COVERSET R 100 B

204 00 100 W COVERSET R 100 W

Notes: