



M26L - BOXY L 92733 MDL

10734 9220 B-B



AVAILABLE IN

BLACK-BLACK 10734 9220 B-B

BLACK-FLEMISH BRONZE 10734 9220 B-FBR

BLACK-FLEMISH GOLD 10734 9220 B-FG

WHITE-WHITE 10734 9220 W-W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 8,6W / CRI>90 (R9: 60) / 2700K / 1041lm
TM-30 VALUES	rf: 89 / Rg: 100
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	33°
LED TECHNICS (LIGHT SOURCE)	1041lm // 8,6W // 121lm/W
LED TECHNICS (LUMINAIRE)	697lm // 9,9W // 70lm/W

Remarks

Take a look at our **MAGNETIC PROFILES** movie

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

Accessories

BOXY HONEYCOMB
BOXY SOFTENING LENS
BOXY GLASS SBL

DELTALIGHT

M26L - BOXY L 92733 MDL


10734 9220 B-B

For detailed installation instructions, please consult the manual : [10734_XXX0_HAND.pdf](#)


FINISH YOUR SPECIFICATION

Current supply

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




21032 0030 SMART 48 MODULATOR PLUG-IN WD

19

Dimtype: WDL = wireless dimmable

SMART 48

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



300 90 011 SMART 48 MODULATOR DIM9

19

Dimtype: 1-10V or DALI or push button




300 90 012 SMART 48 MODULATOR WD

19


Dimtype: WDL = wireless dimmable

LED power supplies

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN

10

Dimtype: non-dimmable

DELTALIGHT

M26L - BOXY L 92733 MDL


10734 9220 B-B



300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN

24

Dimtype: non-dimmable



21012 0230 LED POWER SUPPLY 48V-DC / 100W

10

Dimtype: non-dimmable

Cutout dimension (mm): 40



21012 0240 LED POWER SUPPLY 48V-DC / 200W

20

Dimtype: non-dimmable

Cutout dimension (mm): 40

Light altering devices



Ø40



1.5

Ø45

251 70 03 01 B BOXY HONEYCOMB B

251 70 03 01 W BOXY HONEYCOMB W



Ø40



1.5

Ø45

251 70 03 04 B BOXY SOFTENING LENS B

251 70 03 04 W BOXY SOFTENING LENS W



Ø40



1.5

Ø45

251 70 03 05 B BOXY GLASS SBL B

251 70 03 05 W BOXY GLASS SBL W

DELTALIGHT


M26L - BOXY L 92733 MDL

10734 9220 B-B


COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)


Available Colours




23358 0000 SLM26L - PROFILE



23358 0010 SLM26L - PROFILE 1m



23358 0020 SLM26L - PROFILE 2m



23358 0030 SLM26L - PROFILE 3m



Notes: