





M26L - OCTAV 27 93030 MDL

29013 9320 FBR

AVAILABLE IN
BLACK 29013 9320 B
FLEMISH BRONZE 29013 9320 FBR
FLEMISH GOLD 29013 9320 FG
GOLD COLOURED 29013 9320 GC
WHITE 29013 9320 W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.3
ADJUSTABILITY	0° to 85° swiveling, 360° rotatable
INFORMATION	REFLECTOR FL-30° EXCLLED POWER SUPPLY 48V-DC SPY 27 L TUBE B included

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8W / CRI>90 (R9: 52) / 3000K / 787lm
TM-30 VALUES	rf: 90 / Rg: 99
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	30°
LED TECHNICS (LIGHT SOURCE)	787lm // 5,8W // 135lm/W
LED TECHNICS (LUMINAIRE)	288lm // 6,7W // 43lm/W

Remarks

Take a look at our MAGNETIC PROFILES movie

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : [29013_XXX0_HAND.pdf](#)

FINISH YOUR SPECIFICATION

Current supply

of Fixtures

of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current

21032 0030

SMART 48 MODULATOR PLUG-IN WD

28

Dimtype: WDL = wireless dimmable

SMART 48

of Fixtures

of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current

300 90 011

SMART 48 MODULATOR DIM9

28

Dimtype: 1-10V or DALI or push button

300 90 012

SMART 48 MODULATOR WD

28

Dimtype: WDL = wireless dimmable

LED power supplies

of Fixtures

of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current

300 89 48 100

LED POWER SUPPLY 48V-DC / 100W DIN

15

Dimtype: non-dimmable




DELTALIGHT

M26L - OCTAV 27 93030 MDL

29013 9320 FBR

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	36	☐
Dimtype: non-dimmable			
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	15	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	30	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			

COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)	Available Colours
 23358 0000 SLM26L - PROFILE	 
 23358 0010 SLM26L - PROFILE 1m	 
 23358 0020 SLM26L - PROFILE 2m	           
 23358 0030 SLM26L - PROFILE 3m	           

Notes: