
DELTALIGHT




M26L - JUM-OH! 4R 93030 MDL

REFERENCE 29413 9320 B

AVAILABLE IN
BLACK 29413 9320 B





View on website

General info	
LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.2
ADJUSTABILITY	non adjustable
INFORMATION	4 x REFLECTOR FL-30° EXCL.LED POWER SUPPLY 48V-DC

Electrical info	
ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	F
CERTIFICATES	CB, ENEC

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	2 x (LED cluster 4W / CRI>90 (R9: 60) / 3000K / 481lm)
TM-30 VALUES	Rf: 92 / Rg: 99
SDCM	SDCM3
RISKGROUP	RG2
LM80	L80 > 150000
BEAMANGLE	30°
LED TECHNICS (LIGHT SOURCE)	962lm // 8W // 120lm/W
LED TECHNICS (LUMINAIRE)	795lm // 9,2W // 86lm/W

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : **29413_XXX0_HAND.pdf**

M26L - JUM-OH! 4R 93030 MDL

29413 9320 B


FINISH YOUR SPECIFICATION

Current supply

# of Fixtures

Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



21032 0030 SMART 48 MODULATOR PLUG-IN WD — 20 ☐


Dimtype: WDL = wireless dimmable

SMART 48

# of Fixtures


Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



300 90 011 SMART 48 MODULATOR DIM9 — 20 ☐

Dimtype: 1-10V or DALI or push button



300 90 012 SMART 48 MODULATOR WD — 20 ☐


Dimtype: WDL = wireless dimmable

LED power supplies

# of Fixtures


Min current | Max current

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN — 10 ☐

Dimtype: non-dimmable




300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN — 26 ☐

Dimtype: non-dimmable

M26L - JUM-OH! 4R 93030 MDL


29413 9320 B



21012 0230 LED POWER SUPPLY 48V-DC / 100W — 10

Dimtype: non-dimmable

Cutout dimension (mm): 40



21012 0240 LED POWER SUPPLY 48V-DC / 200W — 21


Dimtype: non-dimmable

Cutout dimension (mm): 40


COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)


Available Colours




23358 0000 SLM26L - PROFILE



23358 0010 SLM26L - PROFILE 1m




23358 0020 SLM26L - PROFILE 2m




23358 0030 SLM26L - PROFILE 3m

SHIFTLINE M35R profile

Available Colours



23375 0000 SLM35R - PROFILE




23375 0010 SLM35R - PROFILE 1m


DELTALIGHT

M26L - JUM-OH! 4R 93030 MDL

29413 9320 B



23375 0020 SLM35R - PROFILE 2m



23375 0030 SLM35R - PROFILE 3m

Notes: