





M26L - MULTINOVA 30 PRISM 930 MDL

27940 9300 W

AVAILABLE IN
BLACK 27940 9300 B
WHITE 27940 9300 W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	1.4
ADJUSTABILITY	non adjustable
INFORMATION	INCL.PC PRISMATIC EXCL.LED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	D
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED cluster 14,9W / CRI>90 (R9: 68) / 3000K / 2174lm
TM-30 VALUES	Rf: 89 / Rg: 97
SDCM	SDCM3
LM80	L70 > 60000
LED TECHNICS (LIGHT SOURCE)	2174lm // 14,9W // 146lm/W
LED TECHNICS (LUMINAIRE)	1394lm // 17,1W // 81lm/W

Remarks

Take a look at our **MAGNETIC PROFILES** movie

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual : [27940_XXX0_HAND.pdf](#)

M26L - MULTINOVA 30 PRISM 930 MDL

27940 9300 W


FINISH YOUR SPECIFICATION

Current supply

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



21032 0030 SMART 48 MODULATOR PLUG-IN WD

Dimtype: WDL = wireless dimmable


11

SMART 48

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


Min current | Max current



300 90 011 SMART 48 MODULATOR DIM9

Dimtype: 1-10V or DALI or push button

11



300 90 012 SMART 48 MODULATOR WD

Dimtype: WDL = wireless dimmable


11

LED power supplies

of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


Min current | Max current



300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN

Dimtype: non-dimmable

6



300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN



Dimtype: non-dimmable

14







DELTALIGHT

M26L - MULTINOVA 30 PRISM 930 MDL

27940 9300 W

	21012 0230 LED POWER SUPPLY 48V-DC / 100W	6	☐
	Dimtype: non-dimmable		
	Cutout dimension (mm): 40		
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	11	☐
	Dimtype: non-dimmable		
	Cutout dimension (mm): 40		


COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)		Available Colours	
	23358 0000 SLM26L - PROFILE		
	23358 0010 SLM26L - PROFILE 1m		
	23358 0020 SLM26L - PROFILE 2m		
	23358 0030 SLM26L - PROFILE 3m		
SHIFTLINE M35R profile		Available Colours	
	23375 0000 SLM35R - PROFILE		
	23375 0010 SLM35R - PROFILE 1m		


DELTALIGHT

M26L - MULTINOVA 30 PRISM 930 MDL

27940 9300 W



23375 0020 SLM35R - PROFILE 2m



23375 0030 SLM35R - PROFILE 3m



Notes: