



## M26L - BOXY L 93033 MDL

10734 9320 W-W



AVAILABLE IN

**BLACK-BLACK** 10734 9320 B-B

**BLACK-FLEMISH BRONZE** 10734 9320 B-FBR

**BLACK-FLEMISH GOLD** 10734 9320 B-FG

**WHITE-WHITE** 10734 9320 W-W



[View on website](#)



### General info

|                           |                                                  |
|---------------------------|--------------------------------------------------|
| <b>LOCATION</b>           | indoor                                           |
| <b>INSTALLATION</b>       | Low voltage systems Low voltage system mounted   |
| <b>INGRESS PROTECTION</b> | IP20                                             |
| <b>WEIGHT (KG)</b>        | 0.4                                              |
| <b>ADJUSTABILITY</b>      | non adjustable                                   |
| <b>INFORMATION</b>        | REFLECTOR FL-33°<br>EXCL.LED POWER SUPPLY 48V-DC |

### Electrical info

|                     |                                    |
|---------------------|------------------------------------|
| <b>ELECTRICAL</b>   | 48V-DC                             |
| <b>CLASS</b>        | III                                |
| <b>DIM TYPE</b>     | MDL = 1-10V or DALI or push button |
| <b>ENERGY CLASS</b> | E                                  |
| <b>CERTIFICATES</b> | CB, ENEC                           |

### Lightsource info

|                                    |                                                   |
|------------------------------------|---------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                               |
| <b>LIGHTSOURCE</b>                 | LED array 8,6W / CRI>90 (R9: 52) / 3000K / 1089lm |
| <b>TM-30 VALUES</b>                | rf: 90 / Rg: 99                                   |
| <b>SDCM</b>                        | SDCM1                                             |
| <b>RISKGROUPE</b>                  | RG1                                               |
| <b>LM80</b>                        | L90B10 > 50000                                    |
| <b>BEAMANGLE</b>                   | 33°                                               |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1089lm // 8,6W // 127lm/W                         |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 729lm // 9,9W // 74lm/W                           |

### Remarks

[Take a look at our MAGNETIC PROFILES movie](#)

### Requirements

LED POWER SUPPLY 48V-DC

### Options

DIMMABLE MODULATOR

### Accessories

BOXY HONEYCOMB  
BOXY SOFTENING LENS  
BOXY GLASS SBL

## M26L - BOXY L 93033 MDL

10734 9320 W-W

For detailed installation instructions, please consult the manual : [10734\\_XXX0\\_HAND.pdf](#)


### FINISH YOUR SPECIFICATION

#### Current supply

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



**21032 0030** SMART 48 MODULATOR PLUG-IN WD

19


Dimtype: WDL = wireless dimmable

#### SMART 48

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


Min current | Max current



**300 90 011** SMART 48 MODULATOR DIM9

19

Dimtype: 1-10V or DALI or push button



**300 90 012** SMART 48 MODULATOR WD

19


Dimtype: WDL = wireless dimmable

#### LED power supplies

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN




10

Dimtype: non-dimmable

# DELTALIGHT

## M26L - BOXY L 93033 MDL

10734 9320 W-W

|                                                                                  |                                                         |    |                          |
|----------------------------------------------------------------------------------|---------------------------------------------------------|----|--------------------------|
|  | <b>300 89 48 240</b> LED POWER SUPPLY 48V-DC / 240W DIN | 24 | <input type="checkbox"/> |
|                                                                                  | Dimtype: non-dimmable                                   |    |                          |
|  | <b>21012 0230</b> LED POWER SUPPLY 48V-DC / 100W        | 10 | <input type="checkbox"/> |
|                                                                                  | Dimtype: non-dimmable                                   |    |                          |
|                                                                                  | Cutout dimension (mm): 40                               |    |                          |
|  | <b>21012 0240</b> LED POWER SUPPLY 48V-DC / 200W        | 20 | <input type="checkbox"/> |
|                                                                                  | Dimtype: non-dimmable                                   |    |                          |
|                                                                                  | Cutout dimension (mm): 40                               |    |                          |

### Light altering devices





|                                                                                     |                                             |                          |
|-------------------------------------------------------------------------------------|---------------------------------------------|--------------------------|
|   | <b>251 70 03 01 B</b> BOXY HONEYCOMB B      | <input type="checkbox"/> |
|  | <b>251 70 03 01 W</b> BOXY HONEYCOMB W      | <input type="checkbox"/> |
|  | <b>251 70 03 04 B</b> BOXY SOFTENING LENS B | <input type="checkbox"/> |
|  | <b>251 70 03 04 W</b> BOXY SOFTENING LENS W | <input type="checkbox"/> |
|  | <b>251 70 03 05 B</b> BOXY GLASS SBL B      | <input type="checkbox"/> |
|  | <b>251 70 03 05 W</b> BOXY GLASS SBL W      | <input type="checkbox"/> |

# DELTALIGHT

## M26L - BOXY L 93033 MDL

10734 9320 W-W

### COMPATIBLE COMPOSABLES

| SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)                                   |                                       | Available Colours                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
|------------------------------------------------------------------------------------|---------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|   | <b>23358 0000</b> SLM26L - PROFILE    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
|   | <b>23358 0010</b> SLM26L - PROFILE 1m |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
|   | <b>23358 0020</b> SLM26L - PROFILE 2m |                               |
|  | <b>23358 0030</b> SLM26L - PROFILE 3m |           |

Notes: