



## M26L - SPY 52 WALLWASH SOFT 930 MDL

19892 9000 FBR

AVAILABLE IN



**NOIR** 19892 9000 B

**FLEMISH BRONZE** 19892 9000 FBR

**FLEMISH GOLD** 19892 9000 FG

**COULEUR OR** 19892 9000 GC

**BLANC** 19892 9000 W



[View on website](#)



### General info

|                           |                                                         |
|---------------------------|---------------------------------------------------------|
| <b>LOCATION</b>           | interieur                                               |
| <b>INSTALLATION</b>       | Systèmes basse tension Monté sur systèmes basse tension |
| <b>INGRESS PROTECTION</b> | IP20                                                    |
| <b>WEIGHT (KG)</b>        | 0.3                                                     |
| <b>ADJUSTABILITY</b>      | 0° à 90° inclinable, 360° rotatif                       |
| <b>INFORMATION</b>        | WALLWASH LENS<br>EXCL LED POWER SUPPLY 48V-DC           |

### Electrical info

|                      |                                                    |
|----------------------|----------------------------------------------------|
| <b>ELECTRICAL</b>    | 48V-DC                                             |
| <b>CLASS</b>         | III                                                |
| <b>DIM TYPE</b>      | MDL = dimmable 1 à 10 V ou DALI ou bouton poussoir |
| <b>ENERGY CLASS</b>  | F                                                  |
| <b>CERTIFICATION</b> | CB, ENEC, EPD                                      |

### Lightsource info

|                                    |                                                          |
|------------------------------------|----------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                      |
| <b>LIGHTSOURCE</b>                 | LED array 10,2W / CRI>90 (R9: 50) / 3000K-1800K / 1038lm |
| <b>SDMC</b>                        | SDCM2                                                    |
| <b>RISKGROUP</b>                   | RG1                                                      |
| <b>LM80</b>                        | L90B10 > 50000                                           |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1038lm // 10,2W // 109lm/W                               |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 490lm // 11,7W // 42lm/W                                 |

### Remarks

Take a look at our **MAGNETIC PROFILES** movie

### Requirements

LED POWER SUPPLY 48V-DC

### Options






DIMMABLE MODULATOR

M26L - SPY 52 WALLWASH SOFT 930 MDL

19892 9000 FBR



For detailed installation instructions, please consult the manual : [19892\\_XXX0\\_HAND.pdf](#)

FINISH YOUR SPECIFICATION





| le cable d'alimentation                                                                                                                             |                                                                                                                           | # of Fixtures               |
|-----------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------|-----------------------------|
| <div><div></div><div>web2print_power_supply_info_box</div></div>   |                                                                                                                           | Min current   Max current   |
|                                                                     | <div><div>21032 0030</div><div>SMART 48 MODULATOR PLUG-IN WD</div><div>Dimtype: WDL = dimmable sans fil</div></div>       | 16 <input type="checkbox"/> |
| SMART 48                                                                                                                                            |                                                                                                                           | # of Fixtures               |
| <div><div></div><div>web2print_power_supply_info_box</div></div> |                                                                                                                           | Min current   Max current   |
|                                                                   | <div><div>300 90 011</div><div>SMART 48 MODULATOR DIM9</div><div>Dimtype: 1 à 10 V ou DALI ou bouton poussoir</div></div> | 16 <input type="checkbox"/> |
|                                                                   | <div><div>300 90 012</div><div>SMART 48 MODULATOR WD</div><div>Dimtype: WDL = dimmable sans fil</div></div>               | 16 <input type="checkbox"/> |
| les alimentations led                                                                                                                               |                                                                                                                           | # of Fixtures               |
| <div><div></div><div>web2print_power_supply_info_box</div></div> |                                                                                                                           | Min current   Max current   |
|                                                                   | <div><div>300 89 48 100</div><div>LED POWER SUPPLY 48V-DC / 100W DIN</div><div>Dimtype: non dimmable</div></div>          | 8 <input type="checkbox"/>  |
|                                                                   | <div><div>300 89 48 240</div><div>LED POWER SUPPLY 48V-DC / 240W DIN</div><div>Dimtype: non dimmable</div></div>          | 20 <input type="checkbox"/> |

M26L - SPY 52 WALLWASH SOFT 930 MDL

19892 9000 FBR

|                                                                                  |                                                  |                             |
|----------------------------------------------------------------------------------|--------------------------------------------------|-----------------------------|
|  | <b>21012 0230</b> LED POWER SUPPLY 48V-DC / 100W | 8 <input type="checkbox"/>  |
|                                                                                  | Dimtype: non dimmable                            |                             |
|                                                                                  | Cutout dimension (mm): 40                        |                             |
|  | <b>21012 0240</b> LED POWER SUPPLY 48V-DC / 200W | 17 <input type="checkbox"/> |
|                                                                                  | Dimtype: non dimmable                            |                             |
|                                                                                  | Cutout dimension (mm): 40                        |                             |

COMPATIBLE COMPOSABLES

| SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)                                                                          | Available Colours                                                                     |
|---------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------|
|  <b>23358 0000</b> SLM26L - PROFILE      |    |
|  <b>23358 0010</b> SLM26L - PROFILE 1m |  |
|  <b>23358 0020</b> SLM26L - PROFILE 2m |  |
|  <b>23358 0030</b> SLM26L - PROFILE 3m |  |

Notes: