




## SPY 39 PLUG WALLWASH SOFT 930

24178 9000 BRCU

AVAILABLE IN

**BLACK** 24178 9000 B  
**BRUSHED ALU** 24178 9000 BRA  
**BRUSHED ANTHRACITE** 24178 9000 BRAT  
**BRUSHED COPPER** 24178 9000 BRCU  
**BRUSHED GOLD** 24178 9000 BRG  
**BRUSHED OLD BRONZE** 24178 9000 BROB  
**FLEMISH BRONZE** 24178 9000 FBR  
**FLEMISH GOLD** 24178 9000 FG  
**FULL WHITE** 24178 9000 FW  
**GOLD COLOURED** 24178 9000 GC  
**WHITE** 24178 9000 W



[View on website](#)



### General info

|                               |                                                          |
|-------------------------------|----------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                   |
| <b>INSTALLATION</b>           | Ceiling Semi-recessed                                    |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - Ø KIT                                            |
| <b>RECESSED DEPTH (MM)</b>    | 80                                                       |
| <b>INGRESS PROTECTION</b>     | IP20                                                     |
| <b>WEIGHT (KG)</b>            | 0.4                                                      |
| <b>ADJUSTABILITY</b>          | 0° to 85° swiveling, 355° rotatable                      |
| <b>INFORMATION</b>            | WALLWASH LENS<br>EXCL.DIMMABLE LED POWER SUPPLY 350mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | F                         |
| <b>CERTIFICATES</b> | CB, ENEC                  |

### Lightsource info

|                                    |                                                      |
|------------------------------------|------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                  |
| <b>LIGHTSOURCE</b>                 | LED array 6W / CRI>90 (R9: 50) / 3000K-1800K / 623lm |
| <b>TM-30 VALUES</b>                | rf: 90 / Rg: 99                                      |
| <b>SDCM</b>                        | SDCM2                                                |
| <b>RISKGROUP</b>                   | RG1                                                  |
| <b>LM80</b>                        | L90B10 > 50000                                       |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 623lm // 6W // 105lm/W                               |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 341lm // 6,9W // 49lm/W                              |

### Requirements

MOUNTING KIT PLUG O.F.A.  
 LED POWER SUPPLY 350mA-DC DIM

# DELTALIGHT

## SPY 39 PLUG WALLWASH SOFT 930

24178 9000 BRCU


For detailed installation instructions, please consult the manual : [24178\\_XXX0\\_HAND.pdf](#)

### CEILING COMPATIBILITY

| Ceiling Type                                                                                                       | Mounting Kit                                                                                                            |          |
|--------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|----------|
|  <b>Plasterboard</b>               |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Concrete + plaster</b>         |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Lintel + plaster</b>           |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |
|  <b>Hollow-core slab + plaster</b> |  24144 0060 - MOUNTING KIT PLUG O.F.A. | Required |

### FINISH YOUR SPECIFICATION

#### Emergency units

|                                                                                    |                                                                     |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------|--------------------------|
|  | <b>21032 0270 B</b> EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B | <input type="checkbox"/> |
|                                                                                    | <b>21032 0270 W</b> EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W | <input type="checkbox"/> |



#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.











Min current | Max current

|                                                                                    |                                                                          |                            |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|----------------------------|
|  | <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 | 2 <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> 1-10V                                                    |                            |
|                                                                                    | <b>Cutout dimension (mm):</b> 30                                         |                            |
|  | <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 2 <input type="checkbox"/> |
|                                                                                    | <b>Dimtype:</b> DALI                                                     |                            |
|                                                                                    | <b>Cutout dimension (mm):</b> 45                                         |                            |

# DELTALIGHT







## SPY 39 PLUG WALLWASH SOFT 930

24178 9000 BRCU


|                                                                                    |                                                                                                                                                        |         |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|---------|--------------------------|
|    | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL<br><b>Dimtype:</b> non-dimmable<br><b>Cutout dimension (mm):</b> 30            | 2       | <input type="checkbox"/> |
|    | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br><b>Dimtype:</b> WDL = wireless dimmable<br><b>Cutout dimension (mm):</b> 45 | 2       | <input type="checkbox"/> |
|    | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6<br><b>Dimtype:</b> mains (phase cut-off) or push button<br><b>Cutout dimension (mm):</b> 56         | 2       | <input type="checkbox"/> |
|    | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button<br><b>Cutout dimension (mm):</b> 82                 | 4(4)    | <input type="checkbox"/> |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype:</b> 1-10V or push button<br><b>Cutout dimension (mm):</b> 72                         | 3(2)    | <input type="checkbox"/> |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button                                  | 2       | <input type="checkbox"/> |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 72                                         | 2(2)    | <input type="checkbox"/> |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9<br><b>Dimtype:</b> 1-10V or DALI or push button<br><b>Cutout dimension (mm):</b> 84              | 2->6(6) | <input type="checkbox"/> |
|  | <b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7<br><b>Dimtype:</b> 1-10V or push button<br><b>Cutout dimension (mm):</b> 55                        | 2(2)    | <input type="checkbox"/> |
|  | <b>300 90 125</b> LED POWER SUPPLY MULTI-POWER MINI DIM5<br><b>Dimtype:</b> DALI<br><b>Cutout dimension (mm):</b> 55                                   | 2(2)    | <input type="checkbox"/> |

SPY 39 PLUG WALLWASH SOFT 930

24178 9000 BRCU

|                                                                                    |                                                                      |      |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|------|--------------------------|
|    | <b>21012 0021</b> LED POWER SUPPLY MULTI POWER DIM1                  | 3    | <input type="checkbox"/> |
| <b>Dimtype:</b> 1-10V                                                              |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 54                                                   |                                                                      |      |                          |
|    | <b>21012 0035</b> LED POWER SUPPLY MULTI POWER DIM5                  | 3    | <input type="checkbox"/> |
| <b>Dimtype:</b> DALI                                                               |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 54                                                   |                                                                      |      |                          |
|    | <b>21012 004W</b> LED POWER SUPPLY MULTI-POWER WDL                   | 4(4) | <input type="checkbox"/> |
| <b>Dimtype:</b> WDL = wireless dimmable                                            |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 84                                                   |                                                                      |      |                          |
|    | <b>21012 005W</b> LED POWER SUPPLY MULTI-POWER COMPACT WDL           | 3    | <input type="checkbox"/> |
| <b>Dimtype:</b> WDL = wireless dimmable                                            |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 54                                                   |                                                                      |      |                          |
|  | <b>21012 0268</b> LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8    | 2->2 | <input type="checkbox"/> |
| <b>Dimtype:</b> mains (phase cut-off)                                              |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 50                                                   |                                                                      |      |                          |
|  | <b>21012 0298</b> LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8    | 2    | <input type="checkbox"/> |
| <b>Dimtype:</b> mains (phase cut-off)                                              |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 48                                                   |                                                                      |      |                          |
|  | <b>21012 0308</b> LED POWER SUPPLY 350mA / 7,35W DIM8                | 1    | <input type="checkbox"/> |
| <b>Dimtype:</b> mains (phase cut-off)                                              |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 40                                                   |                                                                      |      |                          |
|  | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 2    | <input type="checkbox"/> |
| <b>Dimtype:</b> DALI                                                               |                                                                      |      |                          |
| <b>Cutout dimension (mm):</b> 30                                                   |                                                                      |      |                          |

Mounting kits

|                                                                                    |                                            |                          |
|------------------------------------------------------------------------------------|--------------------------------------------|--------------------------|
|  | <b>24144 0060</b> MOUNTING KIT PLUG O.F.A. | <input type="checkbox"/> |
| <b>Cutout dimension (mm):</b> 62 (CONCRETE: 102)                                   |                                            |                          |

# DELTALIGHT

## SPY 39 PLUG WALLWASH SOFT 930

24178 9000 BRCU

Notes: