



M26L - BOXY L SOFT 93045 MDL

10735 9030 W-W



AVAILABLE IN

BLACK-BLACK 10735 9030 B-B

BLACK-FLEMISH BRONZE 10735 9030 B-FBR

BLACK-FLEMISH GOLD 10735 9030 B-FG

WHITE-WHITE 10735 9030 W-W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR WFL-45° EXCL.LED POWER SUPPLY 48V-DC

Electrical info

ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	F
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 10,2W / CRI>90 (R9: 50) / 3000K-1800K / 1038lm
SDCM	SDCM2
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	45°
LED TECHNICS (LIGHT SOURCE)	1038lm // 10,2W // 109lm/W
LED TECHNICS (LUMINAIRE)	805lm // 11,7W // 69lm/W

Remarks

[Take a look at our MAGNETIC PROFILES movie](#)

Requirements

LED POWER SUPPLY 48V-DC

Options

DIMMABLE MODULATOR

Accessories

BOXY HONEYCOMB
BOXY SOFTENING LENS
BOXY GLASS SBL

For detailed installation instructions, please consult the manual : [10735_XXX0_HAND.pdf](#)




FINISH YOUR SPECIFICATION

Current supply		# of Fixtures
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		Min current Max current
16 39 190	21032 0030 SMART 48 MODULATOR PLUG-IN WD	27
Dimtype: WDL = wireless dimmable		
SMART 48		# of Fixtures
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		Min current Max current
56 93 78	300 90 011 SMART 48 MODULATOR DIM9	27
Dimtype: 1-10V or DALI or push button		
56 93 78	300 90 012 SMART 48 MODULATOR WD	27
Dimtype: WDL = wireless dimmable		
LED power supplies		# of Fixtures
# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.		Min current Max current
55 100 90	300 89 48 100 LED POWER SUPPLY 48V-DC / 100W DIN	14
Dimtype: non-dimmable		

DELTALIGHT

M26L - BOXY L SOFT 93045 MDL

10735 9030 W-W

	300 89 48 240 LED POWER SUPPLY 48V-DC / 240W DIN	34	☐
Dimtype: non-dimmable			
	21012 0230 LED POWER SUPPLY 48V-DC / 100W	14	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			
	21012 0240 LED POWER SUPPLY 48V-DC / 200W	29	☐
Dimtype: non-dimmable			
Cutout dimension (mm): 40			





Light altering devices

	251 70 03 01 B BOXY HONEYCOMB B	☐
	251 70 03 01 W BOXY HONEYCOMB W	☐
	251 70 03 04 B BOXY SOFTENING LENS B	☐
	251 70 03 04 W BOXY SOFTENING LENS W	☐
	251 70 03 05 B BOXY GLASS SBL B	☐
	251 70 03 05 W BOXY GLASS SBL W	☐

M26L - BOXY L SOFT 93045 MDL

10735 9030 W-W

COMPATIBLE COMPOSABLES

SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)		Available Colours
	23358 0000 SLM26L - PROFILE	 
	23358 0010 SLM26L - PROFILE 1m	 
	23358 0020 SLM26L - PROFILE 2m	          
	23358 0030 SLM26L - PROFILE 3m	          

Notes: