





## SPY 39 TRIMLESS IN 93040

24123 9330 FG

AVAILABLE IN

**BLACK** 24123 9330 B  
**BRUSHED ALU** 24123 9330 BRA  
**BRUSHED ANTHRACITE** 24123 9330 BRAT  
**BRUSHED COPPER** 24123 9330 BRCU  
**BRUSHED GOLD** 24123 9330 BRG  
**BRUSHED OLD BRONZE** 24123 9330 BROB  
**FLEMISH BRONZE** 24123 9330 FBR  
**FLEMISH GOLD** 24123 9330 FG  
**FULL WHITE** 24123 9330 FW  
**GOLD COLOURED** 24123 9330 GC  
**PIANO BLACK** 24123 9330 PB  
**WHITE** 24123 9330 W



[View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	round - Ø KIT
<b>RECESSED DEPTH (MM)</b>	130
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.4
<b>ADJUSTABILITY</b>	0° to 85° swiveling, 355° rotatable
<b>INFORMATION</b>	REFLECTOR WFL-40° EXCL.LED POWER SUPPLY 350-500mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on power supply
<b>ENERGY CLASS</b>	D
<b>CERTIFICATES</b>	CB, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm
<b>TM-30 VALUES</b>	rf: 90 / Rg: 99
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>BEAMANGLE</b>	40°
<b>LED TECHNICS (LIGHT SOURCE)</b>	1089lm // 8,6W // 127lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	883lm // 9,9W // 89lm/W

### Requirements

SPY 39 TUBE or VISOR 39  
 MOUNTING KIT SPY 39 TRIMLESS IN  
 LED POWER SUPPLY 350 / 500mA-DC DIM (Remote)





# DELTALIGHT

## SPY 39 TRIMLESS IN 93040





24123 9330 FG

For detailed installation instructions, please consult the manual : [24123\\_XXX0\\_HAND.pdf](#)

### CEILING COMPATIBILITY

Ceiling Type	Mounting Kit	
 <b>System ceiling</b>	 24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN	Required
 <b>Plasterboard</b>	 24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN	Required
 <b>Stucanet</b>	 24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN	Required
 <b>Concrete + plaster</b>	 24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN	Required
 <b>Lintel + plaster</b>	 24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN	Required
 <b>Hollow-core slab + plaster</b>	 24144 0050 - MOUNTING KIT SPY 39 TRIMLESS IN	Required

### FINISH YOUR SPECIFICATION

LED power supplies	# of Fixtures
 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.	Min current   Max current
 <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 Dimtype: 1-10V Cutout dimension (mm): 30	2 <input type="checkbox"/>
 <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 Dimtype: DALI Cutout dimension (mm): 45	2 <input type="checkbox"/>
 <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL Dimtype: non-dimmable Cutout dimension (mm): 30	2 <input type="checkbox"/>

# DELTALIGHT

## SPY 39 TRIMLESS IN 93040

24123 9330 FG



**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

2

Dimtype: 1-10V

Cutout dimension (mm): 30



**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 45



**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

2

Dimtype: non-dimmable

Cutout dimension (mm): 30




**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

2

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6

2 | 2

Dimtype: mains (phase cut-off) or push button

Cutout dimension (mm): 56




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

4(4) | 4(4)

Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 82



**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7

2(2) | 2(1)

Dimtype: 1-10V or push button

Cutout dimension (mm): 72



**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

2 | -

Dimtype: 1-10V or DALI or push button



**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

2(2) | 2(1)


Dimtype: DALI

Cutout dimension (mm): 72

# DELTALIGHT

## SPY 39 TRIMLESS IN 93040

24123 9330 FG



**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6) | 6(4)

**Dimtype: 1-10V or DALI or push button**

**Cutout dimension (mm): 84**



**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7

3(2) | 2(1)

**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 55**




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

2(2) | 2(1)

**Dimtype: DALI**

**Cutout dimension (mm): 55**




**300 90 135** LED POWER SUPPLY MULTI-POWER HV

3->4 | 2->4

**Dimtype: non-dimmable**

**Cutout dimension (mm): 90**




**21012 0010** LED POWER SUPPLY MULTI POWER

2 | 2

**Dimtype: non-dimmable**

**Cutout dimension (mm): 50**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1

3 | 3

**Dimtype: 1-10V**

**Cutout dimension (mm): 54**




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5

3 | 3

**Dimtype: DALI**

**Cutout dimension (mm): 54**




**21012 004W** LED POWER SUPPLY MULTI-POWER WDL

4(4) | 3(3)

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 84**




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

3 | 3

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 54**



**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

2->2 | 0


**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 50**

# DELTALIGHT

## SPY 39 TRIMLESS IN 93040

24123 9330 FG




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

2->3

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 55**




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2 | 2

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 48**




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8

1

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8

1

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 40**




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68

2(2)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68

2(1)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

**Dimtype: DALI**

**Cutout dimension (mm): 30**



**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

**Dimtype: DALI**

**Cutout dimension (mm): 30**


# DELTALIGHT

## SPY 39 TRIMLESS IN 93040

24123 9330 FG

### Mounting kits

---



**24144 0050** MOUNTING KIT SPY 39 TRIMLESS IN

Cutout dimension (mm): 82

### Light altering devices

---



**24144 0030 B** VISOR 39 B

### Finish your product

---



**24144 0010 B** SPY 39 TUBE B

**24144 0010 FBR** SPY 39 TUBE FBR

**24144 0010 FG** SPY 39 TUBE FG

**24144 0010 GC** SPY 39 TUBE GC

**24144 0010 W** SPY 39 TUBE W



**24144 0070** SPY 39 TUBE SBL

Notes: