





DEEP RINGO LED 92733

202 272 811 922 FBR

AVAILABLE IN

BLACK 202 272 811 922 B
BRUSHED ALU 202 272 811 922 BRA
BRUSHED ANTHRACITE 202 272 811 922 BRAT
BRUSHED BROWN BRONZE 202 272 811 922 BRBB
BRUSHED COPPER 202 272 811 922 BRCU
BRUSHED GOLD 202 272 811 922 BRG
BRUSHED OLD BRONZE 202 272 811 922 BROB
CREAM 202 272 811 922 CR
FLEMISH BRONZE 202 272 811 922 FBR
FLEMISH GOLD 202 272 811 922 FG
GOLD COLOURED 202 272 811 922 GC
PIANO BLACK 202 272 811 922 PB
WHITE 202 272 811 922 W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - 76
RECESSED DEPTH (MM)	90
THICKNESS OF MOUNTING SURFACE (MM)	min.5
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.2
ADJUSTABILITY	non adjustable
INFORMATION	REFLECTOR FL-33° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	E
CERTIFICATES	CB, EAC, ENEC, EPD, LCA

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm
TM-30 VALUES	rf: 89 / Rg: 100
SDCM	SDCM1
RISKGROUP	RG1
LM80	L90B10 > 50000
BEAMANGLE	33°
LED TECHNICS (LIGHT SOURCE)	1041lm // 8,6W // 121lm/W
LED TECHNICS (LUMINAIRE)	768lm // 9,9W // 78lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

DELTALIGHT

DEEP RINGO LED 92733

202 272 811 922 FBR


For detailed installation instructions, please consult the manual : [202_272_811_XXX_HAND.pdf](#)

CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Concrete	-
 Concrete + plaster	-
 Lintel + plaster	-
 Hollow-core slab	-
 Hollow-core slab + plaster	-
 Stretched ceiling	-

FINISH YOUR SPECIFICATION

Emergency units



21032 0270 B EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B

Cutout dimension (mm): 27

21032 0270 W EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W

DELTALIGHT

DEEP RINGO LED 92733

202 272 811 922 FBR

LED power supplies

of Fixtures



of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1

Dimtype: 1-10V

Cutout dimension (mm): 30



300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1

Dimtype: DALI

Cutout dimension (mm): 45



300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

1

Dimtype: non-dimmable

Cutout dimension (mm): 30



300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

1

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



300 48 500 ED1 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

1

Dimtype: 1-10V

Cutout dimension (mm): 30




300 48 500 ED5 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1

Dimtype: DALI

Cutout dimension (mm): 45




300 48 500 MDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL

1

Dimtype: non-dimmable

Cutout dimension (mm): 30



300 48 500 WDL LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL

1

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45

DELTALIGHT

DEEP RINGO LED 92733

202 272 811 922 FBR




300 90 61 LED POWER SUPPLY MULTI-POWER DIM6

2 | 2



Dimtype: mains (phase cut-off) or push button

Cutout dimension (mm): 56




300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

4(4) | 4(4)



Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 82




300 90 64 LED POWER SUPPLY MULTI-POWER DIM7

2(1) | 2(1)



Dimtype: 1-10V or push button

Cutout dimension (mm): 72




300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9

2



Dimtype: 1-10V or DALI or push button




300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

2(2) | 2(1)



Dimtype: DALI

Cutout dimension (mm): 72




300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9

2->6(6) | 6(4)



Dimtype: 1-10V or DALI or push button

Cutout dimension (mm): 84




300 90 124 LED POWER SUPPLY MULTI-POWER DIM7

3(2) | 2(1)



Dimtype: 1-10V or push button

Cutout dimension (mm): 55




300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5

2(2) | 2(1)



Dimtype: DALI

Cutout dimension (mm): 55




300 90 135 LED POWER SUPPLY MULTI-POWER HV

3->3 | 2->3



Dimtype: non-dimmable

Cutout dimension (mm): 90



21012 004W LED POWER SUPPLY MULTI-POWER WDL

3(3) | 3(3)



Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 84

DELTALIGHT

DEEP RINGO LED 92733

202 272 811 922 FBR



21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL

3 | 3

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 54



21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

1

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 50



21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

1

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 55



21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

2->3

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 55




21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

2 | 2

Dimtype: mains (phase cut-off)

Cutout dimension (mm): 48




21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68

2(2)

Dimtype: non-dimmable

Cutout dimension (mm): 60



21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68

2(1)

Dimtype: non-dimmable

Cutout dimension (mm): 60



21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 30



21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

2

Dimtype: DALI

Cutout dimension (mm): 30

DELTALIGHT

DEEP RINGO LED 92733

202 272 811 922 FBR

Notes: