





## M26L - HALOSCAN MP 92735 MDL

23123 9230 B

AVAILABLE IN  
**BLACK** 23123 9230 B  
**WHITE** 23123 9230 W



 [View on website](#)



### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Low voltage systems Low voltage system mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3
<b>ADJUSTABILITY</b>	0° to 45° swiveling, 355° rotatable
<b>INFORMATION</b>	LENS FL-35° EXCL.LED POWER SUPPLY 48V-DC

### Electrical info

<b>ELECTRICAL</b>	48V-DC
<b>CLASS</b>	III
<b>DIM TYPE</b>	MDL = 1-10V or DALI or push button
<b>ENERGY CLASS</b>	E
<b>CERTIFICATES</b>	CB, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 8,6W / CRI>90 (R9: 60) / 2700K / 1041lm
<b>TM-30 VALUES</b>	rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>BEAMANGLE</b>	35°
<b>LED TECHNICS (LIGHT SOURCE)</b>	1041lm // 8,6W // 121lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	799lm // 9,9W // 81lm/W

### Remarks

**Take a look at our MAGNETIC PROFILES movie**

### Requirements

LED POWER SUPPLY 48V-DC

### Options

DIMMABLE MODULATOR

### Accessories

HALOSCAN HONEYCOMB  
 HALOSCAN LINEAR SPREAD LENS  
 HALOSCAN KAP MP

# DELTALIGHT

## M26L - HALOSCAN MP 92735 MDL


23123 9230 B

For detailed installation instructions, please consult the manual : [23123\\_XXX0\\_HAND.pdf](#)


### FINISH YOUR SPECIFICATION

#### Current supply

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**21032 0030** SMART 48 MODULATOR PLUG-IN WD

19


Dimtype: WDL = wireless dimmable

#### SMART 48

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



**300 90 011** SMART 48 MODULATOR DIM9

19

Dimtype: 1-10V or DALI or push button




**300 90 012** SMART 48 MODULATOR WD

19


Dimtype: WDL = wireless dimmable

#### LED power supplies

#### # of Fixtures

 # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current



**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN

10

Dimtype: non-dimmable

# DELTALIGHT

## M26L - HALOSCAN MP 92735 MDL

23123 9230 B



**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN

24

Dimtype: non-dimmable




**21012 0230** LED POWER SUPPLY 48V-DC / 100W

10

Dimtype: non-dimmable

Cutout dimension (mm): 40




**21012 0240** LED POWER SUPPLY 48V-DC / 200W

20


Dimtype: non-dimmable

Cutout dimension (mm): 40


### Light altering devices



**23110 0040** HALOSCAN LINEAR SPREAD LENS



**23110 0050 B** HALOSCAN HONEYCOMB B




**23110 0060 B** HALOSCAN KAP MP B

**23110 0060 W** HALOSCAN KAP MP W

## COMPATIBLE COMPOSABLES

### SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)

### Available Colours




**23358 0000** SLM26L - PROFILE




# DELTALIGHT

## M26L - HALOSCAN MP 92735 MDL


23123 9230 B



**23358 0010** SLM26L - PROFILE 1m



**23358 0020** SLM26L - PROFILE 2m




**23358 0030** SLM26L - PROFILE 3m




## SHIFTLINE M35R profile


### Available Colours




**23375 0000** SLM35R - PROFILE



**23375 0010** SLM35R - PROFILE 1m



**23375 0020** SLM35R - PROFILE 2m



**23375 0030** SLM35R - PROFILE 3m



Notes: