

## PLAT-OH! TRIMLESS 92723

### REFERENCE



29513 9210 B

### AVAILABLE IN

**BLACK** 29513 9210 B

**GOLD COLOURED** 29513 9210 GC

**WHITE** 29513 9210 W



[View on website](#)



### General info

|                               |                                                     |
|-------------------------------|-----------------------------------------------------|
| <b>LOCATION</b>               | indoor                                              |
| <b>INSTALLATION</b>           | Ceiling Recessed                                    |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - Ø KIT                                       |
| <b>RECESSED DEPTH (MM)</b>    | 55                                                  |
| <b>INGRESS PROTECTION</b>     | IP20                                                |
| <b>WEIGHT (KG)</b>            | 0.2                                                 |
| <b>ADJUSTABILITY</b>          | 0° to 30° swiveling                                 |
| <b>INFORMATION</b>            | REFLECTOR FL-23°<br>EXCL. LED POWER SUPPLY 500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | E                         |
| <b>CERTIFICATES</b> | CB, ENEC                  |

### Lightsource info

|                                    |                                                           |
|------------------------------------|-----------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                       |
| <b>LIGHTSOURCE</b>                 | LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm |
| <b>TM-30 VALUES</b>                | Rf: 89 / Rg: 100                                          |
| <b>SDCM</b>                        | SDCM1                                                     |
| <b>RISKGROUP</b>                   | RG1                                                       |
| <b>LM80</b>                        | L90B10 > 50000                                            |
| <b>BEAMANGLE</b>                   | 23°                                                       |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 1041lm // 8,6W // 121lm/W                                 |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 748lm // 9,9W // 76lm/W                                   |

### Requirements

MOUNTING KIT PLAT-OH! TRIMLESS

LED POWER SUPPLY 350 / 500mA-DC DIM (Remote)

For detailed installation instructions, please consult the manual : [29513\\_XXX0\\_HAND.pdf](#)

## PLAT-OH! TRIMLESS 92723

29513 9210 B

### CEILING COMPATIBILITY

| Ceiling Type                                                                                    | Mounting Kit                                                                                                                  |          |
|-------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------|----------|
|  System ceiling |  29510 0020 - MOUNTING KIT PLAT-OH! TRIMLESS | Required |
|  Plasterboard   |  29510 0020 - MOUNTING KIT PLAT-OH! TRIMLESS | Required |
|  Stucanet       |  29510 0020 - MOUNTING KIT PLAT-OH! TRIMLESS | Required |

### FINISH YOUR SPECIFICATION






#### LED power supplies

#### # of Fixtures













# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current

|                                                                                    |                                                                                                                                          |                        |
|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------|------------------------|
|  | <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 30                  | 2 <input type="text"/> |
|  | <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 45                   | 2 <input type="text"/> |
|  | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 30            | 2 <input type="text"/> |
|  | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 45 | 2 <input type="text"/> |
|  | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 30                  | 2 <input type="text"/> |











PLAT-OH! TRIMLESS 92723

29513 9210 B

|                                                                                    |                                                                          |                |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|----------------|--------------------------|
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                |                          |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                |                          |
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 2              | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                |                          |
|    | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 2   2          | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |                |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |                |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 4(4)   4(4)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |                |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                |                          |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9    | 2   -          | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5                       | 2(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                |                          |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9                    | 2->6(6)   6(4) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                |                          |
|                                                                                    | Cutout dimension (mm): 84                                                |                |                          |
|  | <b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7                      | 3(2)   2(1)    | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                |                          |
|                                                                                    | Cutout dimension (mm): 55                                                |                |                          |

PLAT-OH! TRIMLESS 92723








29513 9210 B

|                                                                                    |                                                                                                                                     |             |                          |
|------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 55                           | 2(2)   2(1) | <input type="checkbox"/> |
|    | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 90                          | 3->4   2->4 | <input type="checkbox"/> |
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 50                             | 2   2       | <input type="checkbox"/> |
|    | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 54                               | 3   3       | <input type="checkbox"/> |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 54                                | 3   3       | <input type="checkbox"/> |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 84              | 4(4)   3(3) | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 54      | 3   3       | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 50 | 2->2   0    | <input type="checkbox"/> |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 1           | <input type="checkbox"/> |
|  | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 2->3        | <input type="checkbox"/> |


# DELTALIGHT

## PLAT-OH! TRIMLESS 92723

29513 9210 B

|                                                                                    |                                                                      |       |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|-------|--------------------------|
|    | <b>21012 0298</b> LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8    | 2   2 | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 48                                                          |                                                                      |       |                          |
|    | <b>21012 0308</b> LED POWER SUPPLY 350mA / 7,35W DIM8                | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 40                                                          |                                                                      |       |                          |
|    | <b>21012 0318</b> LED POWER SUPPLY 500mA / 10W DIM8                  | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 40                                                          |                                                                      |       |                          |
|    | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 2(2)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 2(1)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 2     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |

### Mounting kits

|                                                                                    |                                                  |  |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------|--|--------------------------|
|  | <b>29510 0020</b> MOUNTING KIT PLAT-OH! TRIMLESS |  | <input type="checkbox"/> |
| Cutout dimension (mm): 80                                                          |                                                  |  |                          |

Notes:

# DELTALIGHT

## **PLAT-OH! TRIMLESS 92723**

29513 9210 B