



## INFORM SQ F144-3 93067

25523 9320 W-W


AVAILABLE IN

**BLACK-BLACK** 25523 9320 B-B

**BLACK-FLEMISH GOLD** 25523 9320 B-FG

**WHITE-BLACK** 25523 9320 W-B

**WHITE-WHITE** 25523 9320 W-W



[View on website](#)



### General info

|                           |                                                             |
|---------------------------|-------------------------------------------------------------|
| <b>LOCATION</b>           | indoor                                                      |
| <b>INSTALLATION</b>       | Ceiling Surface mounted                                     |
| <b>INGRESS PROTECTION</b> | IP20                                                        |
| <b>WEIGHT (KG)</b>        | 1                                                           |
| <b>ADJUSTABILITY</b>      | non adjustable                                              |
| <b>INFORMATION</b>        | 36 x REFLECTOR FL-67°<br>EXCL.LED POWER SUPPLY 300/450mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | E                         |
| <b>CERTIFICATES</b> | CB, ENEC, EPD             |

### Lightsource info

|                                    |                                                                |
|------------------------------------|----------------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                            |
| <b>LIGHTSOURCE</b>                 | LED cluster 10,5-16,7W / CRI>90 (R9: 50) / 3000K / 1602-2315lm |
| <b>TM-30 VALUES</b>                | Rf: 92 / Rg: 100                                               |
| <b>SDCM</b>                        | SDCM3                                                          |
| <b>RISKGROUP</b>                   | RG1                                                            |
| <b>LM80</b>                        | L80 > 60000                                                    |
| <b>BEAMANGLE</b>                   | 67°                                                            |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 2315lm // 16,7W // 138lm/W                                     |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 2021lm // 19,2W // 105lm/W                                     |

### Requirements

INFORM POWER SUPPLY 17W

For detailed installation instructions, please consult the manual : [25523\\_XXX0\\_HAND.pdf](#)

FINISH YOUR SPECIFICATION

| LED power supplies                                                                                                                                                                                                                                                                                              |                                                                         | # of Fixtures             |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------|---------------------------|
| <div><div><div></div><div></div></div><div># of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</div></div> |                                                                         | Min current   Max current |
| <div><div><div><div></div><div></div></div><div></div></div><div><div>280</div><div>121</div><div>30</div></div></div> <div><div><div><div></div><div></div></div><div></div></div><div>Dimtype: non-dimmable</div></div>                                                                                       | <div><div>25510 0050</div><div>INFORM POWER SUPPLY 25W</div></div>      | <div>1<div></div></div>   |
| <div><div><div><div></div><div></div></div><div></div></div><div><div>280</div><div>121</div><div>30</div></div></div> <div><div><div><div></div><div></div></div><div></div></div><div>Dimtype: DALI</div></div>                                                                                               | <div><div>25510 0065</div><div>INFORM POWER SUPPLY 35W DIM5</div></div> | <div>1<div></div></div>   |
| <div><div><div><div></div><div></div></div><div></div></div><div><div>131</div><div>200</div><div>70</div></div></div> <div><div><div><div></div><div></div></div><div></div></div><div>Dimtype: DALI</div></div>                                                                                               | <div><div>25510 0375</div><div>INFORM POWER SUPPLY 17W DIM5</div></div> | <div>1<div></div></div>   |
| <div><div><div><div></div><div></div></div><div></div></div><div><div>131</div><div>200</div><div>70</div></div></div> <div><div><div><div></div><div></div></div><div></div></div><div>Dimtype: non-dimmable</div></div>                                                                                       | <div><div>25510 0420</div><div>INFORM POWER SUPPLY 17W</div></div>      | <div>1<div></div></div>   |

Notes: