



SPY 39 PLUG 93020

24149 9320 BRA

AVAILABLE IN

NOIR 24149 9320 B

ALU BROSSÉ 24149 9320 BRA

ANTHRACITE BROSSÉ 24149 9320 BRAT

CUIVRE BROSSÉ 24149 9320 BRCU

OR BROSSÉ 24149 9320 BRG

BRONZE VIEUX BROSSÉ 24149 9320 BROB

FLEMISH BRONZE 24149 9320 FBR

FLEMISH GOLD 24149 9320 FG

ENTIÈREMENT BLANC 24149 9320 FW


COULEUR OR 24149 9320 GC

NOIR PIANO 24149 9320 PB

BLANC 24149 9320 W



0-85°/355°



[View on website](#)



General info

LOCATION	interieur
INSTALLATION	Plafond Semi-encastré
CUTOUT SHAPE/SIZE (MM)	circulaire - Ø KIT
RECESSED DEPTH (MM)	80
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.4
ADJUSTABILITY	0° à 85° inclinable, 355° rotatif
INFORMATION	REFLECTOR FL-20° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
DIM TYPE	selon le type d'alimentation externe
ENERGY CLASS	E
CERTIFICATION	CB, ENEC

Lightsources info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 5,8-8,6W / CRI>90 (R9: 52) / 3000K / 787-1089lm
RVALUES	rf: 90 / Rg: 99
SDMC	SDCM1
RISKGROUPE	RG1
LM80	L90B10 > 50000
BEAMANGLE	20°
LED TECHNICS (LIGHT SOURCE)	1089lm // 8,6W // 127lm/W
LED TECHNICS (LUMINAIRE)	888lm // 9,9W // 90lm/W

Requirements

SPY 39 TUBE or VISOR 39
MOUNTING KIT PLUG O.F.A.
LED POWER SUPPLY 350 / 500mA-DC DIM

DELTALIGHT

SPY 39 PLUG 93020

24149 9320 BRA

For detailed installation instructions, please consult the manual : [24149_XXX0_HAND.pdf](#)





CEILING COMPATIBILITY

Ceiling Type	Mounting Kit	
 Plasterboard	 24144 0060 - MOUNTING KIT PLUG O.F.A.	Required
 Concrete + plaster	 24144 0060 - MOUNTING KIT PLUG O.F.A.	Required
 Lintel + plaster	 24144 0060 - MOUNTING KIT PLUG O.F.A.	Required
 Hollow-core slab + plaster	 24144 0060 - MOUNTING KIT PLUG O.F.A.	Required

FINISH YOUR SPECIFICATION







les alimentations led

of Fixtures

 web2print_power_supply_info_box			Min current Max current
	<u>300 48 350 ED1</u> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 Dimtype: 1 à 10 V Cutout dimension (mm): 30	2	
	<u>300 48 350 ED5</u> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 Dimtype: DALI Cutout dimension (mm): 45	2	
	<u>300 48 350 MDL</u> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL Dimtype: non dimmable Cutout dimension (mm): 30	2	
	<u>300 48 350 WDL</u> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL Dimtype: WDL = dimmable sans fil Cutout dimension (mm): 45	2	

SPY 39 PLUG 93020







24149 9320 BRA

	300 48 500 ED1	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1	2	☐
	Dimtype: 1 à 10 V			
	Cutout dimension (mm): 30			
	300 48 500 ED5	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	2	☐
	Dimtype: DALI			
	Cutout dimension (mm): 45			
	300 48 500 MDL	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL	2	☐
	Dimtype: non dimmable			
	Cutout dimension (mm): 30			
	300 48 500 WDL	LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL	2	☐
	Dimtype: WDL = dimmable sans fil			
	Cutout dimension (mm): 45			
	300 90 61	LED POWER SUPPLY MULTI-POWER DIM6	2 2	☐
	Dimtype: fin de phase ou bouton poussoir			
	Cutout dimension (mm): 56			
	300 90 63	LED POWER SUPPLY MULTI-POWER DIM9	4(4) 4(4)	☐
	Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
	Cutout dimension (mm): 82			
	300 90 64	LED POWER SUPPLY MULTI-POWER DIM7	2(2) 2(1)	☐
	Dimtype: 1 à 10 V ou bouton poussoir			
	Cutout dimension (mm): 72			
	300 90 67	LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9	2 -	☐
	Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
	300 90 68	LED POWER SUPPLY MULTI-POWER DIM5	2(2) 2(1)	☐
	Dimtype: DALI			
	Cutout dimension (mm): 72			
	300 90 69	LED POWER SUPPLY MULTI-POWER HV DIM9	2->6(6) 6(4)	☐
	Dimtype: 1 à 10 V ou DALI ou bouton poussoir			
	Cutout dimension (mm): 84			

DELTALIGHT

SPY 39 PLUG 93020









24149 9320 BRA

	300 90 124 LED POWER SUPPLY MULTI-POWER DIM7 Dimtype: 1 à 10 V ou bouton poussoir Cutout dimension (mm): 55	3(2) 2(1)	☐
	300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5 Dimtype: DALI Cutout dimension (mm): 55	2(2) 2(1)	☐
	300 90 135 LED POWER SUPPLY MULTI-POWER HV Dimtype: non dimmable Cutout dimension (mm): 90	3->4 2->4	☐
	21012 0010 LED POWER SUPPLY MULTI POWER Dimtype: non dimmable Cutout dimension (mm): 50	2 2	☐
	21012 0021 LED POWER SUPPLY MULTI POWER DIM1 Dimtype: 1 à 10 V Cutout dimension (mm): 54	3 3	☐
	21012 0035 LED POWER SUPPLY MULTI POWER DIM5 Dimtype: DALI Cutout dimension (mm): 54	3 3	☐
	21012 004W LED POWER SUPPLY MULTI-POWER WDL Dimtype: WDL = dimmable sans fil Cutout dimension (mm): 84	4(4) 3(3)	☐
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL Dimtype: WDL = dimmable sans fil Cutout dimension (mm): 54	3 3	☐
	21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 Dimtype: fin de phase Cutout dimension (mm): 50	2->2 0	☐
	21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 Dimtype: fin de phase Cutout dimension (mm): 55	1	☐


DELTALIGHT

SPY 39 PLUG 93020

24149 9320 BRA

	21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 Dimtype: fin de phase Cutout dimension (mm): 55	2->3	☐
	21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 Dimtype: fin de phase Cutout dimension (mm): 48	2 2	☐
	21012 0308 LED POWER SUPPLY 350mA / 7,35W DIM8 Dimtype: fin de phase Cutout dimension (mm): 40	1	☐
	21012 0318 LED POWER SUPPLY 500mA / 10W DIM8 Dimtype: fin de phase Cutout dimension (mm): 40	1	☐
	21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68 Dimtype: non dimmable Cutout dimension (mm): 60	2(2)	☐
	21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68 Dimtype: non dimmable Cutout dimension (mm): 60	2(1)	☐
	21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 Dimtype: DALI Cutout dimension (mm): 30	2	☐
	21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 Dimtype: DALI Cutout dimension (mm): 30	2	☐

kit de montage

	24144 0060 MOUNTING KIT PLUG O.F.A. Cutout dimension (mm): 62 (CONCRETE: 102)	☐
--	---	--------------------------

DELTALIGHT

SPY 39 PLUG 93020

24149 9320 BRA

modifier les dispositifs de lumière



24144 0030 B VISOR 39 B

☐

Terminez votre produit



24144 0010 B SPY 39 TUBE B

☐

24144 0010 FBR SPY 39 TUBE FBR

☐

24144 0010 FG SPY 39 TUBE FG

☐

24144 0010 GC SPY 39 TUBE GC

☐

24144 0010 W SPY 39 TUBE W

☐

24144 0070 SPY 39 TUBE SBL

☐

Notes: