

## SPY 20 L 2 AIR 93030

27218 9320 B-B

AVAILABLE IN



**BLACK-BLACK** 27218 9320 B-B

**FLEMISH BRONZE-BLACK** 27218 9320 FBR-B

**FLEMISH GOLD-BLACK** 27218 9320 FG-B

**GOLD COLORED-BLACK** 27218 9320 GC-B

**WHITE-BLACK** 27218 9320 W-B



[View on website](#)



### General info

|                               |                                                                                  |
|-------------------------------|----------------------------------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                                           |
| <b>INSTALLATION</b>           | Ceiling Recessed                                                                 |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - Ø KIT                                                                    |
| <b>INGRESS PROTECTION</b>     | IP20                                                                             |
| <b>WEIGHT (KG)</b>            | 0.2                                                                              |
| <b>ADJUSTABILITY</b>          | 0° to 90° swiveling, 355° rotatable                                              |
| <b>INFORMATION</b>            | REFLECTOR FL-30°<br>EXCLLED POWER SUPPLY 350-1050mA-DC<br>SPY 20 TUBE B included |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | F                         |

### Lightsource info

|                                    |                                                              |
|------------------------------------|--------------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                          |
| <b>LIGHTSOURCE</b>                 | 2 x (LED array 1-3,1W / CRI>90 (R9: 60) / 3000K / 131-334lm) |
| <b>TM-30 VALUES</b>                | rf: 92 / Rg: 99                                              |
| <b>SDCM</b>                        | SDCM3                                                        |
| <b>RISKGROUP</b>                   | RG2                                                          |
| <b>LM80</b>                        | L90B10 > 150000                                              |
| <b>BEAMANGLE</b>                   | 30°                                                          |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 668lm // 6,2W // 109lm/W                                     |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 503lm // 7,1W // 71lm/W                                      |

### Requirements

MOUNTING KIT AIR 104

LED POWER SUPPLY 350 / 500 / 700 / 1050mA-DC DIM

For detailed installation instructions, please consult the manual : [27218\\_XXX0\\_HAND.pdf](#)

# DELTALIGHT

## SPY 20 L 2 AIR 93030

27218 9320 B-B

### CEILING COMPATIBILITY

| Ceiling Type                                                                     | Mounting Kit                                                                                                                |          |
|----------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------|----------|
|  |  29810 0040 - MOUNTING KIT SIDE AIR 104    | Required |
|                                                                                  |  29810 0100 - MOUNTING KIT SIDE AIR ONLY 1 | Required |
|                                                                                  |  29810 0080 - MOUNTING KIT NO AIR 104      | Required |
|  |  29810 0080 - MOUNTING KIT NO AIR 104      | Required |
|                                                                                  |  29810 0200 - MOUNTING KIT TOP AIR ONLY 1  | Required |
|                                                                                  |  29810 0240 - MOUNTING KIT TOP AIR 104     | Required |

### FINISH YOUR SPECIFICATION


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the 'I' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

2->7

Dimtype: 1-10V

Cutout dimension (mm): 30




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

2->7

Dimtype: DALI

Cutout dimension (mm): 45




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL

2->7

Dimtype: non-dimmable

Cutout dimension (mm): 30




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL

2->7

Dimtype: WDL = wireless dimmable

Cutout dimension (mm): 45



**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1

2->7


Dimtype: 1-10V

Cutout dimension (mm): 30

# DELTALIGHT



## SPY 20 L 2 AIR 93030

27218 9320 B-B

|                                                                                    |                                                                          |                                |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|--------------------------------|--------------------------|
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2->7                           | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                |                          |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 2->7                           | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                                |                          |
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 2->7                           | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                |                          |
|    | <b>300 48 700 ED1</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM1 | 2->7                           | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V                                                           |                                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                                |                          |
|  | <b>300 48 700 ED5</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5 | 2->7                           | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |                                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                |                          |
|  | <b>300 48 700 MDL</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W MDL  | 2->7                           | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |                                |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |                                |                          |
|  | <b>300 48 700 WDL</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W WDL  | 2->7                           | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |                                |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |                                |                          |
|  | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 8   8   8                      | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |                                |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |                                |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 13(12)   12(12)   12(9)   9(6) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |                                |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |                                |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 2->9(7)   8(5)   8(3)          | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |                                |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |                                |                          |

SPY 20 L 2 AIR 93030








27218 9320 B-B

|                                                                                    |                                                                                                                                 |                                 |                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------|---------------------------------|--------------------------|
|    | <b>300 90 67</b><br>LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9<br>Dimtype: 1-10V or DALI or push button               | 2->7   2->7   2->7              | <input type="checkbox"/> |
|    | <b>300 90 68</b><br>LED POWER SUPPLY MULTI-POWER DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 72                             | 8(7)   8(5)   7(3)   -          | <input type="checkbox"/> |
|    | <b>300 90 69</b><br>LED POWER SUPPLY MULTI-POWER HV DIM9<br>Dimtype: 1-10V or DALI or push button<br>Cutout dimension (mm): 84  | 4->20(19)   20(14)   14(14)   - | <input type="checkbox"/> |
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br>Dimtype: 1-10V or push button<br>Cutout dimension (mm): 55            | 3->8(7)   7(5)   5(3)           | <input type="checkbox"/> |
|  | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 55                       | 2->8(7)   7(5)   4(3)           | <input type="checkbox"/> |
|  | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 90                      | 9->14   6->14   5->15   5->11   | <input type="checkbox"/> |
|  | <b>300 90 136</b><br>LED POWER SUPPLY MULTI-POWER HC DIM9<br>Dimtype: 1-10V or DALI or push button<br>Cutout dimension (mm): 90 | 7(6)                            | <input type="checkbox"/> |
|  | <b>300 90 148</b><br>LED POWER SUPPLY 1050mA-DC / 22W<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 48                     | 3(1)                            | <input type="checkbox"/> |
|  | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 50                         | 3->7   2->7   2->7   2->6       | <input type="checkbox"/> |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 54                           | 2->9   2->9   2->8   2->6       | <input type="checkbox"/> |

# DELTALIGHT

## SPY 20 L 2 AIR 93030







27218 9320 B-B

|                                                                                    |                                                                                                                                         |                                  |                          |
|------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|----------------------------------|--------------------------|
|    | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 54                                | 2->8   2->9   2->9   2->6        | <input type="checkbox"/> |
|    | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 84              | 12(12)   12(12)   12(10)   10(6) | <input type="checkbox"/> |
|    | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 54      | 2->9   2->9   2->8   2->6        | <input type="checkbox"/> |
|    | <b>21012 0258</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 50 | 4->5                             | <input type="checkbox"/> |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 50 | 5->7                             | <input type="checkbox"/> |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 3->5   3->4                      | <input type="checkbox"/> |
|  | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 55 | 6->9   6->8                      | <input type="checkbox"/> |
|  | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 48 | 2->7   2->7   2->4               | <input type="checkbox"/> |
|  | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40             | 3->3                             | <input type="checkbox"/> |
|  | <b>21012 0318</b><br>LED POWER SUPPLY 500mA / 10W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40               | 3->3                             | <input type="checkbox"/> |


# DELTALIGHT

## SPY 20 L 2 AIR 93030

27218 9320 B-B

|                                                                                    |                                                                      |      |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|------|--------------------------|
|    | <b>21012 0328</b> LED POWER SUPPLY 700mA / 15W DIM8                  | 3->3 | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off)                                       |      |                          |
|                                                                                    | Cutout dimension (mm): 40                                            |      |                          |
|   | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 8(7) | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                |      |                          |
|                                                                                    | Cutout dimension (mm): 60                                            |      |                          |
|   | <b>21012 0490</b> LED POWER SUPPLY 700mA-DC / 30W IP68               | 7(3) | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                |      |                          |
|                                                                                    | Cutout dimension (mm): 60                                            |      |                          |
|   | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 8(5) | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                |      |                          |
|                                                                                    | Cutout dimension (mm): 60                                            |      |                          |
|  | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 2->7 | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                        |      |                          |
|                                                                                    | Cutout dimension (mm): 30                                            |      |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 2->7 | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                        |      |                          |
|                                                                                    | Cutout dimension (mm): 30                                            |      |                          |
|  | <b>21032 0315</b> LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5 | 2->7 | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                        |      |                          |
|                                                                                    | Cutout dimension (mm): 30                                            |      |                          |

### Mounting kits side air + light


|                                                                                    |                                             |  |                          |
|------------------------------------------------------------------------------------|---------------------------------------------|--|--------------------------|
|  | <b>29810 0040</b> MOUNTING KIT SIDE AIR 104 |  | <input type="checkbox"/> |
|                                                                                    | Cutout dimension (mm): 168                  |  |                          |

# DELTALIGHT

## SPY 20 L 2 AIR 93030

27218 9320 B-B

### Mounting kits top air + light




**29810 0240** MOUNTING KIT TOP AIR 104

Cutout dimension (mm): 135

☐

### Mounting kits side air only




**29810 0100** MOUNTING KIT SIDE AIR ONLY 1

Cutout dimension (mm): 168

☐

### Mounting kits top air only




**29810 0200** MOUNTING KIT TOP AIR ONLY 1

Cutout dimension (mm): 135

☐

### Mounting kits no air



**29810 0080** MOUNTING KIT NO AIR 104

Cutout dimension (mm): 168

☐

Notes: