
DELTALIGHT




# MINIGRID 67 IN 2 92718

**REFERENCE** 100004 9210 W-W

AVAILABLE IN
**BLACK-BLACK** 100004 9210 B-B
**WHITE-BLACK** 100004 9210 W-B
**WHITE-WHITE** 100004 9210 W-W




View on website

| General info | |
|---|---|
| **LOCATION** | indoor |
| **INSTALLATION** | Ceiling Recessed |
| **CUTOUT SHAPE/SIZE (MM)** | rectangle - 155 x 84 |
| **RECESSED DEPTH (MM)** | 70 |
| **THICKNESS OF MOUNTING SURFACE (MM)** | max.25 |
| **INGRESS PROTECTION** | IP20 |
| **WEIGHT (KG)** | 0.8 |
| **ADJUSTABILITY** | 0° to 30° swiveling, 360° rotatable |
| **INFORMATION** | REFLECTOR SP-18°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

| Electrical info | |
|---|---|
| **CLASS** | III |
| **DIM TYPE** | depending on power supply |
| **ENERGY CLASS** | F |
| **CERTIFICATES** | CB, ENEC |

| Lightsource info | |
|---|---|
| **LIGHTSOURCE NAME** | LED |
| **LIGHTSOURCE** | 2 x (LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 702-974lm) |
| **TM-30 VALUES** | Rf: 89 / Rg: 100 |
| **SDCM** | SDCM1 |
| **RISKGROUP** | RG1 |
| **LM80** | L90B10 > 50000 |
| **BEAMANGLE** | 18° |
| **LED TECHNICS (LIGHT SOURCE)** | 1948lm // 17,2W // 113lm/W |
| **LED TECHNICS (LUMINAIRE)** | 1324lm // 19,8W // 67lm/W |

**Requirements**

LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : **100004_XXX0_HAND.pdf**

# MINIGRID 67 IN 2 92718

100004 9210 W-W

## CEILING COMPATIBILITY

| Ceiling Type | Mounting Kit |
|---|---|
|  System ceiling | - |
|  Plasterboard | - |
|  Stucanet | - |
|  Wood | - |
|  Stretched ceiling | - |


## FINISH YOUR SPECIFICATION

### LED power supplies

### # of Fixtures

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.


**Min current | Max current**




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 — 1 ☐

**Dimtype: 1-10V**


**Cutout dimension (mm): 30**




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 1 ☐

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL — 1 ☐

**Dimtype: non-dimmable**

**Cutout dimension (mm): 30**





**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL — 1 ☐

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 45**

# MINIGRID 67 IN 2 92718


100004 9210 W-W




**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 — 1

**Dimtype: 1-10V**


**Cutout dimension (mm): 30**




**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 1

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL — 1

**Dimtype: non-dimmable**


**Cutout dimension (mm): 30**




**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL — 1

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 45**




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6 — 1 | 1

**Dimtype: mains (phase cut-off) or push button**


**Cutout dimension (mm): 56**




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9 — 2(2) | 2(2)

**Dimtype: 1-10V or DALI or push button**


**Cutout dimension (mm): 82**




**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7 — 1(1) | 1(1/2)


**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 72**




**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 — 1 | -


**Dimtype: 1-10V or DALI or push button**




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5 — 1(1) | 1(1/2)

**Dimtype: DALI**

**Cutout dimension (mm): 72**





**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9 — 3(3) | 3(2)

**Dimtype: 1-10V or DALI or push button**

**Cutout dimension (mm): 84**

# MINIGRID 67 IN 2 92718

100004 9210 W-W




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7 1(1) | 1(1/2)

**Dimtype: 1-10V or push button**


**Cutout dimension (mm): 55**




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5 1(1) | 1(1/2)

**Dimtype: DALI**


**Cutout dimension (mm): 55**




**300 90 135** LED POWER SUPPLY MULTI-POWER HV 2->2 | 2

**Dimtype: non-dimmable**


**Cutout dimension (mm): 90**




**21012 0010** LED POWER SUPPLY MULTI POWER 1 | 1

**Dimtype: non-dimmable**


**Cutout dimension (mm): 50**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1 1 | 1

**Dimtype: 1-10V**


**Cutout dimension (mm): 54**




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5 1 | 1

**Dimtype: DALI**


**Cutout dimension (mm): 54**




**21012 004W** LED POWER SUPPLY MULTI-POWER WDL 2(2) | 2(1)

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 84**




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL 1 | 1

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 54**




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8 1/2

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 50**





**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 1 | -

**Dimtype: mains (phase cut-off)**

**Cutout dimension (mm): 50**

# MINIGRID 67 IN 2 92718


100004 9210 W-W




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 — 1/2

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 — 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 — 1 | 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 48**




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8 — 1/2

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 40**




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8 — 1/2

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 40**




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68 — 1(1)

**Dimtype: non-dimmable**


**Cutout dimension (mm): 60**




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68 — 1(1/2)

**Dimtype: non-dimmable**


**Cutout dimension (mm): 60**




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 1

**Dimtype: DALI**

**Cutout dimension (mm): 30**




**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 1

**Dimtype: DALI**

**Cutout dimension (mm): 30**

## MINIGRID 67 IN 2 92718

100004 9210 W-W

Notes: