



## SPY FOCUS CLIP MP 927

19873 9200 FBR-B

AVAILABLE IN

**BLACK-BLACK** 19873 9200 B-B



**FLEMISH BRONZE-BLACK** 19873 9200 FBR-B

**FLEMISH GOLD-BLACK** 19873 9200 FG-B

**FULL WHITE** 19873 9200 FW

**WHITE-BLACK** 19873 9200 W-B

**WHITE-WHITE** 19873 9200 W-W



[View on website](#)



### General info

|                               |                                                              |
|-------------------------------|--------------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                       |
| <b>INSTALLATION</b>           | Ceiling Semi-recessed                                        |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | round - 51                                                   |
| <b>RECESSED DEPTH (MM)</b>    | 40                                                           |
| <b>INGRESS PROTECTION</b>     | IP20                                                         |
| <b>WEIGHT (KG)</b>            | 0.5                                                          |
| <b>ADJUSTABILITY</b>          | 0° to 90° swiveling, 355° rotatable                          |
| <b>INFORMATION</b>            | ADJUSTABLE BEAM 12°-45°<br>EXCLLED POWER SUPPLY 350-500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | F                         |
| <b>CERTIFICATES</b> | CB, EAC, ENEC, LCA        |

### Lightsource info

|                                    |                                                              |
|------------------------------------|--------------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                          |
| <b>LIGHTSOURCE</b>                 | LED array 11,6-17,2W / CRI>90 (R9: 60) / 2700K / 1458-2009lm |
| <b>TM-30 VALUES</b>                | rf: 89 / Rg: 100                                             |
| <b>SDCM</b>                        | SDCM1                                                        |
| <b>RISKGROUP</b>                   | RG1                                                          |
| <b>LM80</b>                        | L90B10 > 50000                                               |
| <b>BEAMANGLE</b>                   | 12°-45°                                                      |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 2009lm // 17,2W // 117lm/W                                   |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 703lm // 19,8W // 36lm/W                                     |

### Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

### Options

MOUNTING KIT FLUSH SPY

For detailed installation instructions, please consult the manual : [19873\\_9X00\\_HAND.pdf](#)

# DELTALIGHT

## SPY FOCUS CLIP MP 927

19873 9200 FBR-B

### CEILING COMPATIBILITY

| Ceiling Type                                                                                                         | Mounting Kit                                                                                                                                 |
|----------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------|
|  <b>System ceiling</b>               |  414 90 01 - MOUNTING KIT FLUSH SPY <span>Required</span>   |
|  <b>Plasterboard</b>                 |  414 90 01 - MOUNTING KIT FLUSH SPY <span>Required</span>   |
|  <b>Stucanet</b>                     |  414 90 01 - MOUNTING KIT FLUSH SPY <span>Required</span>   |
|  <b>Wood</b>                         | -                                                                                                                                            |
|  <b>Concrete</b>                     | -                                                                                                                                            |
|  <b>Concrete + plaster</b>          |  414 90 01 - MOUNTING KIT FLUSH SPY <span>Required</span>   |
|  <b>Lintel + plaster</b>           |  414 90 01 - MOUNTING KIT FLUSH SPY <span>Required</span> |
|  <b>Hollow-core slab</b>           | -                                                                                                                                            |
|  <b>Hollow-core slab + plaster</b> |  414 90 01 - MOUNTING KIT FLUSH SPY <span>Required</span> |
|  <b>Stretched ceiling</b>          | -                                                                                                                                            |

### FINISH YOUR SPECIFICATION


#### LED power supplies

#### # of Fixtures



# of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

Min current | Max current




**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1

1

**Dimtype: 1-10V**

**Cutout dimension (mm): 30**



**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5











1

**Dimtype: DALI**

**Cutout dimension (mm): 45**











SPY FOCUS CLIP MP 927

19873 9200 FBR-B

|                                                                                    |                                                                          |             |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |             |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |             |                          |
|    | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |             |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |             |                          |
|    | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V                                                           |             |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |             |                          |
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |             |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |             |                          |
|  | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |             |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |             |                          |
|  | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |             |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |             |                          |
|  | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 1   1       | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |             |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |             |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 2(2)   2(2) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |             |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |             |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 1(1)   1(0) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |             |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |             |                          |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9    | 1   -       | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |             |                          |








SPY FOCUS CLIP MP 927

19873 9200 FBR-B


|                                                                                    |                                                                                                                                |             |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 90 68</b><br>LED POWER SUPPLY MULTI-POWER DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 72                            | 1(1)   1(0) | <input type="checkbox"/> |
|    | <b>300 90 69</b><br>LED POWER SUPPLY MULTI-POWER HV DIM9<br>Dimtype: 1-10V or DALI or push button<br>Cutout dimension (mm): 84 | 3(3)   3(2) | <input type="checkbox"/> |
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br>Dimtype: 1-10V or push button<br>Cutout dimension (mm): 55           | 1(1)   1(0) | <input type="checkbox"/> |
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 55                      | 1(1)   1(0) | <input type="checkbox"/> |
|  | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 90                     | 2->2   2    | <input type="checkbox"/> |
|  | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br>Dimtype: non-dimmable<br>Cutout dimension (mm): 50                        | 1   1       | <input type="checkbox"/> |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br>Dimtype: 1-10V<br>Cutout dimension (mm): 54                          | 1   1       | <input type="checkbox"/> |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br>Dimtype: DALI<br>Cutout dimension (mm): 54                           | 1   1       | <input type="checkbox"/> |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 84         | 2(2)   2(2) | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br>Dimtype: WDL = wireless dimmable<br>Cutout dimension (mm): 54 | 1   1       | <input type="checkbox"/> |

SPY FOCUS CLIP MP 927

19873 9200 FBR-B

|                                                                                    |                                                                      |       |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|-------|--------------------------|
|    | <b>21012 0268</b> LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8    | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 50                                                          |                                                                      |       |                          |
|    | <b>21012 0288</b> LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8    | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 55                                                          |                                                                      |       |                          |
|    | <b>21012 0298</b> LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8    | 1   1 | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 48                                                          |                                                                      |       |                          |
|    | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 1(1)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 1(0)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 1     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 1     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |

Mounting kits

|                                                                                    |                                         |  |                          |
|------------------------------------------------------------------------------------|-----------------------------------------|--|--------------------------|
|  | <b>414 90 01</b> MOUNTING KIT FLUSH SPY |  | <input type="checkbox"/> |
| Cutout dimension (mm): 83                                                          |                                         |  |                          |

Notes:

# DELTALIGHT

## **SPY FOCUS CLIP MP 927**

19873 9200 FBR-B