
DELTALIGHT




# ENTERO RD-M TRIMLESS WALLWASH 930

**REFERENCE** 28433 9300 B

AVAILABLE IN
**BLACK** 28433 9300 B
**GOLD COLOURED** 28433 9300 GC
**WHITE** 28433 9300 W




View on website

| General info | |
|---|---|
| **LOCATION** | indoor |
| **INSTALLATION** | Ceiling Recessed |
| **CUTOUT SHAPE/SIZE (MM)** | round - Ø KIT |
| **RECESSED DEPTH (MM)** | 95 |
| **INGRESS PROTECTION** | IP20 |
| **WEIGHT (KG)** | 0.16 |
| **ADJUSTABILITY** | non adjustable |
| **INFORMATION** | REFLECTOR WALLWASH<br>EXCL.LED POWER SUPPLY 350-700mA-DC |

| Electrical info | |
|---|---|
| **CLASS** | III |
| **DIM TYPE** | depending on power supply |
| **ENERGY CLASS** | E |
| **CERTIFICATES** | CB, ENEC, EPD |

| Lightsource info | |
|---|---|
| **LIGHTSOURCE NAME** | LED |
| **LIGHTSOURCE** | LED array 5,8-12,4W / CRI>90 (R9: 52) / 3000K / 787-1467lm |
| **TM-30 VALUES** | Rf: 90 / Rg: 99 |
| **SDCM** | SDCM1 |
| **RISKGROUP** | RG1 |
| **LM80** | L90B10 > 50000 |
| **LED TECHNICS (LIGHT SOURCE)** | 1467lm // 12,4W // 118lm/W |
| **LED TECHNICS (LUMINAIRE)** | 1141lm // 14,3W // 80lm/W |

**Requirements**

MOUNTING KIT ENTERO ROUND M
LED POWER SUPPLY 350 / 500 / 700mA-DC DIM (Remote)

For detailed installation instructions, please consult the manual : **28433_XXX0_HAND.pdf**

# ENTERO RD-M TRIMLESS WALLWASH 930


28433 9300 B

## CEILING COMPATIBILITY

| Ceiling Type | Mounting Kit | |
|---|---|---|
|  **System ceiling** | 28400 0020 - MOUNTING KIT ENTERO RD-M O.F.A. | Required |
|  **Plasterboard** | 28400 0020 - MOUNTING KIT ENTERO RD-M O.F.A. | Required |
|  **Stucanet** | 28400 0020 - MOUNTING KIT ENTERO RD-M O.F.A. | Required |
|  **Concrete + plaster** | 28400 0020 - MOUNTING KIT ENTERO RD-M O.F.A. | Required |
|  **Lintel + plaster** | 28400 0020 - MOUNTING KIT ENTERO RD-M O.F.A. | Required |
|  **Hollow-core slab + plaster** | 28400 0020 - MOUNTING KIT ENTERO RD-M O.F.A. | Required |
|  **Stretched ceiling** | 28400 0080 - MOUNTING KIT ENTERO RD-M CSC | Required |
| | 28400 0140 - MOUNTING KIT ENTERO RD-M WSC | Required |

## FINISH YOUR SPECIFICATION

### Emergency units




**21032 0270 B** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B

**Cutout dimension (mm): 27**


**21032 0270 W** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W

### LED power supplies

**# of Fixtures**

ⓘ # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the '|' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.

**Min current | Max current**





**300 48 350 ED1** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 — 2

**Dimtype: 1-10V**

**Cutout dimension (mm): 30**

# ENTERO RD-M TRIMLESS WALLWASH 930


28433 9300 B




**300 48 350 ED5** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 — 2

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 350 MDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL — 2

**Dimtype: non-dimmable**


**Cutout dimension (mm): 30**




**300 48 350 WDL** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL — 2

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 45**




**300 48 500 ED1** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 — 2

**Dimtype: 1-10V**


**Cutout dimension (mm): 30**




**300 48 500 ED5** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 — 2

**Dimtype: DALI**


**Cutout dimension (mm): 45**




**300 48 500 MDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL — 2

**Dimtype: non-dimmable**


**Cutout dimension (mm): 30**




**300 48 500 WDL** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL — 2

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 45**




**300 90 61** LED POWER SUPPLY MULTI-POWER DIM6 — 2 | 2

**Dimtype: mains (phase cut-off) or push button**


**Cutout dimension (mm): 56**




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9 — 4(4) | 4(4) | 4(3)

**Dimtype: 1-10V or DALI or push button**

**Cutout dimension (mm): 82**





**300 90 64** LED POWER SUPPLY MULTI-POWER DIM7 — 2(2) | 2(1)

**Dimtype: 1-10V or push button**

**Cutout dimension (mm): 72**


# ENTERO RD-M TRIMLESS WALLWASH 930

28433 9300 B




**300 90 67** LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9 2 | -


**Dimtype: 1-10V or DALI or push button**




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5 2(2) | 2(1) | 2(1)

**Dimtype: DALI**


**Cutout dimension (mm): 72**




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9 2->6(6) | 6(4) | 4(3)

**Dimtype: 1-10V or DALI or push button**


**Cutout dimension (mm): 84**




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7 3(2) | 2(1) | 1(1)

**Dimtype: 1-10V or push button**


**Cutout dimension (mm): 55**




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5 2(2) | 2(1) | 1(1)

**Dimtype: DALI**


**Cutout dimension (mm): 55**




**300 90 135** LED POWER SUPPLY MULTI-POWER HV 3->4 | 2->4

**Dimtype: non-dimmable**


**Cutout dimension (mm): 90**




**21012 0010** LED POWER SUPPLY MULTI POWER 2 | 2 | 2

**Dimtype: non-dimmable**


**Cutout dimension (mm): 50**




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1 3 | 3

**Dimtype: 1-10V**


**Cutout dimension (mm): 54**




**21012 0035** LED POWER SUPPLY MULTI POWER DIM5 3 | 3

**Dimtype: DALI**

**Cutout dimension (mm): 54**





**21012 004W** LED POWER SUPPLY MULTI-POWER WDL 4(4) | 3(3)

**Dimtype: WDL = wireless dimmable**

**Cutout dimension (mm): 84**

# ENTERO RD-M TRIMLESS WALLWASH 930


28433 9300 B




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL — 3 | 3

**Dimtype: WDL = wireless dimmable**


**Cutout dimension (mm): 54**




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8 — 2->2 | 0 | 0

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 50**




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8 — 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8 — 2->3 | 2->2

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 55**




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8 — 2 | 2 | 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 48**




**21012 0308** LED POWER SUPPLY 350mA / 7,35W DIM8 — 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 40**




**21012 0318** LED POWER SUPPLY 500mA / 10W DIM8 — 1

**Dimtype: mains (phase cut-off)**


**Cutout dimension (mm): 40**




**21012 0480** LED POWER SUPPLY 350mA-DC / 17W IP68 — 2(2)

**Dimtype: non-dimmable**


**Cutout dimension (mm): 60**




**21012 0490** LED POWER SUPPLY 700mA-DC / 30W IP68 — 2(1)

**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**




**21012 0500** LED POWER SUPPLY 500mA-DC / 24W IP68 — 2(1)


**Dimtype: non-dimmable**

**Cutout dimension (mm): 60**

DELTALIGHT

# ENTERO RD-M TRIMLESS WALLWASH 930


28433 9300 B




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 2

**Dimtype: DALI**

**Cutout dimension (mm): 30**





**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 2

**Dimtype: DALI**

**Cutout dimension (mm): 30**


## Mounting kits




**28400 0020** MOUNTING KIT ENTERO RD-M O.F.A.

**Cutout dimension (mm): 127**

## Mounting kits stretched ceiling




**28400 0080** MOUNTING KIT ENTERO RD-M CSC




**28400 0140** MOUNTING KIT ENTERO RD-M WSC

Notes: