



## ENTERO RD-L WALLWASH 927



28474 9200 W

AVAILABLE IN

**BLACK** 28474 9200 B

**GOLD COLOURED** 28474 9200 GC

**WHITE** 28474 9200 W



[View on website](#)



### General info

|                                           |                                                          |
|-------------------------------------------|----------------------------------------------------------|
| <b>LOCATION</b>                           | indoor                                                   |
| <b>INSTALLATION</b>                       | Ceiling Recessed                                         |
| <b>CUTOUT SHAPE/SIZE (MM)</b>             | round - 112                                              |
| <b>RECESSED DEPTH (MM)</b>                | 160                                                      |
| <b>THICKNESS OF MOUNTING SURFACE (MM)</b> | max.16                                                   |
| <b>INGRESS PROTECTION</b>                 | IP20                                                     |
| <b>WEIGHT (KG)</b>                        | 0.5                                                      |
| <b>ADJUSTABILITY</b>                      | non adjustable                                           |
| <b>INFORMATION</b>                        | REFLECTOR WALLWASH<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | D                         |
| <b>CERTIFICATES</b> | CB, ENEC, EPD             |

### Lightsource info

|                                    |                                                              |
|------------------------------------|--------------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                          |
| <b>LIGHTSOURCE</b>                 | LED array 11,3-16,4W / CRI>90 (R9: 60) / 2700K / 1561-2195lm |
| <b>TM-30 VALUES</b>                | rf: 89 / Rg: 100                                             |
| <b>SDCM</b>                        | SDCM1                                                        |
| <b>RISKGROUP</b>                   | RG1                                                          |
| <b>LM80</b>                        | L90B10 > 50000                                               |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 2195lm // 16,4W // 134lm/W                                   |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 1806lm // 18,9W // 96lm/W                                    |

### Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

### Options

ENTERO RD-L MOUNTING SET S2

For detailed installation instructions, please consult the manual : [28474\\_XXX0\\_HAND.pdf](#)



ENTERO RD-L WALLWASH 927

28474 9200 W

CEILING COMPATIBILITY

| Ceiling Type                                                                                                  | Mounting Kit                                                                                                                                       |
|---------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
|  System ceiling               | -                                                                                                                                                  |
|  Plasterboard                 | -                                                                                                                                                  |
|  Stucanet                     | -                                                                                                                                                  |
|  Wood                         | -                                                                                                                                                  |
|  Concrete                     |  28500 0210 - ENTERO RD-L MOUNTING SET S2 <span>Required</span>   |
|  Concrete + plaster          |  28500 0210 - ENTERO RD-L MOUNTING SET S2 <span>Required</span>   |
|  Lintel + plaster           |  28500 0210 - ENTERO RD-L MOUNTING SET S2 <span>Required</span> |
|  Hollow-core slab           |  28500 0210 - ENTERO RD-L MOUNTING SET S2 <span>Required</span> |
|  Hollow-core slab + plaster |  28500 0210 - ENTERO RD-L MOUNTING SET S2 <span>Required</span> |
|  Stretched ceiling          | -                                                                                                                                                  |

FINISH YOUR SPECIFICATION

| LED power supplies                                                                                                                                                                                                                                                                                                                                                 | # of Fixtures          |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------|
| <div><div> # of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</div></div> |                        |
| <div><div></div><div><div><b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1</div><div>Dimtype: 1-10V</div><div>Cutout dimension (mm): 30</div></div></div>                                                                                                | 1 <input type="text"/> |
| <div><div></div><div><div><b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5</div><div>Dimtype: DALI</div><div>Cutout dimension (mm): 45</div></div></div>                                                                                                 | 1 <input type="text"/> |






ENTERO RD-L WALLWASH 927

28474 9200 W

|                                                                                    |                                                                          |             |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |             |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |             |                          |
|    | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |             |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |             |                          |
|    | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V                                                           |             |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |             |                          |
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |             |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |             |                          |
|  | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |             |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |             |                          |
|  | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |             |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |             |                          |
|  | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 1   1       | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |             |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |             |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 2(2)   2(2) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |             |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |             |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 1(1)   1(0) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |             |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |             |                          |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9    | 1           | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |             |                          |








ENTERO RD-L WALLWASH 927

28474 9200 W


|                                                                                    |                                                                                                                                        |             |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------|-------------|--------------------------|
|    | <b>300 90 68</b><br>LED POWER SUPPLY MULTI-POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 72                            | 1(1)   1(0) | <input type="checkbox"/> |
|    | <b>300 90 69</b><br>LED POWER SUPPLY MULTI-POWER HV DIM9<br><br>Dimtype: 1-10V or DALI or push button<br><br>Cutout dimension (mm): 84 | 3(3)   3(2) | <input type="checkbox"/> |
|    | <b>300 90 124</b><br>LED POWER SUPPLY MULTI-POWER DIM7<br><br>Dimtype: 1-10V or push button<br><br>Cutout dimension (mm): 55           | 1(1)   1(0) | <input type="checkbox"/> |
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 55                      | 1(1)   1(0) | <input type="checkbox"/> |
|  | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br><br>Dimtype: non-dimmable<br><br>Cutout dimension (mm): 90                     | 2->2   2    | <input type="checkbox"/> |
|  | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><br>Dimtype: non-dimmable<br><br>Cutout dimension (mm): 50                        | 1   1       | <input type="checkbox"/> |
|  | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><br>Dimtype: 1-10V<br><br>Cutout dimension (mm): 54                          | 1   1       | <input type="checkbox"/> |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 54                           | 1   1       | <input type="checkbox"/> |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 84         | 2(2)   2(2) | <input type="checkbox"/> |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 54 | 1   1       | <input type="checkbox"/> |

ENTERO RD-L WALLWASH 927

28474 9200 W

|                                                                                    |                                                                      |       |                          |
|------------------------------------------------------------------------------------|----------------------------------------------------------------------|-------|--------------------------|
|    | <b>21012 0268</b> LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8    | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 50                                                          |                                                                      |       |                          |
|    | <b>21012 0288</b> LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8    | 1     | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 55                                                          |                                                                      |       |                          |
|    | <b>21012 0298</b> LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8    | 1   1 | <input type="checkbox"/> |
| Dimtype: mains (phase cut-off)                                                     |                                                                      |       |                          |
| Cutout dimension (mm): 48                                                          |                                                                      |       |                          |
|    | <b>21012 0480</b> LED POWER SUPPLY 350mA-DC / 17W IP68               | 1(1)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21012 0500</b> LED POWER SUPPLY 500mA-DC / 24W IP68               | 1(0)  | <input type="checkbox"/> |
| Dimtype: non-dimmable                                                              |                                                                      |       |                          |
| Cutout dimension (mm): 60                                                          |                                                                      |       |                          |
|  | <b>21032 0295</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 1     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |
|  | <b>21032 0305</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 1     | <input type="checkbox"/> |
| Dimtype: DALI                                                                      |                                                                      |       |                          |
| Cutout dimension (mm): 30                                                          |                                                                      |       |                          |

Mounting set S2

|                                                                                     |                                               |  |                          |
|-------------------------------------------------------------------------------------|-----------------------------------------------|--|--------------------------|
|  | <b>28500 0210</b> ENTERO RD-L MOUNTING SET S2 |  | <input type="checkbox"/> |
|-------------------------------------------------------------------------------------|-----------------------------------------------|--|--------------------------|

Notes:

# DELTALIGHT

## **ENTERO RD-L WALLWASH 927**

28474 9200 W