



## SPM20 - SPY 392 AIR 92720

29813 9220 FBR

AVAILABLE IN



**BLACK** 29813 9220 B

**FLEMISH BRONZE** 29813 9220 FBR

**FLEMISH GOLD** 29813 9220 FG

**GOLD COLOURED** 29813 9220 GC

**WHITE** 29813 9220 W



[View on website](#)



### General info

|                               |                                                        |
|-------------------------------|--------------------------------------------------------|
| <b>LOCATION</b>               | indoor                                                 |
| <b>INSTALLATION</b>           | Ceiling Recessed                                       |
| <b>CUTOUT SHAPE/SIZE (MM)</b> | rectangle - KIT                                        |
| <b>INGRESS PROTECTION</b>     | IP20                                                   |
| <b>WEIGHT (KG)</b>            | 0.5                                                    |
| <b>ADJUSTABILITY</b>          | 0° to 85° swiveling, 355° rotatable                    |
| <b>INFORMATION</b>            | REFLECTOR FL-20°<br>EXCL.LED POWER SUPPLY 350-500mA-DC |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | E                         |

### Lightsource info

|                                    |                                                                 |
|------------------------------------|-----------------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                             |
| <b>LIGHTSOURCE</b>                 | 2 x (LED array 5,8-8,6W / CRI>90 (R9: 60) / 2700K / 753-1041lm) |
| <b>TM-30 VALUES</b>                | rf: 89 / Rg: 100                                                |
| <b>SDCM</b>                        | SDCM1                                                           |
| <b>RISKGROUP</b>                   | RG1                                                             |
| <b>LM80</b>                        | L90B10 > 50000                                                  |
| <b>BEAMANGLE</b>                   | 20°                                                             |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 2082lm // 17,2W // 121lm/W                                      |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 1697lm // 19,8W // 86lm/W                                       |

### Requirements

SPM20 - AIR KIT 1

SPY 39 TUBE or VISOR 39

LED POWER SUPPLY 350 / 500mA-DC DIM

For detailed installation instructions, please consult the manual : [29813\\_XXX0\\_HAND.pdf](#)

SPM20 - SPY 392 AIR 92720


29813 9220 FBR

CEILING COMPATIBILITY

| Ceiling Type                                                                     | Mounting Kit                                                                                                                           |
|----------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------|
|  |  29810 1010 - SPM20 - AIR KIT 1 <span>Required</span> |






FINISH YOUR SPECIFICATION

AIR kit for M20

|                                                                                  |                                                              |
|----------------------------------------------------------------------------------|--------------------------------------------------------------|
|  | <b>29810 1010</b> SPM20 - AIR KIT 1 <input type="checkbox"/> |
| Cutout dimension (mm): 50 x 310                                                  |                                                              |











LED power supplies

# of Fixtures

|                                                                                                                                                                                                                                                                                                                                           |                                                                          |   |                           |  |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------|---|---------------------------|--|
|  # of fixtures indicates how many devices can be connected (min -> max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V. |                                                                          |   | Min current   Max current |  |
|                                                                                                                                                                                                                                                         | <b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1 | 1 | <input type="checkbox"/>  |  |
| Dimtype: 1-10V                                                                                                                                                                                                                                                                                                                            |                                                                          |   |                           |  |
| Cutout dimension (mm): 30                                                                                                                                                                                                                                                                                                                 |                                                                          |   |                           |  |
|                                                                                                                                                                                                                                                         | <b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5 | 1 | <input type="checkbox"/>  |  |
| Dimtype: DALI                                                                                                                                                                                                                                                                                                                             |                                                                          |   |                           |  |
| Cutout dimension (mm): 45                                                                                                                                                                                                                                                                                                                 |                                                                          |   |                           |  |
|                                                                                                                                                                                                                                                         | <b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL  | 1 | <input type="checkbox"/>  |  |
| Dimtype: non-dimmable                                                                                                                                                                                                                                                                                                                     |                                                                          |   |                           |  |
| Cutout dimension (mm): 30                                                                                                                                                                                                                                                                                                                 |                                                                          |   |                           |  |
|                                                                                                                                                                                                                                                         | <b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL  | 1 | <input type="checkbox"/>  |  |
| Dimtype: WDL = wireless dimmable                                                                                                                                                                                                                                                                                                          |                                                                          |   |                           |  |
| Cutout dimension (mm): 45                                                                                                                                                                                                                                                                                                                 |                                                                          |   |                           |  |
|                                                                                                                                                                                                                                                         | <b>300 48 500 ED1</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM1 | 1 | <input type="checkbox"/>  |  |
| Dimtype: 1-10V                                                                                                                                                                                                                                                                                                                            |                                                                          |   |                           |  |
| Cutout dimension (mm): 30                                                                                                                                                                                                                                                                                                                 |                                                                          |   |                           |  |











SPM20 - SPY 392 AIR 92720

29813 9220 FBR

|                                                                                    |                                                                          |               |                          |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------|---------------|--------------------------|
|    | <b>300 48 500 ED5</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5 | 1             | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |               |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |               |                          |
|    | <b>300 48 500 MDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W MDL  | 1             | <input type="checkbox"/> |
|                                                                                    | Dimtype: non-dimmable                                                    |               |                          |
|                                                                                    | Cutout dimension (mm): 30                                                |               |                          |
|    | <b>300 48 500 WDL</b> LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W WDL  | 1             | <input type="checkbox"/> |
|                                                                                    | Dimtype: WDL = wireless dimmable                                         |               |                          |
|                                                                                    | Cutout dimension (mm): 45                                                |               |                          |
|    | <b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6                       | 1   1         | <input type="checkbox"/> |
|                                                                                    | Dimtype: mains (phase cut-off) or push button                            |               |                          |
|                                                                                    | Cutout dimension (mm): 56                                                |               |                          |
|  | <b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9                       | 2(2)   2(2)   | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |               |                          |
|                                                                                    | Cutout dimension (mm): 82                                                |               |                          |
|  | <b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7                       | 1(1)   1(1/2) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |               |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |               |                          |
|  | <b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9    | 1   -         | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |               |                          |
|  | <b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5                       | 1(1)   1(1/2) | <input type="checkbox"/> |
|                                                                                    | Dimtype: DALI                                                            |               |                          |
|                                                                                    | Cutout dimension (mm): 72                                                |               |                          |
|  | <b>300 90 69</b> LED POWER SUPPLY MULTI-POWER HV DIM9                    | 3(3)   3(2)   | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or DALI or push button                                    |               |                          |
|                                                                                    | Cutout dimension (mm): 84                                                |               |                          |
|  | <b>300 90 124</b> LED POWER SUPPLY MULTI-POWER DIM7                      | 1(1)   1(1/2) | <input type="checkbox"/> |
|                                                                                    | Dimtype: 1-10V or push button                                            |               |                          |
|                                                                                    | Cutout dimension (mm): 55                                                |               |                          |

SPM20 - SPY 392 AIR 92720








29813 9220 FBR

|                                                                                    |                                                                                                                                             |                                        |
|------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------|
|    | <b>300 90 125</b><br>LED POWER SUPPLY MULTI-POWER MINI DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 55                           | 1(1)   1(1/2) <input type="checkbox"/> |
|    | <b>300 90 135</b><br>LED POWER SUPPLY MULTI-POWER HV<br><br>Dimtype: non-dimmable<br><br>Cutout dimension (mm): 90                          | 2   2 <input type="checkbox"/>         |
|    | <b>21012 0010</b><br>LED POWER SUPPLY MULTI POWER<br><br>Dimtype: non-dimmable<br><br>Cutout dimension (mm): 50                             | 1   1 <input type="checkbox"/>         |
|    | <b>21012 0021</b><br>LED POWER SUPPLY MULTI POWER DIM1<br><br>Dimtype: 1-10V<br><br>Cutout dimension (mm): 54                               | 1   1 <input type="checkbox"/>         |
|  | <b>21012 0035</b><br>LED POWER SUPPLY MULTI POWER DIM5<br><br>Dimtype: DALI<br><br>Cutout dimension (mm): 54                                | 1   1 <input type="checkbox"/>         |
|  | <b>21012 004W</b><br>LED POWER SUPPLY MULTI-POWER WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 84              | 2(2)   1(1) <input type="checkbox"/>   |
|  | <b>21012 005W</b><br>LED POWER SUPPLY MULTI-POWER COMPACT WDL<br><br>Dimtype: WDL = wireless dimmable<br><br>Cutout dimension (mm): 54      | 1   1 <input type="checkbox"/>         |
|  | <b>21012 0268</b><br>LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 50 | 1   - <input type="checkbox"/>         |
|  | <b>21012 0278</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 55 | 1/2 <input type="checkbox"/>           |
|  | <b>21012 0288</b><br>LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8<br><br>Dimtype: mains (phase cut-off)<br><br>Cutout dimension (mm): 55 | 1 <input type="checkbox"/>             |


# DELTALIGHT

## SPM20 - SPY 392 AIR 92720

29813 9220 FBR

|                                                                                    |                                                                                                                                         |        |                          |
|------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|--------|--------------------------|
|    | <b>21012 0298</b><br>LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 48 | 1   1  | <input type="checkbox"/> |
|    | <b>21012 0308</b><br>LED POWER SUPPLY 350mA / 7,35W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40             | 1/2    | <input type="checkbox"/> |
|    | <b>21012 0318</b><br>LED POWER SUPPLY 500mA / 10W DIM8<br><br>Dimtype: mains (phase cut-off)<br>Cutout dimension (mm): 40               | 1/2    | <input type="checkbox"/> |
|    | <b>21012 0480</b><br>LED POWER SUPPLY 350mA-DC / 17W IP68<br><br>Dimtype: non-dimmable<br>Cutout dimension (mm): 60                     | 1(1)   | <input type="checkbox"/> |
|  | <b>21012 0500</b><br>LED POWER SUPPLY 500mA-DC / 24W IP68<br><br>Dimtype: non-dimmable<br>Cutout dimension (mm): 60                     | 1(1/2) | <input type="checkbox"/> |
|  | <b>21032 0295</b><br>LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30               | 1      | <input type="checkbox"/> |
|  | <b>21032 0305</b><br>LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5<br><br>Dimtype: DALI<br>Cutout dimension (mm): 30               | 1      | <input type="checkbox"/> |

### Light altering devices


|                                                                                    |                                |  |                          |
|------------------------------------------------------------------------------------|--------------------------------|--|--------------------------|
|  | <b>24144 0030 B</b> VISOR 39 B |  | <input type="checkbox"/> |
|------------------------------------------------------------------------------------|--------------------------------|--|--------------------------|

# DELTALIGHT

## SPM20 - SPY 392 AIR 92720

29813 9220 FBR

### Finish your product

|                                                                                    |                              |                 |                          |
|------------------------------------------------------------------------------------|------------------------------|-----------------|--------------------------|
|    | <b><u>24144 0010 B</u></b>   | SPY 39 TUBE B   | <input type="checkbox"/> |
|                                                                                    | <b><u>24144 0010 FBR</u></b> | SPY 39 TUBE FBR | <input type="checkbox"/> |
|                                                                                    | <b><u>24144 0010 FG</u></b>  | SPY 39 TUBE FG  | <input type="checkbox"/> |
|                                                                                    | <b><u>24144 0010 GC</u></b>  | SPY 39 TUBE GC  | <input type="checkbox"/> |
|                                                                                    | <b><u>24144 0010 W</u></b>   | SPY 39 TUBE W   | <input type="checkbox"/> |
|  | <b><u>24144 0070</u></b>     | SPY 39 TUBE SBL | <input type="checkbox"/> |

Notes: