



## INFORM R4 C DOWN-UP 93048

26826 9320 FG-B

AVAILABLE IN



**BLACK-BLACK** 26826 9320 B-B

**BLACK-FLEMISH GOLD** 26826 9320 B-FG

**FLEMISH GOLD-BLACK** 26826 9320 FG-B

**WHITE-BLACK** 26826 9320 W-B

**WHITE-WHITE** 26826 9320 W-W



[View on website](#)



### General info

|                           |                                                                                                                                                                        |
|---------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>LOCATION</b>           | indoor                                                                                                                                                                 |
| <b>INSTALLATION</b>       | Ceiling Suspended                                                                                                                                                      |
| <b>INGRESS PROTECTION</b> | IP20                                                                                                                                                                   |
| <b>WEIGHT (KG)</b>        | 2.2                                                                                                                                                                    |
| <b>ADJUSTABILITY</b>      | non adjustable                                                                                                                                                         |
| <b>INFORMATION</b>        | 96 x REFLECTOR WFL-71° (DOWN)<br>EXCL.2 x LED POWER SUPPLY 700mA-DC (DOWN/UP)<br>INCL.3 x CABLE SUSPENSION SINGLE AUTO. 1,6m<br>INCL.1 x CABLE 5 x 0.75mm <sup>2</sup> |

### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | C                         |
| <b>CERTIFICATES</b> | CB, ENEC                  |

### Lightsource info

|                                    |                                                                                                                        |
|------------------------------------|------------------------------------------------------------------------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                                                                                    |
| <b>LIGHTSOURCE</b>                 | DOWN: LED cluster 22,9W / CRI>90 (R9: 50) / 3000K / 3504lm<br>UP: LED cluster 11,5W / CRI>90 (R9: 50) / 3000K / 1752lm |
| <b>SDCM</b>                        | SDCM3                                                                                                                  |
| <b>LM80</b>                        | L80 > 60000                                                                                                            |
| <b>BEAMANGLE</b>                   | 71°                                                                                                                    |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | DOWN: 3504lm // 22,9W // 153lm/W<br>UP: 1752lm // 11,5W // 153lm/W                                                     |
| <b>LED TECHNICS (LUMINAIRE)</b>    | DOWN: 2800lm // 26,3W // 106lm/W<br>UP: 1121lm // 13,2W // 85lm/W                                                      |

### Requirements

LED POWER SUPPLY 700mA-DC DIM (Remote)  
INFORM R POWERBOX D/U DIM5


### Options

CABLE BASE R / S  
COVERSET R 62-90-100 / S 62-80-90  
CONNECTION ST / CONNECTION TRIMLESS  
SUSPENSION ST / SUSPENSION TRIMLESS

For detailed installation instructions, please consult the manual : [26826\\_XXX0\\_HAND.pdf](#)


FINISH YOUR SPECIFICATION






Current supply

|                                                                                    |                                       |                          |
|------------------------------------------------------------------------------------|---------------------------------------|--------------------------|
|    | <b>203 99 55 ANO</b> CABLE BASE R ANO | <input type="checkbox"/> |
|                                                                                    | <b>203 99 55 B</b> CABLE BASE R B     | <input type="checkbox"/> |
|                                                                                    | <b>203 99 55 W</b> CABLE BASE R W     | <input type="checkbox"/> |
|  | <b>203 99 56 ANO</b> CABLE BASE S ANO | <input type="checkbox"/> |
|                                                                                    | <b>203 99 56 B</b> CABLE BASE S B     | <input type="checkbox"/> |
|                                                                                    | <b>203 99 56 W</b> CABLE BASE S W     | <input type="checkbox"/> |

Power box

# of Fixtures


|                                                                                                                                                                                                                                                                                                                                                                              |                                                  |                            |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------|----------------------------|
| <div><div></div><div># of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</div></div> |                                                  | Min current   Max current  |
|                                                                                                                                                                                                                                                                                            | <b>26810 0025 B</b> INFORM R POWERBOX D/U DIM5 B | 1 <input type="checkbox"/> |
| Dimtype: DALI                                                                                                                                                                                                                                                                                                                                                                |                                                  |                            |
|                                                                                                                                                                                                                                                                                                                                                                              | <b>26810 0025 W</b> INFORM R POWERBOX D/U DIM5 W | 1 <input type="checkbox"/> |

| LED power supplies                                                                                                                                                                                                                                                                                                                                                         |               | # of Fixtures             |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------|---------------------------|
| <div><div></div><div># of fixtures indicates how many devices can be connected (min -&gt; max) to the power supply. The values before and after the ' ' correspond respectively with the minimum and maximum driving current. Values between brackets are applicable to 110V.</div></div> |               | Min current   Max current |
| <div><div></div><div><div><b>300 90 64</b></div><div>LED POWER SUPPLY MULTI-POWER DIM7</div></div></div>                                                                                                                                                                                   | 1 down   1 up | <input type="checkbox"/>  |
| <div><div>Dimtype: 1-10V or push button</div><div>Cutout dimension (mm): 72</div></div>                                                                                                                                                                                                                                                                                    |               |                           |
| <div><div></div><div><div><b>300 90 68</b></div><div>LED POWER SUPPLY MULTI-POWER DIM5</div></div></div>                                                                                                                                                                                   | 1 down   1 up | <input type="checkbox"/>  |
| <div><div>Dimtype: DALI</div><div>Cutout dimension (mm): 72</div></div>                                                                                                                                                                                                                                                                                                    |               |                           |
| Coversets                                                                                                                                                                                                                                                                                                                                                                  |               |                           |
| <div><div></div><div><div><b>204 00 62 ANO</b></div><div>COVERSET R 62 ANO</div></div></div>                                                                                                                                                                                             |               | <input type="checkbox"/>  |
| <div><div><b>204 00 62 B</b></div><div>COVERSET R 62 B</div></div>                                                                                                                                                                                                                                                                                                         |               | <input type="checkbox"/>  |
| <div><div><b>204 00 62 W</b></div><div>COVERSET R 62 W</div></div>                                                                                                                                                                                                                                                                                                         |               | <input type="checkbox"/>  |
| <div><div></div><div><div><b>204 00 90 ANO</b></div><div>COVERSET R 90 ANO</div></div></div>                                                                                                                                                                                             |               | <input type="checkbox"/>  |
| <div><div><b>204 00 90 B</b></div><div>COVERSET R 90 B</div></div>                                                                                                                                                                                                                                                                                                         |               | <input type="checkbox"/>  |
| <div><div><b>204 00 90 W</b></div><div>COVERSET R 90 W</div></div>                                                                                                                                                                                                                                                                                                         |               | <input type="checkbox"/>  |
| <div><div></div><div><div><b>204 00 100 ANO</b></div><div>COVERSET R 100 ANO</div></div></div>                                                                                                                                                                                           |               | <input type="checkbox"/>  |
| <div><div><b>204 00 100 B</b></div><div>COVERSET R 100 B</div></div>                                                                                                                                                                                                                                                                                                       |               | <input type="checkbox"/>  |
| <div><div><b>204 00 100 W</b></div><div>COVERSET R 100 W</div></div>                                                                                                                                                                                                                                                                                                       |               | <input type="checkbox"/>  |

# DELTALIGHT

## INFORM R4 C DOWN-UP 93048

26826 9320 FG-B




**204 62 62 ANO** COVERSET S 62 ANO

☐

**204 62 62 B** COVERSET S 62 B

☐

**204 62 62 W** COVERSET S 62 W

☐


**204 80 80 ANO** COVERSET S 80 ANO

☐

**204 80 80 B** COVERSET S 80 B

☐

**204 80 80 W** COVERSET S 80 W

☐

**204 90 90 ANO** COVERSET S 90 ANO

☐


**204 90 90 B** COVERSET S 90 B

☐

**204 90 90 W** COVERSET S 90 W

☐


### Suspension parts



**328 10 01** SUSPENSION TRIMLESS O.F.A.

☐

Cutout dimension (mm): 62 (CONCRETE: 102)



**15225 0340 B** SUSPENSION ST B


☐

Cutout dimension (mm): 27

**15225 0340 W** SUSPENSION ST W

☐

### Electric connection parts

|                                                                                   |                                             |                          |
|-----------------------------------------------------------------------------------|---------------------------------------------|--------------------------|
|   | <b>328 10 03</b> CONNECTION TRIMLESS O.F.A. | <input type="checkbox"/> |
| Cutout dimension (mm): 62 (CONCRETE: 102)                                         |                                             |                          |
|  | <b>15225 0360 B</b> CONNECTION ST B         | <input type="checkbox"/> |
| Cutout dimension (mm): 43                                                         |                                             |                          |
|                                                                                   | <b>15225 0360 W</b> CONNECTION ST W         | <input type="checkbox"/> |

Notes: